ANSI/NEMA IA 2.3-1994 (R2002)

PROGRAMMABLE CONTROLLERS – PROGRAMMING LANGUAGES

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale



ANSI Approval Date
May 1, 2002

NEMA Standards Publication ANSI/NEMA IA 2.3-1994 (R2002)

Programmable Controllers - Programming Languages

Published by:

National Electrical Manufacturers Association
1300 North 17th Street, Suite 1847
Rosslyn, VA 22209

www.nema.org

© Copyright 2002 by the National Electrical Manufacturers Association. All rights including translation into other languages, reserved under the Universal Copyright Convention, the Berne Convention for the Protection of Literary and Artistic Works, and the International and Pan American Copyright Conventions.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

NOTICE AND DISCLAIMER

The information in this publication was considered technically sound by the consensus of persons engaged in the development and approval of the document at the time it was developed. Consensus does not necessarily mean that there is unanimous agreement among every person participating in the development of this document.

The National Electrical Manufacturers Association (NEMA) standards and guideline publications, of which the document contained herein is one, are developed through a voluntary consensus standards development process. This process brings together volunteers and/or seeks out the views of persons who have an interest in the topic covered by this publication. While NEMA administers the process and establishes rules to promote fairness in the development of consensus, it does not write the document and it does not independently test, evaluate, or verify the accuracy or completeness of any information or the soundness of any judgments contained in its standards and guideline publications.

NEMA disclaims liability for any personal injury, property, or other damages of any nature whatsoever, whether special, indirect, consequential, or compensatory, directly or indirectly resulting from the publication, use of, application, or reliance on this document. NEMA disclaims and makes no guaranty or warranty, expressed or implied, as to the accuracy or completeness of any information published herein, and disclaims and makes no warranty that the information in this document will fulfill any of your particular purposes or needs. NEMA does not undertake to guarantee the performance of any individual manufacturer or seller's products or services by virtue of this standard or guide.

In publishing and making this document available, NEMA is not undertaking to render professional or other services for or on behalf of any person or entity, nor is NEMA undertaking to perform any duty owed by any person or entity to someone else. Anyone using this document should rely on his or her own independent judgment or, as appropriate, seek the advice of a competent professional in determining the exercise of reasonable care in any given circumstances. Information and other standards on the topic covered by this publication may be available from other sources, which the user may wish to consult for additional views or information not covered by this publication.

NEMA has no power, nor does it undertake to police or enforce compliance with the contents of this document. NEMA does not certify, test, or inspect products, designs, or installations for safety or health purposes. Any certification or other statement of compliance with any health or safety–related information in this document shall not be attributable to NEMA and is solely the responsibility of the certifier or maker of the statement.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

TABLE OF CONTENTS

Page

Foreword ii
Referenced Standards iv
Amendments v
IEC 1131-3 1

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

FOREWORD

This Standards Publication is a NEMA Adoptive Standard based on Part 3 of IEC 1131, "Programmable Controllers."

This Standards Publication was prepared by a technical committee of the NEMA Automation Products and Systems Section. It was approved in accordance with the bylaws of NEMA and supersedes NEMA Standards Publication ICS 3-1988, Part 3-304.

This Standards Publication provides practical information concerning ratings, construction, test, performance and manufacture of industrial control equipment. These standards are used by the electrical industry to provide guidelines for the manufacture and proper application of reliable products and equipment and to promote the benefits of repetitive manufacturing and widespread product availability.

NEMA Standards represent the result of many years of research, investigation and experience by the members of NEMA, its predecessors, its Sections and Committees. They have been developed through continuing consultation among manufacturers, users and national engineering societies and have resulted in improved serviceability of electrical products with economies to manufacturers and users.

One of the primary purposes of this Standards Publication is to encourage the production of reliable control equipment which, in itself, functions in accordance with these accepted standards. Some portions of these standards, such as electrical spacings and interrupting ratings, have a direct bearing on safety; almost all of the items in this publication, when applied properly, contribute to safety in one way or another.

Properly constructed industrial control equipment is, however, only one factor in minimizing the hazards which may be associated with the use of electricity. The reduction of hazard involves the joint efforts of the various equipment manufacturers, the system designer, the installer and the user. Information is provided herein to assist users and others in the proper selection of control equipment.

The industrial control manufacturer has limited or no control over the following factors which are vital to a safe installation:

a. environmental conditions
b. system design
c. equipment selection and application
d. installation
e. operating practices
f. maintenance

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

This publication is not intended to instruct the user of control equipment with regard to these factors except insofar as suitable equipment to meet needs can be recognized in this publication and some application guidance is given.

This Standards Publication is necessarily confined to defining the construction requirements for industrial control equipment and to providing recommendations for proper selection for use under normal or certain specific conditions. Since any piece of industrial control equipment can be installed, operated and maintained in such a manner that hazardous conditions may result, conformance with this publication does not by itself assure a safe installation. When, however, equipment conforming with these standards is properly selected and is installed in accordance with the National Electrical Code and properly maintained, the hazards to persons and property will be reduced.

To continue to serve the best interests of users, NEMA is actively cooperating with other standardization organizations in the development of simple and more universal metrology practices. In this Standards Publication, the U.S. customary units are gradually being supplemented by those of the modernized metric system known as the International Systems of Units (SI). This transition involves no changes in standard dimensions, tolerances, or performance specifications.

NEMA Standards Publications are subject to periodic review. They are revised frequently to reflect user input and to meet changing conditions and technical progress. Users should secure the latest editions. See the postal return card attached to the front cover of this Standards Publication for the proper procedure to obtain revision service for your copy of the publication.

Proposed revisions to this Standards Publication should be submitted to:

Engineering Department
National Electrical Manufacturers Association
2101 L Street, N.W.
Washington, DC 20037

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

REFERENCED STANDARDS

The following standard contains provisions which, through reference in this text, constitute provisions of this NEMA Standards Publication. At the time of publication, the edition indicated was valid. All standards are subject to revision, and parties to agreements based on this Standard are encouraged to investigate the possibility of applying the most recent edition of the standard indicated below.

International Electrotechnical Commission
1, rue de Varembé
Geneva, Switzerland

IEC 1131-3 — *Programmable Controllers • Part 3: Programming Languages*

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

AMENDMENTS

IEC 1131-3, "Programmable controllers • Part 3: Programming languages," is adopted in its entirety.
NEMA Adoptive Standard

Where a conflict exists between the provisions of IA 2.3 and other NEMA Standards Publications, the provisions of IA 2.3 shall govern in the area of programmable controllers and their associated peripherals.
NEMA Standard

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

NEMA IA*2.3 94 ■ 6470247 0506369 719 ■

NORME INTERNATIONALE
INTERNATIONAL STANDARD

CEI
IEC
1131-3

First edition
1993-03

Programmable controllers –

Part 3:
Programming languages

Automates programmables –

Partie 3:
Langages de programmation

Reference number
IEC 1131-3: 1993(E)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

NEMA IA*2.3 94 ■ 6470247 0506370 430 ■

NORME INTERNATIONALE
INTERNATIONAL STANDARD

CEI
IEC
1131-3

First edition
1993-03

Programmable controllers –

Part 3:
Programming languages

Automates programmables –

Partie 3:
Langages de programmation

© CEI 1993 Droits de reproduction réservés — Copyright – all rights reserved

Aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'éditeur

No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

Bureau Central de la Commission Electrotechnique Internationale 3, rue de Varembé Genève, Suisse

Commission Electrotechnique Internationale
International Electrotechnical Commission
Международная Электротехническая Комиссия

CODE PRIX
PRICE CODE XD

Pour prix, voir catalogue en vigueur
For price, see current catalogue

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

CONTENTS

Page

FOREWORD 7

Clause

1 General 9
1.1 Scope 9
1.2 Normative references 9
1.3 Definitions 10
1.4 Overview and general requirements 15
1.4.1 Software model 15
1.4.2 Communication model 17
1.4.3 Programming model 19
1.5 Compliance 21
1.5.1 Programmable controller systems 22
1.5.2 Programs 23

2 Common elements 24
2.1 Use of printed characters 24
2.1.1 Character set 24
2.1.2 Identifiers 25
2.1.3 Keywords 26
2.1.4 Use of spaces 26
2.1.5 Comments 26
2.2 External representation of data 26
2.2.1 Numeric literals 26
2.2.2 Character string literals 27
2.2.3 Time literals 28
2.3 Data types 30
2.3.1 Elementary data types 30
2.3.2 Generic data types 31
2.3.3 Derived data types 32
2.4 Variables 36
2.4.1 Representation 36
2.4.2 Initialization 38
2.4.3 Declaration 39
2.5 Program organization units 44
2.5.1 Functions 44
2.5.2 Function blocks 61
2.5.3 Programs 76

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

Clause Page

2.6 Sequential Function Chart (SFC) elements 77
2.6.1 General 77
2.6.2 Steps 77
2.6.3 Transition 79
2.6.4 Actions 83
2.6.5 Rules of evolution 92
2.6.6 Compatibility of SFC elements 101
2.6.7 Compliance requirements 101
2.7 Configuration elements 102
2.7.1 Configurations, resources, and access paths 103
2.7.2 Tasks 105

3 Textual languages 115

3.1 Common elements 115
3.2 Language IL (Instruction List) 115
3.2.1 Instructions 115
3.2.2 Operators, modifiers and operands 116
3.2.3 Functions and function blocks 117
3.3 Language ST (Structured Text) 118
3.3.1 Expressions 118
3.3.2 Statements 121

4 Graphic languages 124

4.1 Common elements 124
4.1.1 Representation of lines and blocks 124
4.1.2 Direction of flow in networks 125
4.1.3 Evaluation of networks 126
4.1.4 Execution control elements 128
4.2 Language LD (Ladder Diagram) 130
4.2.1 Power rails 130
4.2.2 Link elements and states 130
4.2.3 Contacts 131
4.2.4 Coils 131
4.2.5 Functions and function blocks 131
4.2.6 Order of network evaluation 131
4.3 Language FBD (Function Block Diagram) 134
4.3.1 General 134
4.3.2 Combination of elements 134
4.3.3 Order of network evaluation 134

Annexes

A Specification method for textual languages 135

A.1 Syntax 135
A.2 Semantics 137

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

NEMA IA*2.3 94 ■ 6470247 0506373 14T ■

Page

Annexes *(concluded)*

B Formal specifications of language elements 138

B.0 Programming model 138
B.1 Common elements 138
B.2 Language IL (Instruction List) 148
B.3 Language ST (Structured Text) 149

C Delimiters and keywords 151
D Implementation-dependent parameters 154
E Error conditions 156
F Examples 157

F.1 Function WEIGH 157
F.2 Function block CMD_MONITOR 158
F.3 Function block FWD_REV_MON 161
F.4 Function block STACK_INT 166
F.5 Function block MIX_2_BRIX 171
F.6 Analog signal processing 174
F.7 Program GRAVEL 183
F.8 Program AGV 191

G Index 195
H Software compliance testing 207

Tables

1 Character set features 25
2 Identifier features 25
3 Comment feature 26
4 Numeric literals 27
5 Character string literal feature 28
6 Two-character combinations in character strings 28
7 Duration literal features 29
8 Date and time of day literals 29
9 Examples of date and time of day literals 30
10 Elementary data types 31
11 Hierarchy of generic data types 32
12 Data type declaration features 34
13 Default initial values 34
14 Data type initial value declaration features 35
15 Location and size prefix features for directly represented variables 37
16 Variable declaration keywords 40
17 Variable type assignment features 41
18 Variable initial value assignment features 43
19 Graphical negation of Boolean signals 45
20 Use of EN input and ENO output 47
21 Typed and overloaded functions 49
22 Type conversion function features 52
23 Standard functions of one numeric variable 53
24 Standard arithmetic functions 54
25 Standard bit shift functions 55

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Clause Page

26 Standard bitwise Boolean functions 56
27 Standard selection functions 57
28 Standard comparison functions 58
29 Standard character string functions 59
30 Functions of time data types 60
31 Functions of enumerated data type 60
32 Examples of function block I/O parameter usage 62
33 Function block declaration features 65
34 Standard bistable function blocks 71
35 Standard edge detection function blocks 72
36 Standard counter function blocks 73
37 Standard timer function blocks 74
38 Standard timer function blocks – timing diagrams 75
39 Program declaration features 76
40 Step features 79
41 Transitions and transition conditions 81
42 Declaration of actions 84
43 Step/action association 86
44 Action block features 87
45 Action qualifiers 88
46 Sequence evolution 94
47 Compatible SFC features 101
48 SFC minimal compliance requirements 101
49 Configuration and resource declaration features 104
50 Task features 108
51 Examples of instruction fields 115
52 Instruction List (IL) operators 117
53 Function block invocation features for IL language 118
54 Standard function block input operators for IL language 118
55 Operators of the ST language 120
56 ST language statements 121
57 Representation of lines and blocks 126
58 Graphic execution control elements 129
59 Power rails 130
60 Link elements 131
61 Contacts 132
62 Coils 133

Figures

1 Software model 16
2 Communication model 18
3 Combination of programmable controller language elements 21
4 Examples of function usage 44
5 Use of formal parameter names 46
6 Examples of function declarations 48
7 Examples of explicit type conversion with overloaded functions 50
8 Examples of explicit type conversion with typed functions 52
9 Function block instantiation example 62
10 Examples of function block declarations 64
11 Graphical use of function block names as variables 66

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Clause Page

12 Examples of use of input/output variables 69
13 Semaphore usage example 70
14 ACTION_CONTROL function block – External interface 89
15 ACTION_CONTROL function block body 90
16 Action control example 91
17 SFC evolution rules 98
18 SFC errors 99
19 Configuration example 102
20 Examples of CONFIGURATION and RESSOURCE declaration features 105
21 Synchronization of function blocks 112
22 EXIT statement example 123
23 Feedback path example 128
24 Boolean OR examples 134

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

INTERNATIONAL ELECTROTECHNICAL COMMISSION

PROGRAMMABLE CONTROLLERS –

Part 3: Programming languages

FOREWORD

1) The formal decisions or agreements of the IEC on technical matters, prepared by technical committees on which all the National Committees having a special interest therein are represented, express, as nearly as possible, an international consensus of opinion on the subjects dealt with.

2) They have the form of recommendations for international use and they are accepted by the National Committees in that sense.

3) In order to promote international unification, the IEC expresses the wish that all National Committees should adopt the text of the IEC recommendation for their national rules in so far as national conditions will permit. Any divergence between the IEC recommendation and the corresponding national rules should, as far as possible, be clearly indicated in the latter.

This part of International Standard IEC 1131 has been prepared by sub-committee 65B: Devices, of IEC technical committee 65: Industrial-process measurement and control.

The text of this standard is based on the following documents:

DIS	Report on Voting
65B(CO)85	65B(CO)87

Full information on the voting for the approval of this standard can be found in the Voting Report indicated in the above table.

IEC 1131 will consist of the following parts, of which this is the third under the general title: Programmable controllers.

Part 1: 1992, General information.

Part 2: 1992, Equipment requirements and tests.

Part 3: 1993, Programming languages.

Part 4, User guidelines *(under consideration)*.

Part 5, Messaging service specification *(under consideration)*.

Annexes A, B, C, D and E form an integral part of this part of IEC 1131.
Annexes F, G and H are for information only.

A type 2 technical report (TR) will provide "pre-standardization" guidance for the implementation and application of the programming language defined in this part of IEC 1131, including such issues as operating system/program interaction and requirements for programming support environments.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

PROGRAMMABLE CONTROLLERS –

Part 3: Programming languages

1 General

1.1 *Scope*

This part of IEC 1131 applies to the printed and displayed representation, using characters of the ISO/IEC 646 character set, of the programming languages to be used for Programmable Controllers as defined in Part 1 of IEC 1131. Graphic and semigraphic representation of the language elements which are defined in this part is allowed, but is not defined in this part.

The functions of program entry, testing, monitoring, operating system, etc., are specified in Part 1 of IEC 1131.

1.2 *Normative references*

The following normative documents contain provisions which, through reference in this text, constitute provisions of this part of IEC 1131. At the time of publication, the editions indicated were valid. All normative documents are subject to revision, and parties to agreements based on this part of IEC 1131 are encouraged to investigate the possibility of applying the most recent editions of the normative documents indicated below. Members of IEC and ISO maintain registers of currently valid International Standards.

IEC 50: *International Electrotechnical Vocabulary (IEV)*

IEC 559: 1989, *Binary floating-point arithmetic for microprocessor systems*

IEC 617-12: 1991, *Graphical symbols for diagrams – Part 12: Binary logic elements*

IEC 617-13: 1978, *Graphical symbols for diagrams – Part 13: Analogue elements*

IEC 848: 1988, *Preparation of function charts for control systems*

ISO/AFNOR: 1989, *Dictionary of computer science, ISBN 2-12-486911-6*

ISO/IEC 646: 1991, *Information technology – ISO 7-bit coded character set for information processing interchange*

ISO 8601: 1988, *Data elements and interchange formats – Information interchange – Representations of dates and times*

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

ISO 7185: 1990, *Information technology – Programming languages – Pascal*

ISO 7498: 1984, *Information processing systems – Open systems interconnection – Basic reference model*

1.3 *Definitions*

For the purposes of this part of IEC 1131, the following definitions apply. Definitions applying to all parts of IEC 1131 are given in part 1.

NOTES

1 Terms defined in this subclause are italicized where they appear in the bodies of definitions.

2 The notation "(ISO)" following a definition indicates that the definition is taken from the ISO/AFNOR *Dictionary of computer science.*

3 The ISO/AFNOR *Dictionary of computer science* and the *International Electrotechnical Vocabulary* should be consulted for terms not defined in this standard.

1.3.1 **absolute time:** The combination of time of day and date information.

1.3.2 **access path:** The association of a symbolic name with a variable for the purpose of open communication.

1.3.3 **action:** A Boolean variable, or a collection of operations to be performed, together with an associated control structure, as specified in 2.6.4.

1.3.4 **action block:** A graphical language element which utilizes a Boolean input variable to determine the value of a Boolean output variable or the enabling condition for an *action*, according to a predetermined control structure as defined in 2.6.4.5.

1.3.5 **aggregate:** A structured collection of data objects, forming a *data type*. (ISO)

1.3.6 **argument:** Synonymous with *input parameter* or *output parameter*.

1.3.7 **array:** An *aggregate* that consists of data objects, with identical attributes, each of which may be uniquely referenced by *subscripting*. (ISO)

1.3.8 **assignment:** A mechanism to give a value to a variable or to an *aggregate*. (ISO)

1.3.9 **based number:** A number represented in a specified base other than ten.

1.3.10 **bistable function block:** *A function block* with two stable states controlled by one or more inputs.

1.3.11 **bit string:** A data element consisting of one or more bits.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

1.3.12 **body:** That portion of *a program organization unit* which specifies the operations to be performed on the declared *operands* of the program organization unit when its execution is *invoked.*

1.3.13 **call:** A language construct for *invoking* the execution of a *function* or *function block.*

1.3.14 **character string:** An *aggregate* that consists of an ordered sequence of characters.

1.3.15 **comment:** A language construct for the inclusion of text in a program and having no impact on the execution of the program. (ISO)

1.3.16 **compile:** To translate a *program organization unit* or *data type* specification into its machine language equivalent or an intermediate form.

1.3.17 **configuration:** A language element corresponding to a *programmable controller system* as defined in IEC 1131-1.

1.3.18 **counter function block:** A *function block* which accumulates a value for the number of changes sensed at one or more specified *inputs.*

1.3.19 **data type:** A set of values together with a set of permitted operations. (ISO)

1.3.20 **date and time:** The date within the year and the time of day, represented according to ISO 8601.

1.3.21 **declaration:** The mechanism for establishing the definition of a *language element.* A declaration normally involves attaching an identifier to the language element, and allocating attributes such as *data types* and algorithms to it.

1.3.22 **delimiter:** A character or combination of characters used to separate program *language elements.*

1.3.23 **direct representation:** A means of representing a variable in a programmable controller program from which a manufacturer-specified correspondence to a physical or *logical location* may be determined directly.

1.3.24 **double word:** A data element containing 32 bits.

1.3.25 **evaluation:** The process of establishing a value for an expression or a *function,* or for the *outputs* of a network or *function block,* during program execution.

1.3.26 **execution control element:** A *language element* which controls the flow of program execution.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

1.3.27 **falling edge:** The change from 1 to 0 of a Boolean variable.

1.3.28 **function:** A *program organization unit* which, when executed, yields exactly one data element (which may be multi-valued, e.g., an *array* or *structure*), and whose *invocation* can be used in textual languages as an *operand* in an expression.

1.3.29 **function block instance (function block):** An *instance* of a *function block type*.

1.3.30 **function block type:** A programmable controller programming *language element* consisting of: (i) the definition of a data structure partitioned into input, output, and internal variables; and (ii) a set of operations to be performed upon the elements of the data structure when an *instance* of the function block type is *invoked*.

1.3.31 **function block diagram:** One or more networks of graphically represented *functions*, *function blocks*, data elements, *labels*, and connective elements.

1.3.32 **generic data type:** A *data type* which represents more than one type of data, as specified in 2.3.2.

1.3.33 **global scope:** Scope of a declaration applying to all program organization units within a *resource* or *configuration*.

1.3.34 **global variable:** A variable whose *scope* is *global*.

1.3.35 **hierarchical addressing:** The *direct representation* of a data element as a member of a physical or logical hierarchy, e.g., a point within a module which is contained in a rack, which in turn is contained in a cubicle, etc.

1.3.36 **identifier:** A combination of letters, numbers, and underline characters, as specified in 2.1.2, which begins with a letter or underline and which names a *language element*.

1.3.37 **initial value:** The value assigned to a variable at system start-up.

1.3.38 **input parameter (input):** A parameter which is used to supply an argument to a *program organization unit*.

1.3.39 **instance:** An individual, named copy of the data structure associated with a *function block type* or *program type*, which persists from one *invocation* of the associated operations to the next.

1.3.40 **instance name:** An *identifier* associated with a specific *instance*.

1.3.41 **instantiation:** The creation of an *instance*.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

1.3.42 **integer literal:** A *literal* which directly represents a value of type SINT, INT, DINT, LINT, BOOL, BYTE, WORD, DWORD, or LWORD, as defined in 2.3.1.

1.3.43 **invocation:** The process of initiating the execution of the operations specified in a *program organization unit.*

1.3.44 **keyword:** A lexical unit that characterizes a *language element,* e.g., "IF".

1.3.45 **label:** A language construction naming an instruction, network, or group of networks, and including an *identifier.*

1.3.46 **language element:** Any item identified by a symbol on the left-hand side of a production rule in the formal specification given in annex B of this part of IEC 1131.

1.3.47 **literal:** A lexical unit that directly represents a value. (ISO)

1.3.48 **local scope:** The *scope* of a *declaration* or *label* applying only to the *program organization unit* in which the declaration or label appears.

1.3.49 **logical location:** The location of a *hierarchically addressed* variable in a schema which may or may not bear any relation to the physical structure of the programmable controller's inputs, outputs, and memory.

1.3.50 **long real:** A real number represented in a *long word.*

1.3.51 **long word:** A 64-bit data element.

1.3.52 **memory (user data storage):** A functional unit to which the user program can store data and from which it can retrieve the stored data.

1.3.53 **named element:** An element of a *structure* which is named by its associated *identifier.*

1.3.54 **off-delay (on-delay) timer function block:** A *function block* which delays the *falling (rising) edge* of a Boolean *input* by a specified duration.

1.3.55 **operand:** A *language element* on which an operation is performed.

1.3.56 **operator:** A symbol that represents the action to be performed in an operation.

1.3.57 **output parameter (output):** A *parameter* which is used to return the result(s) of the *evaluation* of a *program organization unit.*

1.3.58 **overloaded:** With respect to an operation or *function,* capable of operating on data of different types, as specified in 2.5.1.4.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

1.3.59 **power flow:** The symbolic flow of electrical power in a ladder diagram, used to denote the progression of a logic solving algorithm.

1.3.60 **program (verb):** To design, write, and test user programs.

1.3.61 **program organization unit:** A *function, function block*, or program.

NOTE - This term may refer to either a *type* or an *instance*.

1.3.62 **real literal:** A *literal* representing data of type REAL or LREAL.

1.3.63 **resource:** A *language element* corresponding to a "signal processing function" and its "man-machine interface" and "sensor and actuator interface functions", if any, as defined in IEC 1131-1.

1.3.64 **retentive data:** Data stored in such a way that its value remains unchanged after a power down / power up sequence.

1.3.65 **return:** A language construction within a *program organization unit* designating an end to the execution sequences in the unit.

1.3.66 **rising edge:** The change from 0 to 1 of a Boolean variable.

1.3.67 **scope:** That portion of a *language element* within which a *declaration* or *label* applies.

1.3.68 **semantics:** The relationships between the symbolic elements of a programming language and their meanings, interpretation and use.

1.3.69 **semigraphic representation:** Representation of graphic information by the use of a limited set of characters.

1.3.70 **single data element:** A data element consisting of a single value.

1.3.71 **step:** A situation in which the behavior of a *program organization unit* with respect to its *inputs* and *outputs* follows a set of rules defined by the associated *actions* of the step.

1.3.72 **structured data type:** An *aggregate* data type which has been declared using a STRUCT or FUNCTION_BLOCK declaration.

1.3.73 **subscripting:** A mechanism for referencing an *array* element by means of an array reference and one or more expressions that, when evaluated, denote the position of the element.

1.3.74 **symbolic representation:** The use of *identifiers* to name variables.

1.3.75 **task:** An *execution control element* providing for periodic or triggered execution of a group of associated *program organization units*.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

1.3.76 **time literal:** A *literal* representing data of type TIME, DATE, TIME_OF_DAY, or DATE_AND_TIME.

1.3.77 **transition:** The condition whereby control passes from one or more predecessor *steps* to one or more successor steps along a directed link.

1.3.78 **unsigned integer:** An *integer literal* not containing a leading plus (+) or minus (–) sign.

1.3.79 **wired OR:** A construction for achieving the Boolean OR function in the LD language by connecting together the right ends of horizontal connectives with vertical connectives.

1.4 *Overview and general requirements*

This part of IEC 1131 specifies the syntax and semantics of a unified suite of programming languages for programmable controllers (PCs). These consist of two textual languages, IL (Instruction List) and ST (Structured Text), and two graphical languages, LD (Ladder Diagram) and FBD (Function Block Diagram).

Sequential Function Chart (SFC) elements are defined for structuring the internal organization of programmable controller *programs* and *function blocks*. Also, *configuration elements* are defined which support the installation of programmable controller *programs* into programmable controller systems.

In addition, features are defined which facilitate communication among programmable controllers and other components of automated systems.


The programming language elements defined in this part may be used in an interactive programming environment. The specification of such environments is beyond the scope of this part; however, such an environment shall be capable of producing textual or graphic program documentation in the formats specified in this part.

The material in this part is arranged in "bottom-up" fashion, that is, simpler language elements are presented first, in order to minimize forward references in the text. The remainder of this subclause provides an overview of the material presented in this part and incorporates some general requirements.

1.4.1 *Software model*

The basic high-level language elements and their interrelationships are illustrated in figure 1. These consist of elements which are *programmed* using the languages defined in this part, that is, *programs* and *function blocks*; and *configuration elements*, namely, *configurations*, *resources*, *tasks*, *global variables*, and *access paths*, which support the installation of programmable controller *programs* into programmable controller systems.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale



NOTES

1 This figure is illustrative only. The graphical representation is not normative.

2 In a configuration with a single resource, the resource need not be explicitly represented.

Figure 1 – Software model

A *configuration* is the language element which corresponds to a *programmable controller system* as defined in IEC 1131-1. A *resource* corresponds to a "signal processing function" and its "man-machine interface" and "sensor and actuator interface" functions (if any) as defined in IEC 1131-1. A *configuration* contains one or more *resources*, each of which contains one or more *programs* executed under the control of zero or more *tasks*. A *program* may contain zero or more *function blocks* or other language elements as defined in this part.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Configurations and *resources* can be started and stopped via the "operator interface", "programming, testing, and monitoring", or "operating system" functions defined in IEC 1131-1. The starting of a *configuration* shall cause the initialization of its *global variables* according to the rules given in 2.4.2, followed by the starting of all the resources in the configuration. The starting of a *resource* shall cause the initialization of all the *variables* in the resource, followed by the enabling of all the *tasks* in the resource. The stopping of a *resource* shall cause the disabling of all its *tasks*, while the stopping of a configuration shall cause the stopping of all its resources. Mechanisms for the control of tasks are defined in 2.7.2, while mechanisms for the starting and stopping of *configurations* and *resources* via communication functions are defined in IEC 1131-5.

Programs, resources, global variables, access paths (and their corresponding access privileges), and *configurations* can be loaded or deleted by the "communication function" defined in IEC 1131-1. The loading or deletion of a *configuration* or *resource* shall be equivalent to the loading or deletion of all the elements it contains.

Access paths and their corresponding access privileges are defined in 2.7.1.

The mapping of the language elements defined in this subclause on to communication objects is defined in IEC 1131-5.

1.4.2 *Communication model*

Figure 2 illustrates the ways that values of variables can be communicated among software elements.

As shown in figure 2a, variable values within a program can be communicated directly by connection of the output of one program element to the input of another. This connection is shown explicitly in graphical languages and implicitly in textual languages.

Variable values can be communicated between programs in the same configuration via *global* variables such as the variable *x* illustrated in figure 2b. These variables shall be declared as GLOBAL in the configuration, and as EXTERNAL in the programs, as specified in 2.4.3.

As illustrated in figure 2c, the values of variables can be communicated between different parts of a program, between programs in the same or different configurations, or between a programmable controller program and a non-programmable controller system, using the communication function blocks defined in IEC 1131-5 and described in 2.5.2.3.5. In addition, programmable controllers or non-programmable controller systems can transfer data which is made available by *access paths*, as illustrated in figure 2d, using the mechanisms defined in IEC 1131-5.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale




Figure 2a – Data flow connection within a program




Figure 2b – Communication via GLOBAL variables




Figure 2c – Communication function blocks

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale




Figure 2d – Communication via access paths

NOTES

1 This figure is illustrative only. The graphical representation is not normative.

2 In these examples, configurations c and d are each considered to have a single resource.

3 The details of the communication function blocks are not shown in this figure. See 2.5.2.3.5 and IEC 1131-5.

4 As specified in 2.7, access paths can be declared on directly represented variables, global variables, or program input, output, or internal variables.

5 IEC 1131-5 specifies the means by which both PC and non-PC systems can use access paths for reading and writing of variables.

Figure 2 – Communication model

1.4.3 *Programming model*

The elements of programmable controller programming languages, and the subclauses in which they appear in this part, are classified as follows:

Data types (2.3)
Program organization units (2.5)
  Functions (2.5.1)
  Function blocks (2.5.2)
  Programs (2.5.3)
Sequential Function Chart (SFC) elements (2.6)
Configuration elements (2.7)
  Global variables (2.7.1)
  Resources (2.7.1)
  Tasks (2.7.2)
  Access paths (2.7.1)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

As shown in figure 3, the combination of these elements shall obey the following rules:

1) Derived *data types* shall be declared as specified in 2.3.3, using the standard data types specified in 2.3.1 and 2.3.2 and any previously derived data types.

2) Derived *functions* can be declared as specified in 2.5.1.3, using standard or derived data types, the standard functions defined in 2.5.1.5, and any previously derived functions. This declaration shall use the mechanisms defined for the IL, ST, LD or FBD language.

3) Derived *function blocks* can be declared as specified in 2.5.2.2, using standard or derived data types and functions, the standard function blocks defined in 2.5.2.3, and any previously derived function blocks. This declaration shall use the mechanisms defined for the IL, ST, LD, or FBD language, and can include Sequential Function Chart (SFC) elements as defined in 2.6.


4) A *program* shall be declared as specified in 2.5.3, using standard or derived data types, functions, and function blocks. This declaration shall use the mechanisms defined for the IL, ST, LD, or FBD language, and can include Sequential Function Chart (SFC) elements as defined in 2.6.

5) *Programs* can be combined into *configurations* using the elements defined in 2.7, that is, *global variables, resources, tasks*, and *access paths.*

Reference to "previously derived" data types, functions, and function blocks in the above rules is intended to imply that once such a derived element has been declared, its definition is available, e.g., in a "library" of derived elements, for use in further derivations. Therefore, the declaration of a derived element type shall not be contained within the declaration of another derived element type.

A programming language other than one of those defined in this standard may be used in the declaration of a *function* or *function block*. The means by which a user program written in one of the languages defined in this standard invokes the execution of, and accesses the data associated with, such a derived function or function block shall be as defined in this standard.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale



NOTES

1 The parenthesized numbers 1) to 5) refer to corresponding paragraphs in 1.4.3.

2 *Data types* are used in all productions. For clarity, the corresponding linkages are omitted in this figure.

Figure 3 – Combination of programmable controller language elements
LD-Ladder Diagram (4.2)
FBD-Function Block Diagram (4.3)
IL-Instruction List (3.2)
ST-Structured Text (3.3)
Others: Other programming languages (1.4.3)

1.5 *Compliance*

This subclause defines the requirements which shall be met by programmable controller systems and programs which claim compliance with this part of IEC 1131.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

1.5.1 *Programmable controller systems*

A programmable controller system, as defined in IEC 1131-1, which claims to comply, wholly or partially, with the requirements of this part of IEC 1131 shall do so only as described below.

A compliance statement shall be included in the documentation accompanying the system, or shall be produced by the system itself. The form of the compliance statement shall be:

"This system complies with the requirements of IEC 1131-3, for the following language features:"

followed by a set of compliance tables in the following format:

Table title

Table No.	Feature No.	Features description
...	...	...

Table and feature numbers and descriptions are to be taken from the tables given in the relevant subclauses of this part of IEC 1131. Table titles are to be taken from the following table.

Table title	For features in:
Common elements	Clause 2
Common textual elements	Subclause 3.1
IL language elements	Subclauses 3.2.1 to 3.2.3
ST language elements	Subclauses 3.3.1 to 3.3.2.4
Common graphical elements	Subclauses 4.1 to 4.1.4
LD language elements	Subclauses 4.2 to 4.2.6
FBD language elements	Subclauses 4.3 to 4.3.3

A programmable controller system complying with the requirements of this part with respect to a language defined in this part:

a) shall not require the inclusion of substitute or additional language elements in order to accomplish any of the features specified in this part;

b) shall be accompanied by a document that specifies the values of all implementation-dependent parameters as listed in annex D;

c) shall be able to determine whether or not a user's language element violates any requirement of this part, where such a violation is not designated an error in annex E, and report the result of this determination to the user. In the case where the system

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

does not examine the whole program organization unit, the user shall be notified that the determination is incomplete whenever no violations have been detected in the portion of the program organization unit examined;

d) shall treat each user violation that is designated an error in annex E in at least one of the following ways:

1) there shall be a statement in an accompanying document that the error is not reported;

2) the system shall report during preparation of the program for execution that an occurrence of that error is possible;

3) the system shall report the error during preparation of the program for execution;

4) the system shall report the error during execution of the program and initiate appropriate system- or user-defined error handling procedures;

and if any violations that are designated as errors are treated in the manner described in d)1) above, then a note referencing each such treatment shall appear in a separate section of the accompanying document;

e) shall be accompanied by a document that separately describes any features accepted by the system that are prohibited or not specified in this part. Such features shall be described as being "extensions to the <language> language as defined in IEC 1131-3";

f) shall be able to process in a manner similar to that specified for errors any use of any such extension;

g) shall be able to process in a manner similar to that specified for errors any use of one of the implementation-dependent features specified in annex D;

h) shall not use any of the standard data type, function or function block names defined in this part for manufacturer-defined features whose functionality differs from that described in this part;

i) shall be accompanied by a document defining, in the form specified in annex A, the formal syntax of all textual language elements supported by the system.

The phrase "be able to" is used in this subclause to permit the implementation of a software switch with which the user may control the reporting of errors.

In cases where compilation or program entry is aborted due to some limitation of tables, etc., an incomplete determination of the kind "no violations were detected, but the examination is incomplete" will satisfy the requirements of this subclause.

1.5.2 *Programs*

A programmable controller program complying with the requirements of IEC 1131-3:

a) shall use only those features specified in this part for the particular language used;

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

b) shall not use any features identified as extensions to the language;

c) shall not rely on any particular interpretation of implementation-dependent features.

The results produced by a complying program shall be the same when processed by any complying system which supports the features used by the program, except as these results are influenced by program execution timing, the use of implementation-dependent features (as listed in annex D) in the program, and the execution of error handling procedures.

2 Common elements

This clause defines textual and graphic elements which are common to all the programmable controller programming languages specified in this part of IEC 1131.

2.1 *Use of printed characters*

2.1.1 *Character set*

Textual languages and textual elements of graphic languages shall be represented in terms of the "Basic code table" of the ISO/IEC 646 character set.

The encoding of characters from national or extended (8-bit) character sets shall be consistent with ISO/IEC 646.

The *required character set* shown as feature 1 in table 1 consists of all the characters in columns 3 to 7 of the "Basic code table" given as table 1 in ISO/IEC 646, except for lowercase letters and those character positions which are reserved or optionally available for use in national character sets.

The manufacturer shall support one option (a or b) for each of features (3a,b) to (6a,b) of table 1, according to the following rules:

– The "pound sign" (£) shall be used in place of the "number sign" (#) when the former occupies character position 2/3 of a national implementation of the ISO/IEC 646 character set.

– The "currency sign" shall be used in place of the "dollar sign" ($) when the former occupies character position 2/4 of a national implementation of the ISO/IEC 646 character set.

– When the 7/12 character position in the ISO/IEC 646 character set is used by another character in a national set, the "exclamation mark" (!) at position 2/1 shall be used to represent vertical lines.

– For delimitation of subscripts, the left and right parentheses "( )" shall be used in place of the left and right brackets "[ ]" when the latter occupy character positions of a national implementation of the ISO/IEC 646 character set.

NOTE - The use of characters from national character sets is a typical extension of this standard.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

Table 1 – Character set features

No	Description
1	Required character set (see 2.1.1)
2	Lower case characters
3a 3b	Number sign (#) or Pound sign (£)
4a 4b	Dollar sign ($) or Currency sign
5a 5b	Vertical bar (|) or Exclamation mark (!)
6a 6b	Subscript delimiters: Left and right brackets "[ ]" or Left and right parentheses "( )"

NOTE - When lower-case letters (feature 2) are supported, the case of letters shall not be significant in language elements (except within terminal symbols as defined in annexes A and B, comments as defined in 2.1.5, string literals as defined in 2.2.2, and variables of type STRING as defined in 2.3.1), e.g., the identifiers "abcd", "ABCD" and "aBCd" shall be interpreted identically.

2.1.2 *Identifiers*

An *identifier* is a string of letters, digits, and underline characters which shall begin with a letter or underline character.

Underlines shall be significant in identifiers, e.g., "A_BCD" and "AB_CD" shall be interpreted as different identifiers. Multiple leading or multiple embedded underlines are not allowed.

Identifiers shall not contain imbedded space (SP) characters.

At least six characters of uniqueness shall be supported in all systems which support the use of identifiers, e.g., "ABCDE1" shall be interpreted as different from "ABCDE2" in all such systems.

Identifier features and examples are shown in table 2.

Table 2 – Identifier features

No.	Feature description	Examples
1	Upper case and numbers	IW215 IW215Z QX75 IDENT
2	Upper and lower case, numbers, embedded underlines	All the above plus: LIM_SW_5 LimSw5 abcd ab_Cd
3	Upper and lower case, numbers, leading or embedded underlines	All the above plus: _MAIN _12V7

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

2.1.3 *Keywords*

Keywords are unique combinations of characters utilized as individual syntactic elements as defined in annex B. All keywords used in this part are listed in annex C. Keywords shall not contain imbedded spaces. The keywords listed in annex C shall not be used for any other purpose, e.g., variable names or extensions as defined in 1.5.1.

NOTE - National standards organizations can publish tables of translations of the keywords given in annex C.

2.1.4 *Use of spaces*

The user shall be allowed to insert one or more spaces (code position 2/0 in the ISO/IEC 646 character set) anywhere in the text of programmable controller programs except within keywords, literals, identifiers, or delimiter combinations (e.g., for comments as defined below).

2.1.5 *Comments*

User comments shall be delimited at the beginning and end by the special character combinations "(*" and "*)", respectively, as shown in table 3. Except in the IL language as defined in 3.2, comments shall be permitted anywhere in the program where spaces are allowed, except within character string literals as defined in 2.2.2. Comments shall have no syntactic or semantic significance in any of the languages defined in this part.

Nested comments are not allowed, e.g., (* (* NESTED *) *).

Table 3 – Comment feature

No.	Feature description	Examples
1	Comments	(**********) (* A framed comment *) (**********)

2.2 *External representation of data*

External representations of data in the various programmable controller programming languages shall consist of numeric literals, character strings, and time literals.

2.2.1 *Numeric literals*

There are two classes of numeric literals: integer literals and real literals. A numeric literal is defined as a decimal number or a based number. The maximum number of digits for each kind of numeric literal shall be sufficient to express the entire range and precision of values of all the data types which are represented by the literal in a given implementation.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Single underline characters (_) inserted between the digits of a numeric literal shall not be significant. No other use of underline characters in numeric literals is allowed.

Decimal literals shall be represented in conventional decimal notation. Real literals shall be distinguished by the presence of a decimal point. An exponent indicates the integer power of ten by which the preceding number is to be multiplied to obtain the value represented. Decimal literals and their exponents can contain a preceding sign (+ or -).

Integer literals can also be represented in base 2, 8, or 16. The base shall be in decimal notation. For base 16, an extended set of digits consisting of the letters A through F shall be used, with the conventional significance of decimal 10 through 15, respectively. Based numbers shall not contain a leading sign (+ or -).

Boolean data shall be represented by integer literals with the value zero (0) or one (1), or the keywords FALSE or TRUE, respectively.

Numeric literal features and examples are shown in table 4.

Table 4 – Numeric literals

No.	Feature description	Examples
1	Integer literals	–12 0 123_456 +986
2	Real literals	–12.0 0.0 0.4560 3.14159_26
3	Real literals with exponents	–1.34E-12 or –1.34e-12 1.0E+6 or 1.0e+6 1.234E6 or 1.234e6
4	Base 2 literals	2#1111_1111 (255 decimal) 2#1110_0000 (240 decimal)
5	Base 8 literals	8#377 (255 decimal) 8#340 (240 decimal)
6	Base 16 literals	16#FF or 16#ff (255 decimal) 16#E0 or 16#e0 (240 decimal)
7	Boolean zero and one	0 1
8	Boolean FALSE and TRUE	FALSE TRUE
NOTE - The keywords FALSE and TRUE correspond to Boolean values of 0 and 1, respectively.		

2.2.2 *Character string literals*

A character string literal is a sequence of zero or more characters prefixed and terminated by the single quote character ('). In character strings, the three-character combination of the dollar sign ($) followed by two hexadecimal digits shall be interpreted as the hexadecimal representation of the eight-bit character code, as shown in table 5. Additionally, two-character combinations beginning with the dollar sign shall be interpreted as shown in table 6 when they occur in character strings.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

Table 5 – Character string literal feature

No.	Example	Explanation
1	''	Empty string (length zero)
	'A'	String of length one containing the single character A
	' '	String of length one containing the "space" character
	'$''	String of length one containing the "single quote" character
	'RL' '$0D$0A'	Strings of length two containing CR and LF characters
	'$$1.00'	String of length five which would print as "$1.00"

Table 6 – Two-character combinations in character strings

No.	Combination	Interpretation when printed
2	$$	*Dollar sign*
3	$'	Single quote
4	$L or $l	Line feed
5	$N or $n	Newline
6	$P or $p	Form feed (page)
7	$R or Sr	Carriage return
8	$T or $t	Tab

NOTE - The "newline" character provides an implementation-independent means of defining the end of a line of data for both physical and file I/O; for printing, the effect is that of ending a line of data and resuming printing at the beginning of the next line.

2.2.3 *Time literals*

The need to provide external representations for two distinct types of time-related data is recognized: *duration* data for measuring or controlling the elapsed time of a control event, and *time of day* data (which may also include date information) for synchronizing the beginning or end of a control event to an absolute time reference.

Duration and time of day literals shall be delimited on the left by the keywords defined in 2.2.3.1 and 2.2.3.2.

2.2.3.1 *Duration*

Duration data shall be delimited on the left by the keyword T#, TIME#, t#, or time#. The representation of duration data in terms of days, hours, minutes, seconds, and milliseconds, or any combination thereof, shall be supported as shown in table 7. The least significant time unit can be written in real notation without exponent.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

The units of duration literals can be separated by underline characters.

"Overflow" of the most significant unit of a duration literal is permitted, e.g., the notation T#25h_15m is permitted.

Time units, e.g., seconds, milliseconds, etc., can be represented in upper- or lower- case letters.

Table 7 – Duration literal features

No.	Feature description	Examples
1a	Duration literals without underlines: Short prefix	T#14ms T#14.7s T#14.7m T#14.7h t#14.7d t#25h15m t#5d14h12m18s3.5ms
1b	Long prefix	TIME#14ms time#14.7s
2a	Duration literals with underlines: Short prefix	t#25h_15m t#5d_14h_12m_18s_3.5ms
2b	Long prefix	TIME#25h_15m time#5d_14h_12m_18s_3.5ms

2.2.3.2 *Time of day and date*

Prefix keywords for time of day and date literals shall be as shown in table 8. As illustrated in table 9, representation of time-of-day and date information shall be as specified in ISO 8601.

Table 8 – Date and time of day literals

No.	Feature description	Prefix keyword
1	Date literals (long prefix)	DATE#
2	Date literals (short prefix)	D#
3	Time of day literals (long prefix)	TIME_OF_DAY#
4	Time of day literals (short prefix)	TOD#
5	Date and time literals (long prefix)	DATE_AND_TIME#
6	Date and time literals (short prefix)	DT#

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 9 – Examples of date and time of day literals

Long prefix notation	Short prefix notation
DATE#1984-06-25 date#1984-06-25	D#1984-06-25 d#1984-06-25
TIME_OF_DAY#15:36:55.36 time_of_day#15:36:55.36	TOD#15:36:55.36 tod#15:36:55.36
DATE_AND_TIME#1984-06-25-15:36:55.36 date_and_time#1984-06-25-15:36:55.36	DT#1984-06-25-15:36:55.36 dt#1984-06-25-15:36:55.36

2.3 *Data types*

A number of elementary (pre-defined) data types are recognized by this standard. Additionally, generic data types are defined for use in the definition of overloaded functions (see 2.5.1.4). A mechanism for the user or manufacturer to specify additional data types is also defined.

2.3.1 *Elementary data types*

The elementary data types, keyword for each data type, number of bits per data element, and range of values for each elementary data type shall be as shown in table 10.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

Table 10 – Elementary data types

No.	Keyword	Data type	Bits	Range
1	BOOL	Boolean	1	Note 8
2	SINT	Short integer	8	Note 2
3	INT	Integer	16	Note 2
4	DINT	Double integer	32	Note 2
5	LINT	Long integer	64	Note 2
6	USINT	Unsigned short integer	8	Note 3
7	UINT	Unsigned integer	16	Note 3
8	UDINT	Unsigned double integer	32	Note 3
9	ULINT	Unsigned long integer	64	Note 3
10	REAL	Real numbers	32	Note 4
11	LREAL	Long reals	64	Note 5
12	TIME	Duration	Note 1	Note 6
13	DATE	Date (only)	Note 1	Note 6
14	TIME_OF_DAY or TOD	Time of day (only)	Note 1	Note 6
15	DATE_AND_TIME or DT	Date and time of day	Note 1	Note 6
16	STRING	Variable-length character string	Note 1	Note 7
17	BYTE	Bit string of length 8	8	Note 7
18	WORD	Bit string of length 16	16	Note 7
19	DWORD	Bit string of length 32	32	Note 7
20	LWORD	Bit string of length 64	64	Note 7

NOTES

1 The length of these data elements is implementation-dependent.

2 The range of values for variables of this data type is from -(2**(Bits-1)) to (2**(Bits-1))-1.

3 The range of values for variables of this data type is from 0 to (2**Bits)-1.

4 The range of values for variables of this data type shall be as defined in IEC 559 for the basic single width floating-point format.

5 The range of values for variables of this data type shall be as defined in IEC 559 for the basic double width floating-point format.

6 The range of values for variables of this data type is implementation-dependent.

7 A numeric range of values does not apply to this data type.

8 The possible values of variables of this data type shall be 0 and 1, corresponding to the keywords FALSE and TRUE, respectively.

2.3.2 *Generic data types*

In addition to the data types in table 10, the hierarchy of generic data types shown in table 11 shall be used as defined in 2.5.1.4 in the specification of overloaded inputs and outputs of standard functions and function blocks. Generic data types are identified by the prefix "ANY".

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

Table 11 – Hierarchy of generic data types

ANY ANY_NUM ANY_REAL LREAL REAL ANY_INT LINT, DINT, INT, SINT ULINT, UDINT, UINT, USINT ANY_BIT LWORD, DWORD, WORD, BYTE, BOOL STRING ANY_DATE DATE_AND_TIME DATE TIME_OF_DAY TIME Derived (see notes)
NOTES 1 Generic data types shall not be used in user-declared program organization units as defined in 2.5. 2 The generic type of a *subrange* derived type (feature 3 of table 12) shall be ANY_INT. 3 The generic type of a *directly* derived type (feature 1 of table 12) shall be the same as the generic type of the elementary type from which it is derived. 4 The generic type of all other derived types defined in table 12 shall be ANY.

2.3.3 *Derived data types*

2.3.3.1 *Declaration*

Derived (i.e., user- or manufacturer-specified) data types can be declared using the TYPE...END_TYPE textual construction shown in table 12. These derived data types can then be used, in addition to the elementary data types defined in 2.3.1, in variable declarations as defined in 2.4.3.

An *enumerated* data type declaration specifies that the value of any data element of that type can only take on one of the values given in the associated list of identifiers, as illustrated in table 12.

A *subrange* declaration specifies that the value of any data element of that type can only take on values between and including the specified upper and lower limits, as illustrated in table 12.

A STRUCT declaration specifies that data elements of that type shall contain sub-elements of specified types which can be accessed by the specified names. For instance, an element of data type ANALOG_CHANNEL_CONFIGURATION as declared in table 12 will contain a RANGE sub-element of type ANALOG_SIGNAL_RANGE, a MIN_SCALE sub-element of type ANALOG_DATA, and a MAX_SCALE element of type ANALOG_DATA.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

An ARRAY declaration specifies that a sufficient amount of data storage shall be allocated for each element of that type to store all the data which can be indexed by the specified index subrange(s). Thus, any element of type ANALOG_16_INPUT_CONFIGURATION as shown in table 12 contains (among other elements) sufficient storage for 16 CHANNEL elements of type ANALOG_ CHANNEL_CONFIGURATION. Mechanisms for access to array elements are defined in 2.4.1.2.

2.3.3.2 *Initialization*

The default initial value of an *enumerated* data type shall be the first identifier in the associated enumeration list, or a value specified by the assignment operator ":=". For instance, as shown in tables 12 and 14, the default initial values of elements of data types ANALOG_SIGNAL_TYPE and ANALOG_SIGNAL_RANGE are SINGLE_ENDED and UNIPOLAR_1_5V, respectively.

For data types with *subranges*, the default initial values shall be the first (lower) limit of the subrange, unless otherwise specified by an assignment operator. For instance, as declared in table 12, the default initial value of elements of type ANALOG_DATA is 4095, while the default initial value for the FILTER_PARAMETER sub-element of elements of type ANALOG_16_INPUT_CONFIGURATION is zero. In contrast, the default initial value of elements of type ANALOG_DATAZ as declared in table 14 is zero.

For other derived data types, the default initial values, unless specified otherwise by the use of the assignment operator ":=" in the TYPE declaration, shall be the default initial values of the underlying elementary data types as defined in table 13. Further examples of the use of the assignment operator for initialization are given in 2.4.2.

The default maximum length of elements of type STRING shall be an implementation-dependent value unless specified otherwise by a parenthesized maximum length (which shall not exceed the implementation-dependent default value) in the associated declaration. For example, if type STR10 is declared by

```
TYPE STR10 : STRING(10) := 'ABCDEF' ; END_TYPE
```

the maximum length, default initial value, and default initial length of data elements of type STR10 are 10 characters, 'ABCDEF', and 6 characters, respectively.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 12 – Data type declaration feature

No.	Feature/textual example
1	Direct derivation from elementary types, e.g.: TYPE R : REAL ; END_TYPE
2	Enumerated data types, e.g: TYPE ANALOG_SIGNAL_TYPE : (SINGLE_ENDED, DIFFERENTIAL) ; END_TYPE
3	Subrange data types, e.g: TYPE ANALOG_DATA : INT (-4095..4095) ; END_TYPE
4	Array data types, e.g.: TYPE ANALOG_16_INPUT_DATA : ARRAY [1..16] OF ANALOG_DATA ; END_TYPE
5	Structured data types, e.g.: TYPE ANALOG_CHANNEL_CONFIGURATION : STRUCT RANGE : ANALOG_SIGNAL_RANGE ; MIN_SCALE : ANALOG_DATA ; MAX_SCALE : ANALOG_DATA ; END_STRUCT ; ANALOG_16_INPUT_CONFIGURATION : STRUCT SIGNAL_TYPE : ANALOG_SIGNAL_TYPE ; FILTER_PARAMETER : SINT (0..99) ; CHANNEL : ARRAY [1..16] OF ANALOG_CHANNEL_CONFIGURATION ; END_STRUCT ; END_TYPE
NOTE - For examples of the use of these types in variable declarations, see 2.3.3.3, 2.4.1.2, and table 17.	

Table 13 – Default initial values

Data type(s)	Initial value
BOOL, SINT, INT, DINT, LINT	0
USINT, UINT, UDINT, ULINT	0
BYTE, WORD, DWORD, LWORD	0
REAL, LREAL	0.0
TIME	T#0S
DATE	D#0001-01-01
TIME_OF_DAY	TOD#00:00:00
DATE_AND_TIME	DT#0001-01-01-00:00:00
STRING	''(the empty string)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

Table 14 – Data type initial value declaration features

No.	Feature/textual example
1	Initialization of directly derived types, e.g.: TYPE FREQ : REAL :- 50.0 ; END_TYPE
2	Initialization of enumerated data types, e.g: TYPE ANALOG_SIGNAL_RANGE : (BIPOLAR_10V, (* –10 to +10 VDC *) UNIPOLAR_10V, (* 0 to +10 VDC *) UNIPOLAR_1_5V, (* +1 to +5 VDC *) UNIPOLAR_0_5V, (* 0 to +5 VDC *) UNIPOLAR_4_20_MA, (* +4 to +20 mADC *) UNIPOLAR_0_20_MA, (* 0 to +20 mADC *)) := UNIPOLAR_1_5V ; END_TYPE
3	Initialization of subrange data types, e.g.: TYPE ANALOG_DATAZ : INT (-4095..4095) := 0 ; END_TYPE
4	Initialization of array data types, e.g.: TYPE ANALOG_16_INPUT_DATAI : ARRAY [1..16] OF ANALOG_DATA := 8(–4095), 8(4095) ; END_TYPE
5	Initialization of structured data type elements, e.g.: TYPE ANALOG_CHANNEL_CONFIGURATIONI : STRUCT RANGE : ANALOG_SIGNAL_RANGE ; MIN_SCALE : ANALOG_DATA := –4095 ; MAX_SCALE : ANALOG_DATA := 4095 ; END_STRUCT ; END_TYPE
6	Initialization of derived structured data types, e.g.: TYPE ANALOG_CHANNEL_CONFIGZ : ANALOG_CHANNEL_CONFIGURATIONI (MIN_SCALE := 0, MAX_SCALE := 9999) ; END_TYPE

2.3.3.3 *Usage*

The usage of variables which are declared (as defined in 2.4.3.1) to be of derived data types shall conform to the following rules:

1) A single-element variable, as defined in 2.4.1.1, of a derived type, can be used anywhere that a variable of its "parent's" type can be used, e.g. variables of the types R and PI as shown in tables 12 and 14 can be used anywhere that a variable of type REAL could be used, and variables of type ANALOG_DATA can be used anywhere that a variable of type INT could be used.

This rule can be applied recursively. For example, given the declarations below, the variable R3 of type R2 can be used anywhere a variable of type REAL can be used:

```
TYPE R1 : REAL := 1.0 ; END_TYPE
TYPE R2 : R1 ; END_TYPE
VAR R3 : R2 ; END_VAR
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

2) An element of a multi-element variable, as defined in 2.4.1.2, can be used anywhere the "parent" type can be used, e.g., given the declaration of ANALOG_16_INPUT_DATA in table 12 and the declaration

VAR INS : ANALOG_16_INPUT_DATA ; END_VAR

the variables INS[1] through INS[16] can be used anywhere that a variable of type INT could be used.

This rule can also be applied recursively, e.g., given the declarations of ANALOG_16_INPUT_CONFIGURATION, ANALOG_CHANNEL_CONFIGURATION, and ANALOG_DATA in table 12 and the declaration

VAR CONF : ANALOG_16_INPUT_CONFIGURATION ; END_VAR

the variable CONF.CHANNEL[2].MIN_SCALE can be used anywhere that a variable of type INT could be used.

2.4 *Variables*

In contrast to the external representations of data described in 2.2, *variables* provide a means of identifying data objects whose contents may change, e.g., data associated with the inputs, outputs, or memory of the programmable controller. A variable can be declared to be one of the elementary types defined in 2.3.1, or one of the derived types which are declared as defined in 2.3.3.1.

2.4.1 *Representation*

2.4.1.1 *Single-element variables*

A *single-element variable* is defined as a variable which represents a single data element of one of the elementary types defined in 2.3.1; a derived enumeration or subrange type as defined in 2.3.3.1; or a derived type whose "parentage", as defined recursively in 2.3.3.3, is traceable to an elementary, enumeration or subrange type. This subclause defines the means of representing such variables *symbolically*, or alternatively in a manner which *directly* represents the association of the data element with physical or logical locations in the programmable controller's input, output, or memory structure.

Identifiers, as defined in 2.1.2, shall be used for symbolic representation of variables.

Direct representation of a single-element variable shall be provided by a special symbol formed by the concatenation of the percent sign "%" (position 2/5 in the ISO/IEC 646 code table), a *location prefix* and a *size prefix* from table 15, and one or more unsigned integers, separated by periods (.)

Examples of directly represented variables are:

%QX75 and %Q75	Output bit 75
%IW215	Input word location 215
%QB7	Output byte location 7
%MD48	Double word at memory location 48
%IW2.5.7.1	See explanation below

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

The manufacturer shall specify the correspondence between the direct representation of a variable and the physical or logical location of the addressed item in memory, input or output. When a direct representation is extended with additional integer fields separated by periods, it shall be interpreted as a *hierarchical* physical or logical address with the leftmost field representing the highest level of the hierarchy, with successively lower levels appearing to the right. For instance, the variable %IW2.5.7.1 may represent the first "channel" (word) of the seventh "module" in the fifth "rack" of the second "I/O bus" of a programmable controller system.

The use of hierarchical addressing to permit a program in one programmable controller system to access data in another programmable controller shall be considered a language extension.

The use of directly represented variables is only permitted in *programs*, as defined in 2.5.3, and in *configurations* and *resources* as defined in 2.7.1. The maximum number of levels of hierarchical addressing is an implementation-dependent parameter.

Table 15 – Location and size prefix features for directly represented variables

No.	Prefix	Meaning
1	I	Input location
2	Q	Output location
3	M	Memory location
4	X	Single bit size
5	None	Single bit size
6	B	Byte (8 bits) size
7	W	Word (16 bits) size
8	D	Double word (32 bits) size
9	L	Long (quad) word (64 bits) size

NOTES

1 Unless otherwise declared, the data type of a directly addressed variable of "single bit" size shall be BOOL.

2 National standards organizations can publish tables of translations of these prefixes.

2.4.1.2 *Multi-element variables*

The *multi-element variable* types defined in this standard are *arrays* and *structures.*

An *array* is a collection of data elements of the same data type referenced by one or more *subscripts* enclosed in brackets and separated by commas. A subscript shall be an expression yielding a value corresponding to one of the sub-types of generic type ANY_INT as defined in table 11.

An example of the use of array variables in the ST language as defined in 3.3 is:

```
OUTARY[%MB6,SYM] := INARY[0] + INARY[7] – INARY[%MB6] * %IW62 ;
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

The maximum number of subscripts, and the maximum range of subscript values, which may be used to access array variables is an implementation-dependent parameter.

A *structured variable* is a variable which is declared to be of a type which has previously been specified to be a *data structure*, i.e., a data type consisting of a collection of named elements.

An element of a structured variable shall be represented by two or more identifiers or array accesses separated by single periods (.). The first identifier represents the name of the structured element, and subsequent identifiers represent the sequence of component names to access the particular data element within the data structure.

For instance, if the variable MODULE_5_CONFIG has been declared to be of type ANALOG_16_INPUT_CONFIGURATION as shown in table 12, the following statements in the ST language defined in 3.3 would cause the value SINGLE_ENDED to be assigned to the element SIGNAL_TYPE of the variable MODULE_5_CONFIG, while the value BIPOLAR_10V would be assigned to the RANGE sub-element of the fifth CHANNEL element of MODULE_5_CONFIG:

```
MODULE_5_CONFIG.SIGNAL_TYPE := SINGLE_ENDED ;
MODULE_5_CONFIG.CHANNEL[5].RANGE := BIPOLAR_10V
```

The maximum number of levels of structure element addressing is an implementation-dependent parameter.

2.4.2 *Initialization*

When a configuration element (*resource* or *configuration*) is "started" as defined in 1.4.1, each of the variables associated with the configuration element and its *programs* can take on one of the following initial values:

- the value the variable had when the configuration element was "stopped" (a *retained* value);
- a user-specified initial value;
- the default initial value for the variable's associated data type.

The user can declare that a variable is to be *retentive* by using the RETAIN qualifier specified in table 16, when this feature is supported by the implementation.

The initial value of a variable upon starting of its associated configuration element shall be determined according to the following rules:

1) If the starting operation is a "warm restart" as defined in IEC 1131-1, the initial values of *retentive* variables shall be their *retained* values as defined above.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

2) If the operation is a "cold restart" as defined in IEC 1131-1, the initial values of retentive variables shall be the user-specified initial values, or the default value, as defined in 2.3.3.2, for the associated data type of any variable for which no initial value is specified by the user.

3) Non-retained variables shall be initialized to the user-specified initial values, or to the default value, as defined in 2.3.3.2, for the associated data type of any variable for which no initial value is specified by the user.

4) Variables which represent *inputs* of the *programmable controller system* as defined in IEC 1131-1 shall be initialized in an implementation-dependent manner.

2.4.3 *Declaration*

Each programmable controller program organization unit type declaration (i.e., each declaration of a *program, function,* or *function block*, as defined in 2.5) shall contain at its beginning at least one *declaration part* which specifies the types (and, if necessary, the physical or logical location) of the variables used in the organization unit. This declaration part shall have the textual form of one of the keywords VAR, VAR_INPUT, or VAR_OUTPUT as defined in table 16, followed in the case of VAR by zero or one occurrence of the qualifier RETAIN or the qualifier CONSTANT, and in the case of VAR_OUTPUT by zero or one occurrence of the qualifier RETAIN, followed by one or more declarations separated by semicolons and terminated by the keyword END_VAR. When a programmable controller supports the declaration by the user of initial values for variables, this declaration shall be accomplished in the declaration part(s) as defined in this subclause.

The *scope* (range of validity) of the declarations contained in the declaration part shall be *local* to the program organization unit in which the declaration part is contained. That is, the declared variables shall not be accessible to other program organization units except by explicit parameter passing via variables which have been declared as *inputs* or *outputs* of those units. The one exception to this rule is the case of variables which have been declared to be *global*, as defined in 2.7.1. Such variables are only accessible to a program organization unit via a VAR_EXTERNAL declaration. The type of a variable declared in a VAR_EXTERNAL block shall agree with the type declared in the VAR_GLOBAL block of the associated *program, configuration* or *resource.*

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 16 – Variable declaration keywords

Keyword	Variable usage
VAR	Internal to organization unit
VAR_INPUT	Externally supplied, not modifiable within organization unit
VAR_OUTPUT	Supplied by organization unit to external entities
VAR_IN_OUT	Supplied by external entities Can be modified within organization unit NOTE - Examples of the use of these variables are given in figures 11b and 12
VAR_EXTERNAL	Supplied by configuration via VAR_GLOBAL (2.7.1) Can be modified within organization unit
VAR_GLOBAL	Global variable declaration (2.7.1)
VAR_ACCESS	Access path declaration (2.7.1)
RETAIN	Retentive variables (see preceding text)
CONSTANT	Constant (variable cannot be modified)
AT	Location assignment (2.4.3.1)
NOTE - The usage of these keywords is a feature of the program organization unit or configuration element in which they are used; see 2.5 and 2.7.	

2.4.3.1 *Type assignment*

As shown in table 17, the VAR...END_VAR construction shall be used to specify data types and retentivity for directly represented variables. This construction shall also be used to specify data types, retentivity, and (where necessary, in *programs* only) the physical or logical location of symbolically represented single- or multi-element variables. The usage of the VAR_INPUT, VAR_OUTPUT, and VAR_IN_OUT constructions is defined in 2.5.

The assignment of a physical or logical address to a symbolically represented variable shall be accomplished by the use of the AT keyword. Where no such assignment is made, automatic allocation of the variable to an appropriate location in the programmable controller memory shall be provided.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 17 – Variable type assignment features

No.	Feature/examples	
1	Declaration of directly represented, non-retentive variable	
	VAR AT %IW6.2 : WORD ; AT %MW6 : INT ; END_VAR	16-bit string (note 2) 16-bit integer, initial value = 0
2	Declaration of directly represented retentive variables	
	VAR RETAIN AT %QW5 : WORD ; END_VAR	At cold restart, %QW5 will be initialized to a 16-bit string with value 0
3	Declaration of locations of symbolic variables	
	VAR_GLOBAL LIM_SW_5 AT %IX27 : BOOL ; CONV_START AT %QX25 : BOOL ; TEMPERATURE AT %IW28 : INT ; END_VAR	 Assigns input bit 27 to the Boolean variable LIM_SW_5 (note 2) Assigns output bit 25 to the Boolean variable CONV_START Assigns input word 28 to the integer variable TEMPERATURE (note 2)
4	Array location assignment	
	VAR INARY AT %IW6 : ARRAY [0..9] OF INT ; END_VAR	Declares an array of 10 integers to be allocated to contiguous input locations starting at %IW6 (note 2)
5	Automatic memory allocation of symbolic variables	
	VAR CONDITION_RED : BOOL ; IBOUNCE : WORD ; MYDUB : DWORD ; AWORD, BWORD, CWORD : INT ; MYSTR : STRING(10) ; END_VAR	Allocates a memory bit to the Boolean variable CONDITION_RED Allocates a memory word to the 16-bit string variable IBOUNCE. Allocates a double memory word to the 32-bit string variable MYDUB. Allocates 3 separate memory words for the integer variables AWORD, BWORD and CWORD Allocates memory to contain a string with a maximum length of 10 characters. After initialization, the string has length 0 and contains the empty string''.
6	Array declaration	
	VAR THREE : ARRAY[1..5,1..10,1..8] OF INT ; END_VAR	Allocates 400 memory words for a three-dimensional array of integers
7	Retentive array declaration	
	VAR RETAIN RTBT : ARRAY[1..2,1..3] OF INT ; END_VAR	Declares retentive array RTBT with "cold restart" initial values of 0 for all elements
8	Declaration of structured variables	
	VAR MODULE_8_CONFIG : ANALOG_16_INPUT_CONFIGURATION ; END_VAR	Declaration of a variable of derived data type (see table 12)

NOTES:

1 Features 1 to 4 can only be used in PROGRAM and VAR_GLOBAL declarations, as defined in 2.5.3 and 2.7.1 respectively.

2 Initialization of system inputs is implementation-dependent; see 2.4.2.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.4.3.2 *Initial value assignment*

The VAR...END_VAR construction shown in table 18 shall be used to specify initial values of directly represented variables. This construction shall also be used to assign initial values of symbolically represented single- or multi-element variables (the usage of the VAR_INPUT, VAR_OUTPUT, and VAR_IN_OUT constructions is defined in 2.5).

Initial values cannot be given in VAR_EXTERNAL declarations.

During initialization of arrays, the rightmost subscript of an array shall vary most rapidly with respect to filling the array from the list of initialization variables.

Parentheses can be used as a repetition factor in array initialization lists, e.g., "2(1,2,3)" is equivalent to the initialization sequence "1,2,3,1,2,3".

If the number of initial values given in the initialization list exceeds the number of array entries, the excess (rightmost) initial values shall be ignored. If the number of initial values is less than the number of array entries, the remaining array entries shall be filled with the default initial values for the corresponding data type. In either case, the user shall be warned of this condition during preparation of the program for execution.

When a variable is declared to be of a derived, structured data type as defined in 2.3.3.1, initial values for the elements of the variable can be declared in a parenthesized list following the data type identifier, as shown in table 18. Elements for which initial values are not listed in the initial value list shall have the default initial values declared for those elements in the data type declaration.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 18 – Variable initial value assignment features

No.	Feature/examples	
1	Initialization of directly represented, non-retentive variables	
	VAR AT %QX 5.1 : BOOL := 1 ; AT %MW6 : INT := 8 ; END_VAR	Boolean type, initial value =1 Initializes a memory word to integer 8
2	Initialization of directly represented retentive variables	
	VAR RETAIN AT %QW5 : WORD := 16#FF00 ; END_VAR	At cold restart, the 8 most significant bits of the 16-bit string at output word 5 are to be initialized to 1 and the 8 least significant bits to 0
3	Location and initial value assignment to symbolic variables	
	VAR VALVE_POS AT %QW28 : INT := 100 ; END_VAR	Assigns output word 28 to the integer variable VALVE_POS, with an initial value of 100
4	Array location assignment and initialization	
	VAR OUTARY AT %QW6: ARRAY [0..9] OF INT := 10(1) ; END_VAR	Declares an array of 10 integers to be allocated to contiguous output locations starting at %QW6, each with an initial value of 1
5	Initialization of symbolic variables	
	VAR MYBIT : BOOL := 1 ; OKAY : STRING(10) := 'OK' ; END_VAR	Allocates a memory bit to the Boolean variable MYBIT with an initial value of 1. Allocates memory to contain a string with a maximum length of 10 characters. After initialization, the string has length 2 and contains the two-byte sequence of characters 'OK' in the ISO/IEC 646 character set, in an order appropriate for printing as a character string.
6	Array initialization	
	VAR BITS : ARRAY [0..7] OF BOOL := 1,1,0,0,0,1,0,0 ; TBT : ARRAY[1..2,1..3] OF INT : = 1,2,3(4),6 ; END_VAR	Allocates 8 memory bits to contain initial values BITS[0] := 1, BITS [1] := 1, ..., BITS[6] := 0, BITS [7] := 0 Allocates a 2-by-3 integer array TBT with initial values TBT[1,1] := 1, TBT[1,2] := 2, TBT[1,3] := 4, TBT[2,1] := 4, TBT[2,2] := 4, TBT[2,3] := 6,
7	Retentive array declaration and initialization	
	VAR RETAIN RTBT : ARRAY [1..2, 1..3] OF INT : = 1,2,3(4) ; END_VAR	Declares retentive array RTBT with "cold restart" initial values of: RTBT[1,1] := 1, RTBT[1,2] := 2, RTBT[1,3] := 4, RTBT[2,1] := 4, RTBT[2,2] := 4, RTBT[2,3] := 0
8	Initialization of structured variables	
	VAR MODULE_8_CONFIG : ANALOG_16_INPUT_CONFIGURATION (SIGNAL_TYPE := DIFFERENTIAL, CHANNEL[5].RANGE := BIPOLAR_10_V, CHANNEL[5].MIN_SCALE := 0, CHANNEL[5].MAX_SCALE := 500) ; END_VAR	Initialization of a variable of derived data type (see table 12)
9	Initialization of constants	
	VAR CONSTANT PI : REAL := 3.141592 ; END_VAR	
	NOTE - Features 1 to 4 can only be used in PROGRAM and VAR_GLOBAL declarations, as defined in 2.5.3 and 2.7.1 respectively.	

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.5 *Program organization units*

The program organization units defined in this part of IEC 1311 are the *function, function block*, and *program*. These program organization units can be delivered by the manufacturer, or programmed by the user by the means defined in this part of the standard.

Program organization units shall not be *recursive*; that is, the invocation of a program organization unit shall not cause the invocation of another program organization unit of the same type.

2.5.1 *Functions*

For the purposes of programmable controller programming languages, a *function* is defined as a program organization unit which, when executed, yields exactly one data element (which can be multi-valued, e.g., an array or structure), and whose invocation can be used in textual languages as an operand in an expression. For example, the SIN and COS functions could be used as shown in figure 4.

a)

```
Z := SIN(X)*COS(Y) + COS(X)*SIN(Y) ;
```

b)




Figure 4 – Examples of function usage
a) Structured Text (ST) language; see subclause 3.3
b) Function Block Diagram (FBD) language; see subclause 4.3

Functions shall contain no internal state information, i.e., invocation of a function with the same arguments (input parameters) shall always yield the same value (output).

Any function type which has already been declared can be used in the declaration of another program organization unit, as shown in figure 3.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.5.1.1 *Representation*

Functions and their invocation can be represented either graphically or textually.

In the graphic languages defined in clause 4 of this part, functions shall be represented as graphic blocks according to the following rules:

1) The form of the block shall be rectangular or square.

2) The size and proportions of the block may vary depending on the number of inputs and other information to be displayed.

3) The direction of processing through the block shall be from left to right (input parameters on the left and output parameter on the right).

4) The function name or symbol, as specified below, shall be located inside the block.

5) Provision shall be made for formal input parameter names appearing at the inside left of the block when the block represents:

- one of the standard functions defined in subclause 2.5.1.5, when the given graphical form includes the formal parameter names; or
- any additional function declared as specified in subclause 2.5.1.3.



6) Since the name of the function is used for the assignment of its output value as specified in 2.5.1.3, no formal output parameter name shall be shown at the right side of the block.

7) Actual parameter connections shall be shown by signal flow lines.

8) Negation of Boolean signals shall be shown by placing an open circle just outside of the input or output line intersection with the block. In the ISO/IEC 646 character set, this shall be represented by the upper case alphabetic "O", as shown in table 19.

9) The output of a graphically represented function shall be represented by a single line at the right side of the block, even though the output may be a multi-element variable.

Table 19 – Graphical negation of Boolean signals

No.	Feature	Representation
1	Negated input	
2	Negated output	
NOTE - If either of these features is supported for functions, it shall also be supported for function blocks as defined in 2.5.2, and vice versa.		

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

As shown in figure 5, where a formal parameter name is present in the definition of a standard function in 2.5.1.5, the formal parameter name shall also be used in the textual invocation of the function. In the latter case, the formal parameter names and associated actual values can be given in any order.

The representation of functions in textual languages shall be as specified in clause 3 of this part.



Example	Explanation
	Graphical use of "ADD" function (See 2.5.1.5.2) (FBD language; see 4.3) (No formal parameter names)
`A := ADD(B,C,D);`	Textual use of "ADD" function (ST language; see 3.3)
	Graphical use of "SHL" function (See 2.5.1.5.3) (FBD language; see 4.3) (Formal parameter names)
`A := SHL(IN := B,N := C);`	Textual use of "SHL" function (ST language; see 3.3)

Figure 5 – Use of formal parameter names

2.5.1.2 *Execution control*

As shown in table 20, an additional Boolean "EN" (Enable) input and "ENO" (Enable Out) output shall be used with functions in the LD language defined in 4.2, and their use shall also be possible in the FBD language defined in this part. These variables are considered to be available in every function according to the implicit declarations

VAR_INPUT EN : BOOL := 1 ; END_VAR

VAR_OUTPUT ENO : BOOL ; END_VAR

When these variables are used, the execution of the operations defined by the function shall be controlled according to the following rules:

1) If the value of EN is FALSE (0) when the function is invoked, the operations defined by the function body shall not be executed and the value of "ENO" shall be reset to FALSE (0) by the programmable controller system.




2) Otherwise, the value of ENO shall be set to TRUE (1) by the programmable controller system, and the operations defined by the function body shall be executed. These operations can include the assignment of a Boolean value to ENO.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

3) If one of the errors defined in annex E occurs during the execution of one of the standard functions defined in 2.5.1.5, the ENO output of that function shall be reset to FALSE (0) by the programmable controller system.

NOTE - The use of the ENO output is an allowable exception to the rule that the execution of a function yields exactly one output.

Table 20 – Use of EN input and ENO output

No.	Feature	Example
1	Use of "EN" and "ENO" Required for LD (Ladder Diagram) language (see 4.2)	
2	Use of "EN" and "ENO" Optional for FBD (Function Block Diagram) language (see 4.3)	
3	FBD without "EN" and "ENO"	

2.5.1.3 *Declaration*

A function shall be declared textually or graphically.

As illustrated in figure 6, the textual declaration of a function shall consist of the following elements:

1) The keyword FUNCTION, followed by an identifier specifying the name of the function being declared, a colon (:), and the data type of the value to be returned by the function;

2) A VAR_INPUT...END_VAR construct as defined in 2.4.2, specifying the names and types of the function's input parameters;

3) A VAR...END_VAR construct, if required, specifying the names and types of the function's internal variables;

4) *A function body*, written in one of the languages defined in this part, or another programming language as defined in 1.4.3, which specifies the operations to be performed upon the input parameter(s) in order to assign one or more values to a variable with the same name as the function, which represents the value to be returned by the function;

5) The terminating keyword END_FUNCTION.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

As illustrated in figure 6, the graphic declaration of a function shall consist of the following elements:

1) The bracketing keywords FUNCTION...END_FUNCTION or a graphical equivalent;

2) A graphic specification of the function name and the names and types of the function's inputs and output;

3) A specification of the names and types of the internal variables used in the function, e.g., using the VAR...END_VAR construct;

4) A function body as defined above.

a)

```
FUNCTION SIMPLE_FUN : REAL
  VAR_INPUT
    A,B : REAL;          (* External interface specification *)
      C : REAL := 1.0;
  END_VAR
  SIMPLE_FUN := A*B/C;  (* Function body specification *)
  END_FUNCTION
```

b)

```
FUNCTION
         +-------------+
         | SIMPLE_FUN  |
REAL-----|A            |----REAL
REAL-----|B            |    (* External interface specification *)
REAL-----|C            |
         +-------------+


    +---+                    (* Function body specification *)
A---| * |    +---+
B---|   |----| / |---SIMPLE_FUN
    +---+    |   |
             |   |
C------------|   |
             +---+

END_FUNCTION
```

NOTE - In example a), the input variable C is given a default value of 1.0, as specified in 2.4.3.2, to avoid a "division by zero" error if the input is not specified when the function is invoked, for example, if a graphical input to the function is left unconnected.

Figure 6 – Examples of function declarations
a) Textual declaration in ST language (see 3.3)
b) Graphical declaration in FBD language (see 4.3)

2.5.1.4 *Typing, overloading, and type conversion*



A function or operation is said to be *overloaded* when it can operate on input data elements of various types within a generic type designator as defined in 2.3.2. For instance, an overloaded addition function on generic type ANY_NUM can operate on data of types LREAL, REAL, DINT, INT, and SINT.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

When a programmable controller system supports an overloaded operation or function, this operation or function shall apply to all data types of the given generic type which are supported by that system. For example, if a programmable controller system supports the overloaded function ADD and the data types SINT, INT, and REAL, then the system shall support the ADD function on inputs of type SINT, INT, and REAL.

When a function which normally represents an overloaded operator is to be typed, i.e., the types of its inputs and outputs restricted to a particular subtype, this shall be done by appending an "underline" character followed by the required type, as shown in table 21.

Table 21 – Typed and overloaded functions

No.	Feature	Example
1	Overloaded functions	
2	Typed functions	




NOTES

1 If feature 2 is supported, the manufacturer shall provide a table of which functions are overloaded and which are typed in the implementation.

2 User-defined functions cannot be overloaded.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

When all the formal input parameters to a standard function defined in 2.5.1.5 are of the same generic type then all the actual parameters shall be of the same type. If necessary, the type conversion functions defined in 2.5.1.5.1 can be used to meet this requirement. The output value of the function shall then have the same type as the actual inputs, except as noted in table 22. Examples of the application of this rule are given in figures 7 and 8.




Type declaration (ST language - see 3.3)	Usage (FBD language - see 4.3) (ST language - see 3.3)
VAR A : INT ; B : INT ; C : INT ; END_VAR	
VAR A : INT ; B : REAL ; C : REAL ; END_VAR	
VAR A : INT ; B : INT ; C : REAL ; END_VAR	

NOTE - Type conversion is not required in the first example shown above.

Figure 7 – Examples of explicit type conversion with overloaded functions

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

Type declaration (ST language - see 3.3)	Usage (FBD langage - see 4.3) (ST language - see 3.3)
VAR A : INT ; B : INT ; C : INT ; END_VAR	 C := ADD_INT(A+B) ;
VAR A : INT ; B : REAL ; C : REAL ; END_VAR	 C := ADD_REAL(INT_TO_REAL(A),B) ;
VAR A : INT ; B : INT ; C : REAL ; END_VAR	 C := INT_TO_REAL(ADD_INT(A,B)) ;

NOTE - Type conversion is not required in the first example shown above.

Figure 8 – Examples of explicit type conversion with typed functions

2.5.1.5 *Standard functions*

Definitions of functions common to all programmable controller programming languages are given in this subclause. Where graphical representations of standard functions are shown in this subclause, equivalent textual declarations may be written as specified in 2.5.1.3.





A standard function specified in this subclause to be *extensible* is allowed to have a variable number of inputs, and shall be considered as applying the indicated operation to each input in turn, e.g., extensible addition shall give as its output the sum of all its inputs. The maximum number of inputs of an extensible function is an implementation-dependent parameter.

2.5.1.5.1 *Type conversion functions*

As shown in table 22, type conversion functions shall have the form *_TO_**, where *** is the type of the input variable IN, and **** the type of the output variable OUT, e.g., INT_TO_REAL.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 22 – Type conversion function features

No.	Graphical form	Usage example	Notes
1	 (*) Input data type, e.g., INT (**) Output data type, e.g., REAL (*_TO_**) Function name, e.g., INT_TO_REAL	A := INT_TO_REAL(B) ;	1 2 5
2		A := TRUNC(B) ;	3
3		A := BCD_TO_INT(B) ;	4
4		A := INT_TO_BCD(B) ;	4

NOTES

1 A statement of conformance to feature 1 of this table shall include a list of the specific type conversions supported, and a statement of the effects of performing each conversion.

2 Conversion from type REAL or LREAL to SINT, INT, DINT, or LINT shall round according to the conventions of IEC 559, e.g.:

REAL_TO_INT(1.6) is equivalent to 2
REAL_TO_INT(-1.6) is equivalent to -2
REAL_TO_INT(1.5) is equivalent to 2
REAL_TO_INT(-1.5) is equivalent to -2
REAL_TO_INT(1.4) is equivalent to 1
REAL_TO_INT(-1.4) is equivalent to -1
REAL_TO_INT(2.5) is equivalent to 2
REAL_TO_INT(-2.5) is equivalent to -2

3 The function TRUNC shall be used for truncation toward zero of a REAL or LREAL, yielding one of the integer types, for instance,

TRUNC(1.6) is equivalent to 1
TRUNC(-1.6) is equivalent to -1
TRUNC(1.4) is equivalent to 1
TRUNC(-1.4) is equivalent to -1

4 The conversion functions *_TO_BCD and BCD_TO_** are defined to perform conversions between variables of type BYTE, WORD, DWORD, and LWORD and variables of type SINT, INT, and DINT (represented by "**"), when the corresponding bit-string variables contain data encoded in BCD format. For example, the value of INT_TO_BCD(25) would be 2#0010_0101, and the value of BCD_TO_INT (2#0011_0110_1001) would be 369.

5 When an input or output of a type conversion function is of type STRING, the character string data shall conform to the external representation of the corresponding data, as specified in 2.2, in the ISO/IEC 646 character set.

6 Usage examples are given in the ST language defined in 3.3.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.5.1.5.2 *Numerical functions*

The standard graphical representation, function names, input and output variable types, and function descriptions of functions of a single numeric variable shall be as defined in table 23. These functions shall be overloaded on the defined generic types, and can be typed as defined in 2.5.1.4. For these functions, the types of the input and output shall be the same.


The standard graphical representation, function names and symbols, and descriptions of arithmetic functions of two or more variables shall be as shown in table 24. These functions shall be overloaded on all numeric types, and can be typed as defined in 2.5.1.4.

Table 23 – Standard functions of one numeric variable

Graphical form			Usage example
+----------+ *---| ** |---* +----------+ (*) – Input/Output (I/O) type (**) – Function name			A := SIN(B) ; (ST language – see 3.3)
No.	**Function name**	**I/O type**	**Description**
	General functions		
1	ABS	ANY_NUM	Absolute value
2	SQRT	ANY_REAL	Square root
	Logarithmic functions		
3	LN	ANY_REAL	Natural logarithm
4	LOG	ANY_REAL	Logarithm base 10
5	EXP	ANY_REAL	Natural exponential
	Trigonometric functons		
6	SIN	ANY_REAL	Sine of input in radians
7	COS	ANY_REAL	Cosine in radians
8	TAN	ANY_REAL	Tangent in radians
9	ASIN	ANY_REAL	Principal arc sine
10	ACOS	ANY_REAL	Principal arc cosine
11	ATAN	ANY_REAL	Principal arc tangent

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 24 – Standard arithmetic functions

Graphical form	Usage example
 (***) – Name or Symbol	A := ADD(B,C,D) ; or A := B+C+D ;

No.	Name	Symbol (note 1)	Description (notes 2 and 8)	
	Extensible arithmetic functions			
12	ADD	+	OUT := IN1 + IN2 +...+ INn	
13	MUL	*	OUT := IN1 * IN2 *...* INn	
	Non-extensible arithmetic functions			
14	SUB	–	OUT := IN1 – IN2	
15	DIV	/	OUT := IN1 / IN2	(note 5)
16	MOD		OUT := IN1 modulo IN2	(note 3)
17	EXPT	**	Exponentiation: OUT := $IN1^{IN2}$	(note 4)
18	MOVE	:=	OUT := IN	(note 9)

NOTES

1 These symbols are suitable for use as operators in textual languages, as shown in tables 52 and 55.

2 The notations IN1, IN2, ..., INn refer to the inputs in top-to-bottom order; OUT refers to the output.

3 IN1 and IN2 shall be of generic type ANY_INT for this function. The result of evaluating this function shall be the equivalent of executing the following statements in the ST language as defined in 3.3:

IF (IN2 = 0) THEN OUT := 0 ; ELSE OUT := IN1 - (IN1/IN2)*IN2 ; END_IF

4 IN1 shall be of type ANY_REAL, and IN2 of type ANY_NUM for this function. The output shall be of the same type as IN1.

5 The result of division of integers shall be an integer of the same type with truncation toward zero, for instance, 7/3 = 2 and (-7)/3 = -2.

6 When the named representation of a function is supported, this shall be indicated by the suffix "n" in the compliance statement. For example, "12n" represents the notation "ADD".

7 When the symbolic representation of a function is supported, this shall be indicated by the suffix "s" in the compliance statement. For example, "12s" represents the notation "+".

8 Usage examples and descriptions are given in the ST language defined in 3.3.

9 The MOVE function has exactly one input (IN) of type ANY and one output (OUT) of type ANY.


Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

2.5.1.5.3 *Bit-string functions*

The standard graphical representation, function names and descriptions of shift functions for a single bit-string variable shall be as defined in table 25. These functions shall be overloaded on all bit-string types, and can be typed as defined in 2.5.1.4.

The standard graphical representation, function names and symbols, and descriptions of bitwise Boolean functions shall be as defined in table 26. These functions shall be extensible, except for NOT, and overloaded on all bit-string types, and can be typed as defined in 2.5.1.4.

Table 25 – Standard bit-shift functions

Graphical form	Usage example
 (***) – Function Name	A := SHL(IN := B, N := 5) ; (ST language – see 3.3)

No.	Name	Description
1	SHL	OUT := IN left-shifted by N bits, zero-filled on right
2	SHR	OUT := IN right-shifted by N bits, zero-filled on left
3	ROR	OUT := IN right-rotated by N bits, circular
4	ROL	OUT := IN left-rotated by N bits, circular

NOTE – The notation "OUT" refers to the function output.

2.5.1.5.4 *Selection and comparison functions*


Selection and comparison functions shall be overloaded on all data types. The standard graphical representations, function names and descriptions of selection functions shall be as shown in table 27.

The standard graphical representation, function names and symbols and descriptions of comparison functions shall be as defined in table 28. All comparison functions (except NE) shall be extensible.

Comparisons of bit-string data shall be made bitwise from the most significant to the least significant bit, and shorter bit strings shall be considered to be filled on the left with zeros when compared to longer bit strings; that is, comparison of bit-string variables shall have the same result as comparison of unsigned integer variables.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 26 – Standard bitwise Boolean functions

Graphical form	Usage example
 (***) – Name or symbol	A := AND(B,C,D) ; or A := B & C & D ;

No.	Name	Symbol	Description
5	AND	& (note 1)	OUT := IN1 & IN2 & ... & INn
6	OR	>=1 (note 2)	OUT := IN1 OR IN2 OR ... OR INn
7	XOR	=2k+1 (note 2)	OUT := IN1 XOR IN2 XOR ... XOR INn
8	NOT		OUT := NOT IN1 (note 4)

NOTES

1 This symbol is suitable for use as an operator in textual languages, as shown in tables 52 and 55.

2 This symbol is not suitable for use as an operator in textual languages.

3 The notations IN1, IN2, ..., INn refer to the inputs in top-to-bottom order; OUT refers to the output.

4 Graphic negation of signals of type BOOL can also be accomplished as shown in table 19.






5 When the named representation of a function is supported, this shall be indicated by the suffix "n" in the compliance statement. For example, "5n" represents the notation "AND".

6 When the symbolic representation of a function is supported, this shall be indicated by the suffix "s" in the compliance statement. For example, "5s" represents the notation "&".

7 Usage examples and descriptions are given in the ST language defined in 3.3.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 27 – Standard selection functions

No.	Graphical form	Explanation/example
1		**Binary selection:** OUT := IN0 if G = 0 OUT := IN1 if G = 1 **Example:** A := SEL(G := 0, IN0 := X, IN1 := 5) ;
2a		**Extensible maximum function:** OUT := MAX(IN1,IN2,...,INn) **Example:** A := MAX(B,C,D) ;
2b		**Extensible minimum function:** OUT := MIN(IN1,IN2,...,INn) **Example:** A := MIN(B,C,D) ;
3		**Limiter:** OUT := MIN(MAX(IN,MN),MX) **Example:** A := LIMIT(IN := B, MN := 0, MX := 5) ;
4		**Extensible multiplexer:** Select one of "N" inputs depending on input K **Example:** A :=MUX(K := 0, IN0 :=B, IN1 := C, IN2 := D) ; would have the same effect as A := B ;

NOTES


1 These inputs can be of type ANY_BIT, ANY_NUM, STRING, ANY_DATE, or TIME. The type conversion rules given in 2.5.1.4 shall be followed for these inputs.

2 The notations IN1, IN2, ..., INn refer to the inputs in top-to-bottom order; OUT refers to the output.

3 Usage examples and descriptions are given in the ST language defined in 3.3.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 28 – Standard comparison functions

Graphical form	Usage examples
 (***) – Name or Symbol	A := GT(B,C,D) ; or A := (B>C) & (C>D) ;

No.	Name	Symbol	Description
5	GT	>	Decreasing sequence: OUT := (IN1>IN2) & (IN2>IN3) & ... & (INn-1 > INn)
6	GE	>=	Monotonic sequence: OUT := (IN1>=IN2) & (IN2>=IN3) & ... & (INn-1 >= INn)
7	EQ	=	Equality: OUT := (IN1=IN2) & (IN2=IN3) & ... & (INn-1 = INn)
8	LE	<=	Monotonic sequence: OUT := (IN1<=IN2) & (IN2<=IN3) & ... & (INn-1 <= INn)
9	LT	<	Increasing sequence: OUT := (IN1<IN2) & (IN2<IN3) & ... & (INn-1 < INn)
10	NE	<>	Inequality (non-extensible) OUT := (IN1 <> IN2)

NOTES

1 These inputs can be of type ANY_BIT, ANY_NUM, STRING, ANY_DATE, or TIME. The type conversion rules given in 2.5.1.4 shall be followed for these inputs.

2 The notations IN1, IN2, ..., INn refer to the inputs in top-to-bottom order; OUT refers to the output.

3 All the symbols shown in this table are suitable for use as operators in textual languages, as shown in tables 52 and 55.

4 When the named representation of a function is supported, this shall be indicated by the suffix "n" in the compliance statement. For example, "5n" represents the notation "GT".

5 When the symbolic representation of a function is supported, this shall be indicated by the suffix "s" in the compliance statement. For example, "5s" represents the notation ">".

6 Usage examples and descriptions are given in the ST language defined in 3.3.

2.5.1.5.5 *Character string functions*









All the functions defined in 2.5.1.5.4 shall be applicable to character strings. For the purposes of comparison of two strings of unequal length, the shorter string shall be considered to be extended on the right to the length of the longer string by characters with the value zero. Comparison shall proceed from left to right, based on the numeric value of the character codes in the ISO/IEC 646 code table. For example, the character string 'Z' shall be greater than the character string 'AZ', and 'AZ' shall be greater than 'ABC'.

The standard graphical representations, function names and descriptions of additional functions of character strings shall be as shown in table 29. For the purpose of these operations, character positions within the string shall be considered to be numbered 1,2,...,L, beginning with the leftmost character position, where L is the length of the string.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

Table 29 – Standard character string functions

No.	Graphical form	Explanation/example
1		String length function Example: A := LEN ('ASTRING') ; is equivalent to A := 7 ;
2		Leftmost L characters of IN Example: A := LEFT(IN := 'ASTR', L := 3) ; is equivalent to A := 'AST' ;
3		Rightmost L characters of IN Example: A := RIGHT(IN := 'ASTR', L := 3) ; is equivalent to A := 'STR' ;
4		L characters of IN, beginning at the P-th Example: A := MID(IN := 'ASTR', L := 2, P := 2) ; is equivalent to A := 'ST' ;
5		Extensible concatenation Example: A := CONCAT ('AB', 'CD', 'E') ; is equivalent to A := 'ABCDE' ;
6		Insert IN2 into IN1 after the P-th character position Example: A := INSERT(IN1 := 'ABC', IN2 := 'XY', P := 2) ; is equivalent to A := 'ABXYC' ;
7		Delete L characters of IN, beginning at the P-th character position Example: A := DELETE(IN := 'ABXYC', L := 2, P:=3) ; is equivalent to A := 'ABC' ;
8		Replace L characters of IN1 by IN2, starting at the P-th character position Example: A := REPLACE(IN1 := 'ABCDE', IN2 := 'X', L := 2, P := 3) ; is equivalent to A := 'ABXE' ;
9		Find the character position of the beginning of the first occurrence of IN2 in IN1. If no occurrence of IN2 is found, then OUT := 0 Example: A := FIND(IN1 := 'ABCBC', IN2 := 'BC') ; is equivalent to A := 2 ;

NOTE - The examples in this table are given in the Structured Text (ST) language defined in 3.3.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.5.1.5.6 *Functions of time data types*

In addition to the comparison and selection functions defined in 2.5.1.5.4, the combinations of input and output time data types shown in table 30 shall be allowed with the associated functions.

2.5.1.5.7 *Functions of enumerated data types*

The selection and comparison functions listed in table 31 can be applied to inputs which are of an enumerated data type as defined in 2.3.3.1.

Table 30 – Functions of time data types

Numeric and concatenation functions					
No.	Name	Symbol	IN1	IN2	OUT
1	ADD	+	TIME	TIME	TIME
2			TIME_OF_DAY	TIME	TIME_OF_DAY
3			DATE_AND_TIME	TIME	DATE_AND_TIME
4	SUB	–	TIME	TIME	TIME
5			DATE	DATE	TIME
6			TIME_OF_DAY	TIME	TIME_OF_DAY
7			TIME_OF_DAY	TIME_OF_DAY	TIME
8			DATE_AND_TIME	TIME	DATE_AND_TIME
9			DATE_AND_TIME	DATE_AND_TIME	TIME
10	MUL	*	TIME	ANY_NUM	TIME
11	DIV	/	TIME	ANY_NUM	TIME
12	CONCAT		DATE	TIME_OF_DAY	DATE_AND_TIME
	Type conversion functions				
13	DATE_AND_TIME_TO_TIME_OF_DAY				
14	DATE_AND_TIME_TO_DATE				

NOTE - The type conversion functions shall have the effect of "extracting" the appropriate data, e.g., the ST language statements

```
X := DT#1986-04-28-08:40:00 ;
Y := DATE_AND_TIME_TO_TIME_OF_DAY(X) ;
W := DATE_AND_TIME_TO_DATE(X)
```

shall have the same result as the statements

```
X := DT#1986-04-28-08:40:00 ;
W := DATE#1986-04-28 ;
Y := TIME_OF_DAY#08:40:00
```

Table 31 – Functions of enumerated data types

No.	Name	Symbol	Feature number in 2.5.1.5.4
1	SEL		1
2	MUX		4
3	EQ	=	7
4	NE	<>	10

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.5.2 *Function blocks*

For the purposes of programmable controller programming languages, a *function block* is a program organization unit which, when executed, yields one or more values. Multiple, named *instances* (copies) of a function block can be created. Each instance shall have an associated identifier (the *instance name*), and a data structure containing its output and internal variables, and, depending on the implementation, values of or references to its input parameters. All the values of the output variables and the necessary internal variables of this data structure shall persist from one execution of the function block to the next; therefore, invocation of the same function block with the same arguments (input parameters) need not always yield the same output values.

Only the input and output parameters shall be accessible outside of an instance of a function block, i.e., the function block's internal variables shall be hidden from the user of the function block.

Execution of the operations of a function block shall be invoked as defined in clause 3 for textual languages, according to the rules of network evaluation given in clause 4 for graphic languages, or under the control of sequential function chart (SFC) elements as defined in 2.6.

Any function block which has already been declared can be used in the declaration of another function block or program as shown in figure 3.

The scope of an instance of a function block shall be local to the program organization unit in which it is instantiated, unless it is declared to be global in a VAR_GLOBAL block as defined in 2.7.1.

As illustrated in 2.5.2.2, the instance name of a function block instance can be used as the input to a function or function block if declared as an input variable in a VAR_INPUT declaration, or as an input/output variable of a function block in a VAR_IN_OUT declaration, as defined in 2.4.3.

2.5.2.1 *Representation*

As illustrated in figure 9, an instance of a function block can be created *textually*, by declaring a data element using the declared function block type in a VAR...END_VAR construct, identically to the use of a structured data type, as defined in 2.4.3.

As further illustrated in figure 9, an instance of a function block can be created *graphically*, by using a graphic representation of the function block, with the function block type name inside the block, and the instance name above the block, following the rules for representation of functions given in 2.5.1.1 with the following additional conditions:

1) The size and orientation of the block may vary depending on the number of inputs, outputs, and other information to be displayed.

2) Formal input and output parameter names shall be shown at the inside left and right sides of the block, respectively.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

As shown in figure 9, input and output variables of an instance of a function block can be represented as elements of structured data types as defined in 2.3.6.1.

If either of the two graphical negation features defined in table 19 is supported for function blocks, it shall also be supported for functions as defined in 2.5.1, and vice versa.

Function block instances can be declared to be retentive, as shown in feature 3 of table 33.


Graphical (FBD language)	Textual (ST language)
	VAR FF75 : SR ; END_VAR (* Declaration *) FF75(S1 := %IX1, R := %IX2) ; (* Invocation *) %QX3 := FF75.Q1 ; (* Assign Output *)

Figure 9 – Function block instantiation example

Assignment of a value to an output variable of a function block is not allowed except from within the function block. The assignment of a value to the input of a function block is permitted only as part of the invocation of the function block. Allowable usages of function block inputs and outputs are summarized in table 32, using the function block FF75 of type SR shown in figure 9. The examples are shown in the ST language.

Table 32 – Examples of function block I/O parameter usage

Usage	Inside function block	Outside function block
Input Read	IF S1 THEN	Not allowed (note 1 and 2)
Input Write	Not allowed (notes 1 and 3)	FF75(S1 := %IX1, R := %IX2) ;
Output Read	Q1 := Q1 AND NOT R ;	%QX3 := FF75.Q1 ;
Output Write	Q1 := 1 ;	Not allowed (note 1)

NOTES

1 Those usages listed as "not allowed" in this table could lead to implementation-dependent, unpredictable side effects.

2 Reading of an input of a function block may be performed by the "communication function", "operator interface function", or the "programming, testing, and monitoring functions" defined in part 1 of this standard.

3 As illustrated in 2.5.2.2, modification within the function block of a variable declared in a VAR_IN_OUT block is permitted.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

2.5.2.2 *Declaration*

As illustrated in figure 10, a function block shall be declared textually or graphically in the same manner as defined for functions in 2.5.1.3, with the differences described below and summarized in table 33.

1) The delimiting keywords for declaration of function blocks shall be FUNCTION_BLOCK...END_FUNCTION_BLOCK.

2) A function block can have more than one output parameter, declared textually with the VAR_OUTPUT...END_VAR construct defined in 2.4.3, or graphically as illustrated in figure 10.

3) The RETAIN qualifier defined in 2.4.3 can be used for internal and output variables of a function block, as shown in features 1, 2, and 3 in table 33.

4) The values of variables which are passed to the function block via a VAR_IN_OUT or VAR_EXTERNAL construct can be modified from within the function block, as shown in feature 4 of table 33.

5) The output values of a function block instance whose name is passed into the function block via a VAR_INPUT, VAR_IN_OUT, or VAR_EXTERNAL construct can be accessed, but not modified, from within the function block, as shown in features 5, 6, and 7 of table 33.

6) A function block whose instance name is passed into the function block via a VAR_IN_OUT or VAR_EXTERNAL construction can be invoked from inside the function block, as shown in features 6 and 7 of table 33.

7) In textual declarations, the R_EDGE and F_EDGE qualifiers can be used to indicate an edge-detection function on Boolean inputs. This shall cause the implicit declaration of a function block of type R_TRIG or F_TRIG, respectively, as defined in 2.5.2.3.2, to perform the required edge detection. For an example of this construction, see features 8a and 8b of table 33 and the accompanying NOTE.

8) The construction illustrated in table 33, features 9a and 9b shall be used in graphical declarations for rising and falling edge detection. When the ISO/IEC 646 character set is used, the "greater than" (>) or "less than" (<) character shall be in line with the edge of the function block. When graphic or semigraphic representations are employed, the notation of IEC 617, part 12 for dynamic inputs shall be used.

9) The variable initialization constructs defined in 2.4.3.2 can be used for the declaration of default values of function block inputs and initial values of their internal and output variables.

As illustrated in figure 12, only variables or function block instance names can be passed into a function block via the VAR_IN_OUT construct, i.e., function or function block outputs cannot be passed via this construction. This is to prevent the inadvertent modifications of such outputs. However, "cascading" of VAR_IN_OUT constructions is permitted, as illustrated in figure 12c.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

a)

```
FUNCTION_BLOCK DEBOUNCE
(*** External Interface ***)

  VAR_INPUT
    IN : BOOL ;                    (* Default = 0 *)
    DB_TIME : TIME := t#10ms ;     (* Default = t#10ms *)
  END_VAR
  VAR_OUTPUT OUT : BOOL ;          (* Default = 0 *)
      ET_OFF : TIME ;              (* Default = t#0s *)
  END_VAR
  VAR DB_ON : TON ;                (** Internal Variables **)
      DB_OFF : TON ;               (** and FB Instances **)
      DB_FF : SR ;
  END_VAR

(** Function Block Body**)

DB_ON(IN := IN, PT := DB_TIME) ;
DB_OFF(IN := NOT IN, PT := DB_TIME) ;
DB_FF(S1 := DB_ON.Q, R := DB_OFF.Q) ;
OUT := DB_FF.Q ;
ET_OFF := DB_OFF.ET ;
END_FUNCTION_BLOCK
```

b)

```
FUNCTION_BLOCK
(** External Interface **)

                          +---------------+
                          |   DEBOUNCE    |
                   BOOL---|IN          OUT|---BOOL
                   TIME---|DB_TIME  ET_OFF|---TIME
                          +---------------+

(** Function Block Body **)

                            DB_ON       DB_FF
                           +-----+     +-----+
                           | TON |     | SR  |
              IN-----+-----|IN  Q|-----|S1  Q|---OUT
                     |  +---|PT ET|  +--|R    |
                     |  |   +-----+  |  +-----+
                     |  |            |
                     |  |   DB_OFF   |
                     |  |   +-----+  |
                     |  |   | TON |  |
                     +--|--O|IN  Q|--+
              DB_TIME--+---|PT ET|--------------ET_OFF
                           +-----+

END_FUNCTION_BLOCK
```

Figure 10 – Examples of function block declarations
a) Textual declaration in ST language (see 3.3)
b) Graphical declaration in FBD language (see 4.3)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 33 – Function block declaration features

No.	Description	Example
1	RETAIN qualifier on internal variables	VAR RETAIN X : REAL ; END_VAR
2	RETAIN qualifier on output variables	VAR_OUTPUT RETAIN X : REAL ; END_VAR
3	RETAIN qualifier on internal function blocks	VAR RETAIN TMR1 : TON ; END_VAR
4a	Input/output declaration (textual)	VAR_INPUT X : INT ; END_VAR VAR_IN_OUT A : INT ; END_VAR A := A+X ;
4b	Input/output declaration (graphical)	See figure 12
5a	Function block instance name as input (textual)	VAR_INPUT I_TMR : TON ; END_VAR EXPIRED := I_TMR.Q ; (* Note 1 *)
5b	Function block instance name as input (graphical)	See figure 11a
6a	Function block instance name as input/output (textual)	VAR_IN_OUT IO_TMR : TOF ; END_VAR IO_TMR(IN := A_VAR, PT := T#10S) ; EXPIRED := I_TMR.Q ; (* Note 1 *)
6b	Function block instance name as input/output (graphical)	See figure 11b
7a	Function block instance name as external variable (textual)	VAR_EXTERNAL EX_TMR : TOF ; END_VAR EX_TMR(IN := A_VAR, PT := T#10S) ; EXPIRED := EX_TMR.Q ; (* Note 1 *)
7b	Function block instance name as external variable (graphical)	See figure 11c
8a 8b	Textual declaration of: rising edge inputs falling edge inputs	FUNCTION_BLOCK AND_EDGE (* Note 2 *) VAR_INPUT X : BOOL R_EDGE ; Y : BOOL F_EDGE ; END_VAR VAR_OUTPUT Z : BOOL ; END_VAR Z := X AND Y ; (* ST language example *) END_FUNCTION_BLOCK (* - see 3.3 *)
9a 9b	Graphical declaration of: rising edge inputs falling edge inputs	FUNCTION_BLOCK (* Note 2 *) +----------+ (* External interface *) | AND_EDGE | BOOL--->X Z|---BOOL | | BOOL---<Y | | | +----------+ +---+ (* Function block body *) X---| & |---Z (* FBD language example *) Y---| | (* - see 4.3 *) +---+ END_FUNCTION_BLOCK

NOTES

1 It is assumed in these examples that the variables EXPIRED and A_VAR have been declared of type BOOL.

2 The declaration of function block AND_EDGE in the above examples is equivalent to:

```
FUNCTION_BLOCK AND_EDGE
  VAR_INPUT XCLK : BOOL ; YCLK : BOOL ; END_VAR
  VAR X_TRIG : R_TRIG ; Y_TRIG : F_TRIG ; END_VAR
  X_TRIG(CLK := XCLK) ; X := X_TRIG.Q ;
  Y_TRIG(CLK := YCLK) ; Y := Y_TRIG.Q ;
  Z := X AND Y ;
END_FUNCTION_BLOCK
```

See 2.5.2.3.2 for the definition of the edge detection function blocks R_TRIG and F_TRIG.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

```
FUNCTION_BLOCK

      +---------------+           (* External interface*)
      |   INSIDE_A    |
TON---|I_TMR  EXPIRED|---BOOL
      +---------------+


            I_TMR                 (* Function Block body *)
           +-----+
           | TON |
           |IN  Q|---EXPIRED
           |PT ET|
           +-----+

END_FUNCTION_BLOCK
```

```
FUNCTION_BLOCK

       +---------------+          (* External interface *)
       |  EXAMPLE_A    |
BOOL---|GO         DONE|---BOOL
       +---------------+


            E_TMR                 (* Function Block body *)
           +-----+                     I_BLK
           | TON |                +---------------+
      GO---|IN  Q|                |   INSIDE_A    |
 t#100ms---|PT ET|     E_TMR------|I_TMR  EXPIRED|---DONE
           +-----+                +---------------+

END_FUNCTION_BLOCK
```

Figure 11a – Graphical use of a function block name as an input variable (table 33, feature 5b)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale




Figure 11b – Graphical use of a function block name as an input/output variable (table 33, feature 6b)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

```
FUNCTION_BLOCK

       +---------------+              (* External interface*)
       |   INSIDE_C    |
BOOL---|TMR_GO EXPIRED|---BOOL
       +---------------+

VAR_EXTERNAL X_TMR : TON ; END_VAR


             X_TMR                    (* Function Block body *)
            +------+
            | TON  |
  TMR_GO--- |IN  Q|---EXPIRED
            |PT ET|
            +------+

END_FUNCTION_BLOCK
```

```
PROGRAM

        +---------------+             (* External interface *)
        |  EXAMPLE_C    |
 BOOL---|GO         DONE|---BOOL
        +---------------+

VAR_GLOBAL X_TMR : TON ; END_VAR


             I_BLK                    (* Program body *)
        +----------------+
        |   INSIDE_C     |
GO------|TMR_GO  EXPIRED|---DONE
        +----------------+


END_PROGRAM
```

NOTE - PROGRAM declaration is defined in 2.5.3

Figure 11c - Graphical use of a function block name as an external variable (table 33, feature 7b)


Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

a)





```
FUNCTION_BLOCK ACCUM
  VAR_IN_OUT A : INT ; END_VAR
  VAR_INPUT X : INT ; END_VAR
  A := A+X ;
END_FUNCTION_BLOCK
```

b)




Note 1

c)



Note 2

d)



Note 3

NOTES

1 A declaration such as

```
VAR
   ACC : INT ;
   X1 : INT ;
   X2 : INT ;
END_VAR
```

is assumed.

2 Declarations as in b) are assumed for ACC, X1, X2, X3 and X4.

3 ILLEGAL USAGE:
Input/output A is not a variable or function block name (see preceding text).

Figure 12 – Examples of use of input/output variables
a) Graphical and textual declarations
b, c) Legal usage
d) Illegal usage

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.5.2.3 *Standard function blocks*

Definitions of function blocks common to all programmable controller programming languages are given in this subclause.

Where graphical declarations of standard function blocks are shown in this subclause, equivalent textual declarations, as specified in 2.5.2.2, can also be written, as for example in table 35.

2.5.2.3.1 *Bistable elements*

The representation and function block bodies for standard bistable elements are shown in table 34. The notation for these elements is chosen to be as consistent as possible with symbols 12-09-01 and 12-09-02 of IEC 617-12.









Figure 13 – Semaphore usage example (see note 4 of table 34)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 34 – Standard bistable function blocks

<table>
<tr><th>No.</th><th>Graphical form</th><th>Function block body</th></tr>
<tr><td>1</td><td colspan="2">Bistable Function Block (set dominant) (notes 1 and 2)</td></tr>
<tr><td></td><td>
</td><td>
</td></tr>
<tr><td>2</td><td colspan="2">Bistable Function Block (reset dominant) (notes 1 and 2)</td></tr>
<tr><td></td><td>
</td><td>
</td></tr>
<tr><td>3</td><td colspan="2">Semaphore with non-interruptible "Test and Set" (notes 3, 4, 5 and 6)</td></tr>
<tr><td></td><td>
</td><td>VAR X : BOOL := 0 ; END_VAR
BUSY := X ;
IF CLAIM THEN X := 1 ;
ELSIF RELEASE THEN BUSY := 0 ; X := 0 ;
END_IF</td></tr>
</table>

NOTES

1 The function block body is specified in the Function Block Diagram (FBD) language defined in 4.3.

2 The initial state of the output variable Q1 shall be the normal default value of zero for Boolean variables.

3 The function block body is specified in the Structured Text (ST) language defined in 3.3.

4 This function block is intended to be used for controlling access to operating system resources; therefore, the first two statements in the function block body, namely,

BUSY := X ; IF CLAIM THEN X := 1;

shall be non-interruptible.

5 User programs must co-operate in such a way that only the "owner" of a semaphore, that is, the most recent entity to successfully assert a CLAIM on a non-BUSY semaphore, can RELEASE the semaphore.

6 Figure 13 shows a program fragment using a semaphore declared as VAR_GLOBAL to control access to a printer resource, using SFC elements (see 2.6).

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale



2.5.2.3.2 *Edge detection*

The graphic representation of standard rising- and falling-edge detecting function blocks shall be as shown in table 35. The behaviors of these blocks shall be equivalent to the definitions given in this table. This behavior corresponds to the following rules:

1) The "Q" output of an R_TRIG function block shall stand at the Boolean "1" value from one execution of the function block to the next, following the "0" to "1" transition of the "CLK" input, and shall return to "0" at the next execution.

2) The "Q" output of an F_TRIG function block shall stand at the Boolean "1" value from one execution of the function block to the next, following the "1" to "0" transition of the "CLK" input, and shall return to "0" at the next execution.

Table 35 – Standard edge detection function blocks




No.	Graphical form	Definition (ST language – see 3.3)
1	Rising edge detector	
		FUNCTION_BLOCK R_TRIG VAR_INPUT CLK : BOOL ; END_VAR VAR_OUTPUT Q : BOOL ; END_VAR VAR M : BOOL := 0 ; END_VAR Q := CLK AND NOT M ; M := CLK ; END_FUNCTION_BLOCK
2	Falling edge detector	
		FUNCTION_BLOCK F_TRIG VAR_INPUT CLK : BOOL ; END_VAR VAR_OUTPUT Q : BOOL ; END_VAR VAR M : BOOL := 1 ; END_VAR Q := NOT CLK AND NOT M ; M := NOT CLK ; END_FUNCTION_BLOCK

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.5.2.3.3 *Counters*

The graphic representations of standard counter function blocks, with the types of the associated inputs and outputs, shall be as shown in table 36. The operation of these function blocks shall be as specified in the corresponding function block bodies.

Table 36 – Standard counter function blocks

No.	Graphical form	Function block body (ST language – see 3.3)
1	**Up-counter**	
		IF R THEN CV := 0 ; ELSIF CU AND (CV < PVmax) THEN CV := CV+1 ; END_IF ; Q := (CV >= PV) ;
2	**Down-counter**	
		IF LD THEN CV := PV ; ELSIF CD AND (CV > PVmin) THEN CV := CV-1 ; END_IF ; Q := (CV <= 0) ;
3	**Up-down counter**	
		IF R THEN CV := 0 ; ELSIF LD THEN CV := PV ; ELSIF CU AND (CV < PVmax) THEN CV := CV+1 ; ELSIF CD AND (CV > PVmin) THEN CV := CV-1 ; END_IF ; QU := (CV >= PV) ; QD := (CV <= 0) ;
NOTE - The numerical values of the limit variables PVmin and PVmax are implementation-dependent.		

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.5.2.3.4 *Timers*

The graphic form for standard timer function blocks shall be as shown in table 37. The operation of these function blocks shall be as defined in the timing diagrams given in table 38.

Table 37 – Standard timer function blocks

No.	Description	Graphic form
1	***is: TP (Pulse)	+--------+ | *** | BOOL--- |IN Q|---BOOL TIME--- |PT ET|---TIME +--------+
2a	TON (On-delay)	
2b	T---0 (On-delay)	
3a	TOF (Off-delay)	
3b	0---T (Off-delay)	
4	Real-time clock	
	PDT = Preset date and time, loaded on rising edge of EN CDT = Current date and time, valid when EN=1 Q = copy of EN	+--------+ | RTC | BOOL--- |EN Q|---BOOL DT----- |PDT CDT|-----DT +--------+


NOTE - In textual languages, features 2b and 3b shall not be used.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS


Not for Resale

Table 38 – Standard timer function blocks – timing diagrams


Pulse (TP) timing



On-delay (TON) timing



Off-delay (TOF) timing



Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.5.2.3.5 *Communication function blocks*

Standard communication function blocks for programmable controllers are defined in IEC 1131-5. These function blocks provide programmable communications functionality such as device verification, polled data acquisition, programmed data acquisition, parametric control, interlocked control, programmed alarm reporting, and connection management and protection.

2.5.3 *Programs*

A *program* is defined in IEC 1131-1 as a "logical assembly of all the programming language elements and constructs necessary for the intended signal processing required for the control of a machine or process by a programmable controller system."

Subclause 1.4.1 of this part describes the place of programs in the overall software model of a programmable controller; subclause 1.4.2 describes the means available for inter- and intra-program communication; and subclause 1.4.3 describes the overall process of program development.

The declaration and usage of *programs* is identical to that of *function blocks* as defined in 2.5.2.1 and 2.5.2.2, with the additional features shown in table 39 and the following differences:

1) The delimiting keywords for program declarations shall be PROGRAM...END_PROGRAM.

2) A program can contain a VAR_ACCESS...END_VAR construction, which provides a means of specifying named variables which can be accessed by some of the communication services specified in IEC 1131-5. An *access path* associates each such variable with an input, output or internal variable of the program. The format and usage of this declaration shall be as described in 2.7.1 and in IEC 1131-5.

3) *Programs* can only be instantiated within *resources*, as defined in 2.7.1, while *function blocks* can only be instantiated within *programs* or other *function blocks*.

The declaration and use of programs are illustrated in figure 19, and in examples F.7 and F.8 of annex F.

Table 39 – Program declaration features

No.	Description
1 to 9b	Same as features 1 to 9b, respectively, of table 33
10	Formal input and output parameters
11 to 14	Same as features 1 to 4, respectively, of table 17
15 to 18	Same as features 1 to 4, respectively, of table 18
19	Use of directly represented variables (see 2.4.1.1)
20	VAR_GLOBAL ... END_VAR declaration within a PROGRAM (see 2.4.3 and 2.7.1)
21	VAR_ACCESS .. END_VAR declaration within a PROGRAM

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.6 *Sequential Function Chart (SFC) elements*

2.6.1 *General*

This subclause defines *sequential function chart* (SFC) elements for use in structuring the internal organization of a programmable controller program organization unit, written in one of the languages defined in this standard, for the purpose of performing *sequential control* functions. The definitions in this subclause are derived from IEC 848, with the changes necessary to convert the representations from a *documentation standard* to a set of *execution control elements* for a programmable controller program organization unit.

The SFC elements provide a means of partitioning a programmable controller program organization unit into a set of *steps* and *transitions* interconnected by *directed links*. Associated with each step is a set of *actions*, and with each transition is associated a *transition condition*.

Since SFC elements require storage of state information, the only program organization units which can be structured using these elements are *function blocks* and *programs*.

If any part of a program organization unit is partitioned into SFC elements, the entire program organization unit shall be so partitioned. If no SFC partitioning is given for a program organization unit, the entire program organization unit shall be considered to be a single *action* which executes under the control of the invoking entity.

2.6.2 *Steps*

A *step* represents a situation in which the behavior of a program organization unit with respect to its inputs and outputs follows a set of rules defined by the associated *actions* of the step. A step is either *active* or *inactive*. At any given moment, the state of the program organization unit is defined by the set of active steps and the values of its internal and output variables.

As shown in table 40, a step shall be represented graphically by a block containing a *step name* in the form of an identifier as defined in 2.1.2, or textually by a STEP...END_STEP construction. The directed link(s) into the step can be represented graphically by a vertical line attached to the top of the step. The directed link(s) out of the step can be represented by a vertical line attached to the bottom of the step. Alternatively, the directed links can be represented textually by the TRANSITION...END_TRANSITION construction defined in 2.6.3.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

The *step flag* (active or inactive state of a step) can be represented by the logic value of a Boolean structure element ***.X, where *** is the step name, as shown in table 40. This Boolean variable has the value "1" when the corresponding step is active, and "0" when it is inactive. The state of this variable is available for graphical connection at the right side of the step as shown in table 40.

Similarly, the elapsed time, ***.T, since initiation of a step can be represented by a structure element of type TIME, as shown in table 40. When a step is deactivated, the value of the step elapsed time shall remain at the value it had when the step was deactivated. When a step is activated, the value of the step elapsed time shall be reset to t#0s.

The *scope* of step names, step flags, and step times shall be *local* to the program organization unit in which the steps appear.

The initial state of the program organization unit is represented by the initial values of its internal and output variables, and by its set of *initial steps*, i.e., the steps which are initially active. Each SFC *network*, or its textual equivalent, shall have exactly one initial step.



An initial step can be drawn graphically with double lines for the borders, and with the ISO/IEC 646 character set shall be drawn as shown in table 40.

For system initialization as defined in 2.4.2, the default initial elapsed time for steps is t#0s, and the default initial state is Boolean 0 for ordinary steps and Boolean 1 for initial steps. However, when an instance of a function block or a program is declared to be *retentive* (for instance, as in feature 3 of table 33), the states and (if supported) elapsed times of all steps contained in the program or function block shall be treated as retentive for system initialization as defined in 2.4.2.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

Table 40 – Step features

No.	Representation	Description
1		Step - Graphical form with directed links ***** = step name
		Initial step - Graphical form with directed links ***** = Name of initial step (note 2)
2	STEP *** : (* Step body *) END_STEP	Step - Textual form without directed links (see 2.6.3) ***** = Step name
	INITIAL_STEP *** : (* Step body *) END_STEP	Initial step - Textual form without directed links (see 2.6.3) ***** = Name of initial step
3a	***.X	Step flag - General form ***** = Step name ***.X = Boolean 1 when *** is active, Boolean 0 otherwise
3b		Step flag - Direct connection of Boolean variable ***.X to right side of step *****
4	***.T	Step elapsed time - General form ***** = Step name ***.T = A variable of type TIME (see 2.6.2)

NOTES

1 When feature 3a, 3b, or 4 is supported, it shall be an *error* if the user program attempts to modify the associated variable. For example, if S4 is a step name, then the following statements would be *errors* in the ST language defined in 3.3:

S4.X := 1 ; (* ERROR *)

S4.T := t#100ms ; (* ERROR *)

2 The upper directed link is not required if the initial step has no predecessors.

2.6.3 *Transition*

A *transition* represents the condition whereby control passes from one or more steps preceding the transition to one or more successor steps along the corresponding directed link. The transition shall be represented by a horizontal line across the vertical directed link.

The direction of evolution following the directed links shall be from the bottom of the predecessor step(s) to the top of the successor step(s).

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Each transition shall have an associated *transition condition* which is the result of the evaluation of a single Boolean expression. A transition condition which is always true shall be represented by the symbol "1" or the keyword TRUE.

A transition condition can be associated with a transition by one of the following means, as shown in table 41:

1) By placing the appropriate Boolean expression in the ST language defined in 3.3 to the right of the vertical directed link.

2) By a ladder diagram network in the LD language defined in 4.2, whose output intersects the vertical directed link instead of a right rail.

3) By a network in the FBD language defined in 4.3, whose output intersects the vertical directed link.

4) By a LD or FBD network whose output intersects the vertical directed link via a *connector* as defined in 4.1.1.

5) By a TRANSITION...END_TRANSITION construct using the ST language. This shall consist of:

- The keywords TRANSITION FROM followed by the step name of the predecessor step (or, if there is more than one predecessor, by a parenthesized list of predecessor steps);
- The keyword TO followed by the step name of the successor step (or, if there is more than one successor, by a parenthesized list of successor steps);
- The assignment operator (:=), followed by a Boolean expression in the ST language, specifying the transition condition;
- The terminating keyword END_TRANSITION.

6) By a TRANSITION...END_TRANSITION construct using the IL language defined in 3.2. This shall consist of:

- The keywords TRANSITION FROM followed by the step name of the predecessor step (or, if there is more than one predecessor, by a parenthesized list of predecessor steps), followed by a colon (':');
- The keyword TO followed by the step name of the successor step (or, if there is more than one successor, by a parenthesized list of successor steps);
- Beginning on a separate line, a list of instructions in the IL language, the result of whose evaluation determines the transition condition;
- The terminating keyword END_TRANSITION on a separate line.

7) By the use of a *transition name* in the form of an identifier to the right of the directed link. This identifier shall refer to a TRANSITION...END_TRANSITION construction defining one of the following entities, whose evaluation shall result in the assignment of a Boolean value to the variable denoted by the transition name:







- A network in the LD or FBD language;
- A list of instructions in the IL language;
- An assignment of a Boolean expression in the ST language.

The *scope* of a transition name shall be *local* to the program organization unit in which the transition is located.

It shall be an *error* in the sense of 1.5.1 if any "side effect" (for instance, the assignment of a value to a variable other than the transition name) occurs during the evaluation of a transition condition.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale




Table 41 – Transitions and transition conditions

No.	Example	Description
1		Predecessor step Transition condition using ST language (see 3.3) Successor step
2		Predecessor step Transition condition using LD language (see 4.2) Successor step
3		Predecessor step Transition condition using FBD language (see 4.3) Successor step
4		Use of connector: Predecessor step Transition connector Successor step
4a		Transition condition: Using LD language (see 4.2)
4b		Using FBD language (see 4.3)

(continued overleaf)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 41 *(concluded)*

No.	Example	Description
5	STEP STEP7 : END_STEP TRANSITION FROM STEP7 TO STEP 8 := %IX2.4 & %IX2.3 ; END_TRANSITION STEP STEP8 : END_STEP	Textual equivalent of feature 1 using ST language (see 3.3)
6	STEP STEP7 : END_STEP TRANSITION FROM STEP7 TO STEP 8: LD %IX2.4 AND %IX2.3 END_TRANSITION STEP STEP8 : END_STEP	Textual equivalent of feature 1 using IL language (see 3.2)
7		Use of transition name: Predecessor step Transition name Successor step
7a	TRANSITION TRAN78 :  END_TRANSITION	Transition condition using LD language (see 4.2)
7b	TRANSITION TRAN78 :  END_TRANSITION	Transition condition using FBD language (see 4.3)
7c	TRANSITION TRAN78 : LD %IX2.4 AND %IX2.3 END_TRANSITION	Transition condition using IL language (see 3.2)
7d	TRANSITION TRAN78 : := %IX2.4 & %IX2.3 ; END_TRANSITION	Transition condition using ST language (see 3.3)

NOTES

1 If feature 1 of table 40 is supported, then one or more of features 1, 2, 3, 4, or 7 of this table shall be supported.

2 If feature 2 of table 40 is supported, then feature 5 or 6 of this table, or both, shall be supported.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

2.6.4 *Actions*

Zero or more *actions* shall be associated with each step. A step which has zero associated actions shall be considered as having a WAIT function, that is, waiting for a successor transition condition to become true.

An action can be a Boolean variable, a collection of *instructions* in the IL language defined in 3.2, a collection of *statements* in the ST language defined in 3.3, a collection of *rungs* in the LD language defined in 4.2, a collection of *networks* in the FBD language defined in 4.3, or a *sequential function chart* (SFC) organized as defined in this subclause (2.6).




Actions shall be declared via one or more of the mechanisms defined in 2.6.4.1, and shall be associated with steps via textual *step bodies* or graphical *action blocks*, as defined in 2.6.4.2. The details of action block representation are defined in 2.6.4.3. Control of actions shall be expressed by *action qualifiers* as defined in 2.6.4.4.

2.6.4.1 *Declaration*

A programmable controller implementation which supports SFC elements shall provide one or more of the mechanisms defined in table 42 for the declaration of actions. The *scope* of the declaration of an action shall be *local* to the program organization unit containing the declaration.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 42 – Declaration of actions

No.	Feature	
1	Any Boolean variable in a VAR or VAR_OUTPUT block, or their graphical equivalents, can be an action	
	Example	Feature
2l		Graphical declaration in LD language (see 4.2)
2s		Inclusion of SFC elements in action
2f		Graphical declaration in FBD language (see 4.3)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

Table 42 *(concluded)*

No.	Feature	
1	Any Boolean variable declared in a VAR or VAR_OUTPUT block, or their graphical equivalents, can be an action	
	Example	Feature
3s	ACTION ACTION_4 : %QX17 := %IX1 & %MX3 & S8.X ; FF28(S1 := (C<D)) ; %MX10 := FF28.Q ; END_ACTION	Textual declaration in ST language (see 3.3)
3i	ACTION ACTION_4 : LD S8.X AND %IX1 AND %MX3 ST %QX17 LD C LT D S1 FF28 LD FF28.Q ST %MX10 END_ACTION	Textual declaration in IL langage (see 3.2)

NOTES

1 The step flag S8.X is used in these examples to obtain the desired result that, when S8 is de-activated, %QX17 := 0.

2 If feature 1 of table 40 is supported, then one or more of the features in this table, or feature 4 of table 43, shall be supported.




3 If feature 2 of table 40 is supported, then one or more of features 1, 3s, or 3i of this table shall be supported.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.6.4.2 *Association with steps*

A programmable controller implementation which supports SFC elements shall provide one or more of the mechanisms defined in table 43 for the association of actions with steps.

Table 43 – Step/action association

No.	Example	Feature
1		Action block (see 2.6.4.3)
2		Concatenated action blocks
3	STEP S8 : ACTION_1(L,t#10s,DN1) ; ACTION_2(P) ; ACTION_3(N) ; END_STEP	Textual step body
4		Action block "d" Field (see 2.6.4.3)
NOTE - When feature 4 is used, the corresponding action name cannot be used in any other action block.		

2.6.4.3 *Action blocks*

As shown in table 44, an *action block* is a graphical element for the combination of a Boolean variable with one of the *action qualifiers* specified in subclause 2.6.4.4 to produce an enabling condition, according to the rules given in subclause 2.6.4.5, par an associated action.



Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

The action block provides a means of optionally specifying Boolean "indicator" variables, indicated by the "c" field in table 44, which can be set by the specified action to indicate its completion, timeout, error conditions, etc. If the "c" field is not present, and the "b" field specifies that the action shall be a Boolean variable, then this variable shall be interpreted as the "c" variable when required.

When action blocks are concatenated graphically as illustrated in table 43, such concatenations can have multiple indicator variables, but shall have only a single common Boolean input variable, which shall act simultaneously upon all the concatenated blocks.

As well as being associated with a step, an action block can be used as a graphical element in the LD or FBD languages specified in clause 4. In this case, signal or power flow through an action block shall follow the rules specified in 4.1.1.

Table 44 – Action block features

No.	Feature	Graphical form
1	"a": Qualifier as per 2.6.4.4	
2	"b": Action name	
3	"c": Boolean "indicator" variables	
	"d": Action using:	
4	IL language (3.2)	
5	ST language (3.3)	
6	LD language (4.2)	
7	FBD language (4.3)	
	Feature/Example	
8	Use of action blocks in ladder diagrams (see 4.2): 	
9	Use of action blocks in function block diagrams (see 4.3): 	

NOTES

1 Field "a" can be omitted when the qualifier is "N".

2 Field "c" can be omitted when no indicator variable is used.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.6.4.4 *Action qualifiers*

Associated with each step/action association defined in 2.6.4.2, or each occurrence of an action block as defined in 2.6.4.3, shall be an *action qualifier*. The value of this qualifier shall be one of the values listed in table 45. In addition, the qualifiers L, D, SD, DS, and SL shall have an associated duration of type TIME.

NOTE - IEC 848 gives informal definitions and examples of the use of these qualifiers. This standard formalizes these definitions, redefining the "S" qualifier and introducing the "R" qualifier. The control of actions using these qualifiers is defined in the following subclause, and additional examples of their use are given in annex F.

Table 45 – Action qualifiers

No.	Qualifier	Explanation
1	None	Non-stored (null qualifier)
2	N	Non-stored
3	R	overriding Reset
4	S	Set (Stored)
5	L	time Limited
6	D	time Delayed
7	P	Pulse
8	SD	Stored and time Delayed
9	DS	Delayed and Stored
10	SL	Stored and time Limited

2.6.4.5 *Action control*

The control of actions shall be functionally equivalent to the application of the following rules:

1) Associated with each action shall be the functional equivalent of an instance of the ACTION_CONTROL function block defined in figures 14 and 15. If the action is declared as a Boolean variable, as defined in 2.6.4.1, the "Q" output of this block shall be the state of this Boolean variable. If the action is declared as a collection of statements or networks, as defined in 2.6.4.1, then this collection shall be executed continually while the "Q" output of the ACTION_CONTROL function block stands at Boolean 1. The statements or networks shall be executed one final time after the falling edge of "Q".

2) A Boolean input to the ACTION_CONTROL block for an action shall be said to have an *association* with a step as defined in 2.6.4.2, or with an action block as defined in 2.6.4.3, if the corresponding qualifier is equivalent to the input name (N, R, S, L, D, P, SD, DS, or SL). The association shall be said to be *active* if the associated step is active, or if the associated action block's input has the value Boolean 1. The *active associations* of an *action* are equivalent to the set of *active associations* of all inputs to its ACTION_CONTROL function block.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

A Boolean input to an ACTION_CONTROL block shall have the value Boolean 1 if it has at least one active association, and the value Boolean 0 otherwise.

3) The value of the T input to an ACTION_CONTROL block shall be the value of the *duration portion of a time-related qualifier* (L, D, SD, DS, or SL) *of an active association*. If no such association exists, the value of the T input shall be t#0s.

4) It shall be an *error* in the sense of subclause 1.5.1 if one or more of the following conditions exist:

a) More than one *active association* of an action has a time-related qualifier (L, D, SD, DS, or SL).

b) The SD input to an ACTION_CONTROL block has the Boolean value 1 when the Q1 output of its SL_FF block has the Boolean value 1.

c) The SL input to an ACTION_CONTROL block has the Boolean value 1 when the Q1 output of its SD_FF block has the Boolean value 1.

5) It is not required that the ACTION_CONTROL block itself be implemented, but only that the control of actions be equivalent to the preceding rules. Only those portions of the action control appropriate to a particular action need be instantiated, as illustrated in figure 16. In particular, note that simple MOVE (:=) and Boolean OR functions suffice for control of Boolean variable actions if the latter's associations have only "N" qualifiers.




Figure 14 – ACTION_CONTROL function block – External interface (not visible to the user)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale





Figure 15 – ACTION_CONTROL function block body (not visible to the user)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale



NOTE - The complete SFC network and its associated declarations are not shown in this example.

Figure 16a – Action control example – SFC representation

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale




Figure 16b – Action control example – Functional equivalent

2.6.5 *Rules of evolution*

The *initial situation* of a SFC network is characterized by the *initial step* which is in the active state upon initialization of the program or function block containing the network.

Evolutions of the active states of steps shall take place along the *directed links* when caused by the *clearing* of one or more *transitions*.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

A transition is *enabled* when all the preceding steps, connected to the corresponding transition symbol by directed links, are active. The clearing of a transition occurs when the transition is enabled and when the associated transition condition is true.

The clearing of a transition causes the *deactivation* (or "resetting") of all the immediately preceding steps connected to the corresponding transition symbol by directed links, followed by the *activation* of all the immediately following steps.

The alternation Step/Transition and Transition/Step shall always be maintained in SFC element connections, that is:

- Two steps shall never be directly linked; they shall always be separated by a transition.
- Two transitions shall never be directly linked; they shall always be separated by a step.

When the clearing of a transition leads to the activation of several steps at the same time, the sequences to which these steps belong are called *simultaneous sequences*. After their simultaneous activation, the evolution of each of these sequences becomes independent. In order to emphasize the special nature of such constructs, the divergence and convergence of simultaneous sequences shall be indicated by a double horizontal line.

Table 46 defines the syntax and semantics of the allowed combinations of steps and transitions.

The clearing time of a transition may theoretically be considered as short as one may wish, but it can never be zero. In practice, the clearing time will be imposed by the programmable controller implementation. For the same reason, the duration of a step activity can never be considered to be zero.

Several transitions which can be cleared simultaneously shall be cleared simultaneously, within the timing constraints of the particular programmable controller implementation and the priority constraints defined in table 46.





Testing of the successor transition condition(s) of an active step shall not be performed until the effects of the step activation have propagated throughout the program organization unit in which the step is declared.

Figure 17 illustrates the application of these rules. In this figure, the active state of a step is indicated by the presence of an asterisk (*) in the corresponding block. This notation is used for illustration only, and is not a required language feature.

The application of the rules given in this subclause cannot prevent the formulation of "unsafe" SFCs, such as the one shown in figure 18a, which may exhibit uncontrolled proliferation of tokens. Likewise, the application of these rules cannot prevent the formulation of "unreachable" SFCs, such as the one shown in figure 18b, which may exhibit "locked up" behavior. The programmable controller system shall treat the existence of such conditions as *errors* as defined in 1.5.1.




Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 46 – Sequence evolution

No.	Example	Rule
1		*Single sequence:* The alternation step-transition is repeated in series. *Example:* An evolution from step S3 to step S4 shall take place if and only if step S3 is in the active state and the transition condition c is true.
2a		*Divergence of sequence selection:* A selection between several sequences is represented by as many transition symbols, *under* the horizontal line, as there are different possible evolutions. The asterisk denotes left-to-right priority of transition evaluations. *Example:* An evolution shall take place from S5 to S6 only if S5 is active and the transition condition "e" is true, or from S5 to S8 only if S5 is active and ■ is true and "e" is false.
2b		*Divergence of sequence selection:* The asterisk, followed by numbered branches, indicates a user-defined priority of transition evaluation, with the lowerst-numbered branch having the highest priority. *Example:* An evolution shall take place from S5 to S8 only if S5 is active and the transition condition "f" is true, or from S5 to S6 only if S5 is active, and "e" is true, and "f" is false.
2c		*Divergence of sequence selection:* The connection of the branch indicates that the user must assure that transition conditions are mutually exclusive, as specified by IEC 848. *Exemple:* S6 only if S5 is active and the transition condition "e" is true, or from S5 to S8 only if S5 is active and "e" is false and "f" is true.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

Table 46 *(continued)*



No.	Example	Rule
3		*Convergence of sequence selection:* The end of a sequence selection is represented by as many transition symbols, *above* the horizontal line, as there are selection paths to be ended. *Example:* An evolution shall take place from S7 to S10 only if S7 is active and the transition "h" is true, or from S9 to S10 only if S9 is active and "j" is true.
4		*Simultaneous sequences – divergence:* Only one common transition symbol shall be possible, immediately *above* the double horizontal line of synchronization. *Example:* An evolution shall take place from S11 to S12, S14, ... only if S11 is active and the transition condition "b" associated to the common transition is true. After the simultaneous activation of S12, S14, etc., the evolution of each sequence proceeds independently.
		*Simultaneous sequences – convergence:* Only one common transition symbol shall be possible, immediately *under* the double horizontal line of synchronization. *Example:* An evolution shall take place from S13, S15, ... to S16 only if all steps above and connected to the double horizontal line are active and the transition condition "d" associated to the common transition is true.

(continued overleaf)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale


NEMA IA*2.3 94 ■ 6470247 0506464 018 ■

Table 46 *(continued)*


No.	Example	Rule
5a 5b 5c		*Sequence skip:* A "sequence skip" is a special case of sequence selection (Feature 2) in which one or more of the branches contain no steps. Features 5a, 5b, and 5c correspond to the representation options given in features 2a, 2b and 2c, respectively. *Example:* (Feature 5a shown) An evolution shall take place from S30 to S33 if "a" is false and "d" is true, that is, the sequence (S31, S32) will be skipped.
6a 6b 6c		*Sequence loop:* A "sequence loop" is a special case of sequence selection (Feature 2) in which one or more of the branches return to a preceding step. Features 6a, 6b and 6c correspond to the representation options given in features 2a, 2b and 2c, respectively. *Example:* (Feature 6a shown) An evolution shall take place from S32 to S31 if "c" is false and "d" is true, that is, the sequence (S31, S32) will be repeated.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 46 *(concluded)*

No.	Example	Rule
7		*Directional arrows:* When necessary for clarity, the "less than" (<) character of the ISO/IEC 646 character set can be used to indicate *right-to-left control flow*, and the "greater than" (>) character to represent left-to-right control flow. When this feature is used, the corresponding character shall be located between two "-" characters, that is, in the character sequence "-<-" or "->-" as shown in the accompanying example.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale



NOTE - In this figure, the active state of a step is indicated by the presence of an asterisk (*) in the corresponding block. This notation is used for illustration only, and is not a required language feature.

Figure 17 – SFC evolution rules

a) Transition not enabled (X = Don't care)
b) Transition enabled but not cleared (X=0)
c) Transition cleared (X=1)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale




Figure 18a – SFC errors: an "unsafe" SFC (see 2.6.5)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale




Figure 18b – SFC errors: an "unreachable" SFC (see 2.6.5)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

2.6.6 *Compatibility of SFC elements*

SFCS can be represented graphically or textually, utilizing the elements defined above. Table 47 summarizes for convenience those elements which are mutually compatible for graphical and textual representation, respectively.

Table 47 – Compatible SFC features

Table	Graphical representation	Textual representation
40	1, 3a, 3b, 4	2, 3a, 4
41	1, 2, 3, 4, 4a, 4b, 7, 7a, 7b	5, 6, 7c, 7d
42	1, 2i, 2s, 2f	3s, 3i
43	1, 2, 4	3
44	1 to 9	–
45	1 to 10	1 to 10 (textual equivalent)
46	1 to 7	1 to 6
57	All	–

2.6.7 *Compliance requirements*

In order to claim compliance with the requirements of 2.6, the elements shown in table 48 shall be supported and the compatibility requirements defined in 2.6.6 shall be observed.

Table 48 – SFC minimal compliance requirements

Table	Graphical representation	Textual representation
40	1	2
41	1 or 2 or 3 or (4 and (4a or 4b)) or (7 and (7a or 7b or 7c or 7 d))	5 or 6
42	1 or 2i or 2f	3s or 3i
43	1 or 2 or 4	3
45	1 or 2	1 or 2
46	1 and (2a or 2b or 2c) and 3 and 4	Same (textual equivalent)
57	(1 or 2) and (3 or 4) and (5 or 6) and (7 or 8) and (9 or 10 and (11 or 12)	Not required

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

2.7 *Configuration elements*

As described in 1.4.1, a *configuration* consists of *resources, tasks* (which are defined within *resources*), *global variables*, and *access paths*. Each of these elements is defined in detail in this subclause.

A graphic example of a simple configuration is shown in figure 19a. Skeleton declarations for the corresponding function blocks and programs are given in figure 19b. This figure serves as a reference point for the examples of configuration elements given in the remainder of this subclause such as in figure 20.




Figure 19a – Graphical example of a configuration

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

```
FUNCTION_BLOCK A
  VAR_OUTPUT  y1 : UINT ;
              y2 : BYTE ;
  END_VAR
END_FUNCTION_BLOCK
```

```
FUNCTION_BLOCK B
  VAR_INPUT b1 : UINT ;
            b2 : BYTE ;
  END_VAR
END_FUNCTION_BLOCK
```

```
FUNCTION_BLOCK C
  VAR_OUTPUT c1 : BOOL ;
  END_VAR
END_FUNCTION_BLOCK
```

```
FUNCTION_BLOCK D
  VAR_INPUT d1 : BOOL ; END_VAR
  VAR_OUTPUT y2 : INT ; END_VAR
END_FUNCTION_BLOCK
```

```
PROGRAM F
  VAR_INPUT  x1 : BOOL ; x2 : UINT ; END_VAR
  VAR_OUTPUT y1 : BYTE ; END_VAR
END_PROGRAM
```

```
PROGRAM G
  VAR_OUTPUT out1 : UINT ; END_VAR
  VAR_EXTERNAL z1 : BYTE ; END_VAR
  VAR  FB1 : A ; FB2 : B ; END_VAR
FB1(...) ; out1 := FB1.y1 ; z1 := FB1.y2 ;
FB2(b1 := FB1.y1, b2 := FB1.y2) ;
END_PROGRAM
```

```
PROGRAM H
  VAR_OUTPUT HOUT1 : INT ; END_VAR
  VAR  FB1 : C ; FB2 : D ; END_VAR
FB1(...) ;
FB2(d1 := FB1.c1) ; HOUT1 := FB2.y2 ;
END_PROGRAM
```

Figure 19b – Skeleton function block and program declarations for configuration example

2.7.1 *Configurations, resources, and access paths*

Table 49 enumerates the language features for declaration of *configurations, resources, global* variables, and *access paths.* Partial enumeration of TASK declaration features is also given; additional information on *tasks* is provided in 2.7.2. The formal syntax for these features is given in B.1.7. Figure 20 provides examples of these features, corresponding to the example configuration shown in figure 19b and the supporting declarations in figure 19a.

The ON qualifier in the RESOURCE...ON...END_RESOURCE construction is used to specify the type of "processing function" and its "man-machine interface" and "sensor and actuator interface" functions upon which the *resource* and its associated *programs* and *tasks* are to be implemented. The manufacturer shall supply a *resource library* of such functions, as illustrated in figure 3. Associated with each element in this library shall be an identifier (the *resource type name*) for use in resource declaration.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

The *scope* of a VAR_GLOBAL declaration shall be limited to the *configuration* or resource in which it is declared, with the exception that an *access path* can be declared to a *global* variable in a *resource* using feature 10d in table 49.

The VAR_ACCESS...END_VAR construction provides a means of specifying named variables which can be accessed by some of the communication services specified in IEC 1131-5. An *access path* associates each such variable with an input or output variable of a *program*, a *global* variable, or a *directly represented* variable as defined in 2.4.1.1. If such a variable is a *multi-element variable* (*structure* or *array*), an access path can be specified to an element of the variable. The direction of the access path can be specified as READ_WRITE or READ_ONLY, indicating that the communication services can both read and modify the value of the variable in the first case, or read but not modify the value in the second case. If no direction is specified, the default direction is READ_ONLY.

Table 49 – Configuration and resource declaration features

No.	Description
1	CONFIGURATION...END_CONFIGURATION construction
2	VAR_GLOBAL...END_VAR construction within CONFIGURATION
3	RESOURCE...ON...END_RESOURCE construction
4	VAR_GLOBAL...END_VAR construction within RESOURCE
5a	Periodic TASK construction within RESOURCE (Note 1)
5b	Non-periodic TASK construction within RESOURCE (Note 1)
6a	PROGRAM declaration with PROGRAM-to-TASK association (Note 1)
6b	PROGRAM declaration with FUNCTION BLOCK-to-TASK association (Note 1)
6c	PROGRAM declaration with no TASK association (Note 1)
7	Declaration of directly represented variables in VAR_GLOBAL (Note 2)
8a	Connection of directly represented variables to PROGRAM inputs
8b	Connection of GLOBAL variables to PROGRAM inputs
9a	Connection of PROGRAM outputs to directly represented variables
9b	Connection of PROGRAM outputs to GLOBAL variables
10a	VAR_ACCESS...END_VAR construction
10b	Access paths to directly represented variables
10c	Access paths to PROGRAM inputs
10d	Access paths to GLOBAL variables in RESOURCES
10e	Access paths to GLOBAL variables in CONFIGURATION
10f	Access paths to PROGRAM outputs

NOTES

1 See 2.7.2 for further description of TASK features.

2 See 2.4.3.1 for further description of related features.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

No.	Example
1	CONFIGURATION CELL_1
2	VAR_GLOBAL w : UINT; END_VAR
3	RESOURCE STATION_1 ON PROCESSOR_TYPE_1
4	VAR_GLOBAL z1 : BYTE ; END_VAR
5a	TASK SLOW_1(INTEGRAL := t#20ms, PRIORITY := 2) ;
5b	TASK FAST_1(INTERVAL := t#10ms, PRIORITY := 1) ;
6a	PROGRAM P1 WITH SLOW_1 :
8a	F(x1 := %IX1.1) ;
9b	PROGRAM P2 : G(out1 => w,
6b	FB1 WITH SLOW_1,
6b	FB2 WITH FAST_1) ;
3	END_RESOURCE
3	RESOURCE STATION_2 ON PROCESSOR TYPE_2
4	VAR_GLOBAL z2 : BOOL ;
7	AT %QW5 : INT ;
4	END_VAR
5a	TASK PER_2(INTERVAL := t#50ms, PRIORITY := 2) ;
5b	TASK INT_2(SINGLE := z2, PRIORITY := 1) ;
6a	PROGRAM P1 WITH PER_2 :
8b	F(x1 := z2, x2 := w) ;
6a	PROGRAM P4 WITH INT_2 :
9a	H(HOUT1 => %QW5,
6b	FB1 WITH PER_2) ;
3	END_RESOURCE
10a	VAR_ACCESS
10b	ABLE : STATION_1.%IX1.1 : BOOL READ_ONLY ;
10c	BAKER : STATION_1.P1.x2 : UINT READ_ONLY ;
10d	CHARLIE : STATION_1.z1 : BYTE ;
10e	DOG : w : UINT READ_ONLY ;
10f	ALPHA : STATION_2.P1.y1 : BYTE READ_ONLY ;
10f	BETA : STATION_2.P4.HOUT1 : INT READ_ONLY ;
10d	GAMMA : STATION_2.z2 : BOOL READ_WRITE ;
10a	END_VAR
1	END_CONFIGURATION

NOTES

1 Graphical and semigraphic representation of these features is allowed but is beyond the scope of this part of IEC 1131.

2 It is an error if the data type declared for a variable in a VAR_ACCESS statement is not the same as the data type declared for the variable elsewhere, e.g., if variable BAKER is declared of type WORD in the above examples.

Figure 20 – Examples of CONFIGURATION and RESOURCE declaration features

2.7.2 *Tasks*

For the purposes of IEC 1131-3, a *task* is defined as an execution control element which is capable of invoking, either on a periodic basis or upon the occurrence of the rising edge of a specified Boolean variable, the execution of a set of program organization units, which can include *programs* and *function blocks* whose instances are specified in the declaration of *programs*.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

Tasks and their association with program organization units can be represented graphically or textually, as shown in table 50, as part of *resources* within *configurations*. A task is implicitly enabled or disabled by its associated resource according to the mechanisms defined in 1.4.1. The control of program organization units by enabled tasks shall conform to the following rules:

1) The associated program organization units shall be scheduled for execution upon each rising edge of the SINGLE input of the task.

2) If the INTERVAL input is non-zero, the associated program organization units shall be scheduled for execution periodically at the specified interval as long as the SINGLE input stands at zero (0). If the INTERVAL input is zero (the default value), no periodic scheduling of the associated program organization units shall occur.

3) The PRIORITY input of a task establishes the scheduling priority of the associated program organization units, with zero (0) being highest priority and successively lower priorities having successively higher numeric values. As shown in table 50, the priority of a program organization unit (that is, the priority of its associated task) can be used for *preemptive* or *non-preemptive* scheduling.

a) In *non-preemptive* scheduling, processing power becomes available on a *resource* when execution of a program organization unit or operating system function is complete. When processing power is available, the program organization unit with highest scheduled priority shall begin execution. If more than one program organization unit is waiting at the highest scheduled priority, then the program organization unit with the longest waiting time at the highest scheduled priority shall be executed.

b) In *preemptive* scheduling, when a program organization unit is scheduled, it can *interrupt* the execution of a program organization unit of lower priority on the same *resource*, that is, the execution of the lower-priority unit can be suspended until the execution of the higher-priority unit is completed. A program organization unit shall not interrupt the execution of another unit of the same or higher priority.

NOTE - Depending on schedule priorities, a program organization unit might not begin execution at the instant it is scheduled. However, in the examples shown in table 50, all program organization units meet their *deadlines*, that is, they all complete execution before being scheduled for re-execution. The manufacturer shall provide information to enable the user to determine whether all deadlines will be met in a proposed configuration.

4) A *program* with no task association shall have the lowest system priority. Any such program shall be scheduled for execution upon "starting" of its *resource*, as defined in 1.4.1, and shall be re-scheduled for execution as soon as its execution terminates.

5) When a *function block instance* is associated with a task, its execution shall be under the exclusive control of the task, independent of the rules of evaluation of the program organization unit in which the task-associated function block instance is declared.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

6) Execution of *a function block instance* which is not directly associated with a task shall follow the normal rules for the order of evaluation of language elements for the program organization unit (which can itself be under the control of a task) in which the function block instance is declared.

7) The execution of function blocks within a program shall be synchronized to ensure that data concurrency is achieved according to the following rules:





a) If a function block receives more than one input from another function block, then when the former is executed, all inputs from the latter shall represent the results of the same evaluation. For instance, in the example represented by figure 21a, when Y2 is evaluated, the inputs Y2.A and Y2.B shall represent the outputs Y1.C and Y1.D from the same (not two different) evaluations of Y1.

b) If two or more function blocks receive inputs from the same function block, and if the "destination" blocks are all explicitly or implicitly associated with the same task, then the inputs to all such "destination" blocks at the time of their evaluation shall represent the results of the same evaluation of the "source" block. For instance, in the example represented by figures 21b and 21c, when Y2 and Y3 are evaluated in the normal course of evaluating program P1, the inputs Y2.A and Y2.B shall be the results of the same evaluation of Y1 as the inputs Y3.A and Y3.B.

Provision shall be made for storage of the outputs of functions or function blocks which have explicit task associations, or which are used as inputs to program organization units which have explicit task associations, as necessary to satisfy the rules given above.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 50 – Task features

No.	Description/Examples
1a	Textual declaration of periodic TASK (feature 5a of table 49)
1b	Textual declaration of non-periodic TASK (feature 5b of table 49)
	Graphical representation of TASKs within a RESOURCE
	
2a	Graphical representation of periodic TASKS
	
2b	Graphical representation of non-periodic TASK
	
3a	Textual association with PROGRAMS (feature 6a of table 49)
3b	Textual association with FUNCTION BLOCKs (feature 6b of table 49)
4a	Graphical association with PROGRAMS (within RESOURCES)
	

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 50 *(continued)*

<table>
<tr><th>No.</th><th>Description/Examples</th></tr>
<tr><td>4b</td><td>Graphical association with FUNCTION BLOCKS
(within PROGRAMS inside RESOURCES)</td></tr>
<tr><td></td><td>
<pre>
RESOURCE STATION_1
                                P2
  +---+
  | G |
  | |
  | |
  | FB1   FB2 |
  | +-------+   +-------+ |
	A		B	
+-------+   +-------+
	SLOW_1		FAST_1	
+-------+   +-------+
  +---+

END_RESOURCE
</pre>
</td></tr>
<tr><td>5a</td><td>Non-preemptive scheduling</td></tr>
<tr><td></td><td>Example 1:
– RESOURCE STATION_1 as configured in figure 20
– Execution times: P1 = 2 ms, P2 = 8 ms
P2.FB1 = P2.FB2 = 2 ms (note 3)
– STATION_1 starts at t = 0</td></tr>
<tr><td></td><td>Schedule (repeats every 40 ms)</td></tr>
</table>

t(ms)	Executing	Waiting
0	P2.FB2 @ 1	P1 @ 2, P2.FB1 @ 2, P2
2	P1 @ 2	P2.FB1 @ 2, P2
4	P2.FB1 @ 2	P2
6	P2	
10	P2	P2.FB2 @ 1
14	P2.FB2 @ 1	P2
16	P2	(P2 restarts)
20	P2	P2.FB.2 @ 1, P1 @ 2, P2.FB1 @ 2
24	P2.FB2 @ 1	P1 @ 2, P2.FB1 @ 2, P2
26	P1 @ 2	P2.FB1 @ 2, P2
28	P2.FB1 @ 2	P2
30	P2.FB2 @ 1	P2
32	P2	
40	P2.FB2 @ 1	P1 @ 2, P2.FB1 @ 2, P2

(continued overleaf)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 50 *(continued)*

No.	Description/Examples		
	Example 2: – RESOURCE STATION_2 as configured in figure 20 – Execution times: P1 = 30 ms, P4 = 5 ms, P4.FB1 = 10 ms (note 4) – INT_2 is triggered at t = 25, 50, 90, ... ms – STATION_2 starts at t = 0		
	Schedule		
	t(ms)	Executing	Waiting
	0	P1 @ 2	P4.FB1 @ 2
	25	P1 @ 2	P4.FB1 @ 2, P4 @ 1
	30	P4 @ 1	P4.FB1 @ 2
	35	P4.FB1 @ 2	
	50	P4 @ 1	P1 @ 2, P4.FB1 @ 2
	55	P1 @ 2	P4.FB1 @ 2
	85	P4.FB1 @ 2	
	90	P4.FB1 @ 2	P4 @ 1
	95	P4 @ 1	
	100	P1 @ 2	P4.FB1 @ 2
5b	Preemptive scheduling		
	Example 3: – RESOURCE STATION_1 as configured in figure 20 – Execution times: P1 = 2 ms, P2 = 8 ms; P2.FB1 = P2.FB2 = 2 ms (note 3) – STATION_1 starts at t = 0		
	Schedule		
	t(ms)	Executing	Waiting
	0	P2.FB2 @ 1	P1 @ 2, P2.FB1 @ 2, P2
	2	P1 @ 2	P2.FB1 @ 2, P2
	4	P2.FB1 @ 2	P2
	6	P2	
	10	P2.FB2 @ 1	P2
	12	P2	
	16	P2	(P2 restarts)
	20	P2.FB2 @ 1	P1 @ 2, P2.FB1 @ 2, P2

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 50 *(concluded)*

<table>
<tr><td>No.</td><td colspan="3">Description/Examples</td></tr>
<tr><td rowspan="12">5b</td><td colspan="3">Example 4:
– RESOURCE STATION_2 as configured in figure 20
– Execution times: P1 = 30 ms, P4 = 5 ms, P4.FB1 = 10 ms (note 4)
– INT_2 is triggered at = 25, 50, 90, ... ms
– STATION_2 starts at t = 0</td></tr>
<tr><td colspan="3">Schedule</td></tr>
<tr><td>t(ms)</td><td>Executing</td><td>Waiting</td></tr>
<tr><td>0</td><td>P1 @ 2</td><td>P4.FB1 @ 2</td></tr>
<tr><td>25</td><td>P4 @ 1</td><td>P1. @ 2, P4.FB1 @ 2</td></tr>
<tr><td>30</td><td>P1 @ 2</td><td>P4.FB1 @ 2</td></tr>
<tr><td>35</td><td>P4.FB1 @ 2</td><td></td></tr>
<tr><td>50</td><td>P4 @ 1</td><td>P1 @ 2, P4.FB1 @ 2</td></tr>
<tr><td>55</td><td>P1 @ 2</td><td>P4.FB1 @ 2</td></tr>
<tr><td>85</td><td>P4.FB1 @ 2</td><td></td></tr>
<tr><td>90</td><td>P4. @ 1</td><td>P4 FB1 @ 2</td></tr>
<tr><td>95</td><td>P4.FB1 @ 2</td><td></td></tr>
<tr><td>100</td><td>P1 @ 2</td><td>P4.FB1 @ 2</td></tr>
<tr><td colspan="4">NOTES
1 Details of RESOURCE and PROGRAM declarations are not shown; see 2.7 and 2.7.1.
2 The notation "X @ Y" indicates that program organization unit X is scheduled or executing at priority Y.
3 The execution times of P2.FB1 and P2.FB2 are not included in the execution time of P2.
4 The execution time of P4.FB1 is not included in the execution time of P4.</td></tr>
</table>

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale




Figure 21a – Synchronization of function blocks with explicit task associations

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale




Figure 21b – Synchronization of function blocks with implicit task associations

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale




Figure 21c – Explicit task associations equivalent to figure 21b

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

NEMA IA*2.3 94 ■ 6470247 0506483 T7T ■

3 Textual languages

The textual languages defined in this standard are IL (Instruction List) and ST (Structured Text). The sequential function chart (SFC) elements defined in 2.6 can be used in conjunction with either of these languages.

3.1 *Common elements*

The textual elements specified in clause 2 shall be common to the textual languages (IL and ST) defined in this clause. In particular, the following program structuring elements shall be common to textual languages:

TYPE...END_TYPE	(2.3.3)
VAR...END_VAR	(2.4.3)
VAR_INPUT...END_VAR	(2.4.3)
VAR_OUTPUT...END_VAR	(2.4.3)
VAR_IN_OUT...END_VAR	(2.4.3)
VAR_EXTERNAL...END_VAR	(2.4.3)
FUNCTION...END_FUNCTION	(2.5.1.3)
FUNCTION_BLOCK...END_FUNCTION_BLOCK	(2.5.2.2)
PROGRAM...END_PROGRAM	(2.5.3)
STEP...END_STEP	(2.6.2)
TRANSITION...END_TRANSITION	(2.6.3)
ACTION...END_ACTION	(2.6.4)

3.2 *Language IL (Instruction List)*

This subclause defines the semantics of the IL (Instruction List) language whose formal syntax is given in B.2.

3.2.1 *Instructions*

As illustrated in table 51, an *instruction list* is composed of a sequence of *instructions.* Each instruction shall begin on a new line and shall contain an operator with optional *modifiers*, and, if necessary for the particular operation, one or more *operands* separated by commas. Operands can be any of the data representations defined in 2.2 for literals and 2.4 for variables.

The instruction can be preceded by an identifying *label* followed by a colon (:). A *comment*, as defined in 2.1.5, if present, shall be the last element on a line. Empty lines can be inserted between instructions.

Table 51 – Examples of instruction fields

Label	Operator	Operand	Comment
START:	LD	%IX1	(* PUSH BUTTON *)
	ANDN	%MX5	(* NOT INHIBITED*)
	ST	%QX2	(* FAN ON *)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

3.2.2 *Operators, modifiers and operands*

Standard operators with their allowed modifiers and operands shall be as listed in table 52. The typing of operators shall conform to the conventions of 2.5.1.4.

Unless otherwise defined in table 52, the semantics of the operators shall be

result := result OP operand

That is, the value of the expression being evaluated is replaced by its current value operated upon by the operator with respect to the operand. For instance, the instruction AND %IX1 is interpreted as

result := result AND %IX1

The comparison operators shall be interpreted with the current result to the left of the comparison and the operand to the right, with a Boolean result. For instance, the instruction "GT %IW10" will have the Boolean result 1 if the current result is greater than the value of Input Word 10, and the Boolean result 0 otherwise.

The modifier "N" indicates Boolean negation of the operand. For instance, the instruction ANDN %IX2 is interpreted as

result := result AND NOT %IX2

The left parenthesis modifier "(" indicates that evaluation of the operator shall be deferred until a right parenthesis operator ")" is encountered, e.g., the sequence of instructions

```
AND(  %IX1
OR    %IX2
)
```

shall be interpreted as

result := result AND (%IX1 OR %IX2)

The modifier "C" indicates that the associated instruction shall be performed only if the value of the currently evaluated result is Boolean 1 (or Boolean 0 if the operator is combined with the "N" modifier)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

Table 52 – Instruction List (IL) operators

No.	Operator	Modifiers	Operand	Semantics
1	LD	N	Note 2	Set current result equal to operand
2	ST	N	Note 2	Store current result to operand location
3	S R	Note 3 Note 3	BOOL BOOL	Set Boolean operand to 1 Reset Boolean operand to 0
4 5 6 7	AND & OR XOR	N, (N, (N, (N, (	BOOL BOOL BOOL BOOL	Boolean AND Boolean AND Boolean OR Boolean Exclusive OR
8 9 10 11	ADD SUB MUL DIV	((((	Note 2 Note 2 Note 2 Note 2	Addition Subtraction Multiplication Division
12 13 14 15 16 17	GT GE EQ NE LE LT	((((((	Note 2 Note 2 Note 2 Note 2 Note 2 Note 2	Comparison: >; Comparison: >= Comparison: = Comparison: <>; Comparison: <= Comparison: <
18 19 20	JMP CAL RET	C, N C, N C, N	LABEL NAME	Jump to label Call function block (note 4) Return from called function or function block
21	)			Evaluate deferred operation

NOTES

1 See 3.2.2 for explanation of modifiers and evaluation of expressions.

2 These operators shall be either overloaded or typed as defined in 2.5.1.4. The current result and the operand shall be of the same type.

3 These operations are performed if and only if the value of the current result is Boolean 1.

4 The function block name is followed by a parenthesized argument list as defined in 3.2.3.

5 When a JMP instruction is contained in an ACTION... END_ACTION construct, the operand shall be a label within the same construct.

3.2.3 *Functions and function blocks*

Functions as defined in 2.5.1 shall be invoked by placing the function name in the operator field. The current result shall be used as the first argument of the function. Additional arguments, if required, shall be given in the operand field. The value returned by a function upon the successful execution of a RET instruction or upon reaching the physical end of the function shall become the "current result" described in 3.2.2.

Function blocks as defined in 2.5.2 can be invoked conditionally and unconditionally via the CAL (Call) operator listed in table 52. As shown in table 53, this invocation can take one of three forms. The input operators shown in table 54 can be used in conjunction with feature 3 of table 53.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 53 – Function block invocation features for IL language

No.	Description/example
1	CAL with input list: `CAL C10(CU := %IX10, PV := 15)`

2	CAL with load/store of inputs:
	`LD 15`
	`ST C10.PV`
	`LD %IX10`
	`ST C10.CU`
	`CAL C10`

3	Use of input operators:
	`LD 15`
	`PV C10`
	`LD %IX10`
	`CU C10`

NOTE - A declaration such as VAR C10 : CTU ; END_VAR is assumed in the above examples.	

Table 54 – Standard function block input operators for IL language

No.	Operators	FB Type	Reference
4	S1,R	SR	2.5.2.3.1
5	S,R1	RS	2.5.2.3.1
6	CLK	R_TRIG	2.5.2.3.2
7	CLK	F_TRIG	2.5.2.3.2
8	CU,R,PV	CTU	2.5.2.3.3
9	CD,LD,PV	CTD	2.5.2.3.3
10	CU,CD,R,LD,PV	CTUD	2.5.2.3.3
11	IN,PT	TP	2.5.2.3.4
12	IN,PT	TON	2.5.2.3.4
13	IN,PT	TOF	2.5.2.3.4

3.3 *Language ST (Structured Text)*

This subclause defines the semantics of the ST (Structured Text) language whose syntax is defined in B.3. In this language, the end of a textual line shall be treated the same as a space (SP) character, as defined in 2.1.4.

3.3.1 *Expressions*

An *expression* is a construct which, when evaluated, yields a value corresponding to one of the data types defined in 2.3.1 and 2.3.3.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

Expressions are composed of operators and operands. An *operand* shall be a literal as defined in 2.2, a variable as defined in 2.4, a function invocation as defined in 2.5.1, or another expression.

The *operators* of the ST language are summarized in table 55. The evaluation of an expression consists of applying the operators to the operands in a sequence defined by the operator precedence shown in table 55. The operator with highest precedence in an expression shall be applied first, followed by the operator of next lower precedence, etc., until evaluation is complete. Operators of equal precedence shall be applied as written in the expression from left to right. For example, if A, B, C, and D are of type INT with values 1, 2, 3, and 4, respectively, then

A+B–C*ABS(D)

shall evaluate to –9, and

(A+B–C)*ABS(D)

shall evaluate to 0 .

When an operator has two operands, the leftmost operand shall be evaluated first. For example, in the expression

SIN(A)*COS(B)

the expression SIN(A) shall be evaluated first, followed by COS(B), followed by evaluation of the product.

Boolean expressions may be evaluated only to the extent necessary to determine the resultant value. For instance, if A<=B, then only the expression (A>B) would be evaluated to determine that the value of the expression

(A>B) & (C<D)

is Boolean zero.

Functions shall be invoked as elements of expressions consisting of the function name followed by a parenthesized list of arguments, as defined in 2.5.1.1.

When an operator in an expression can be represented as one of the overloaded functions defined in 2.5.1.5, conversion of operands and results shall follow the rule and examples given in 2.5.1.4.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

Table 55 – Operators of the ST language

No.	Operation	Symbol	Precedence
1	Parenthesization	(Expression)	HIGHEST
2	Function evaluation Examples:	Identifier (argument list) LN(A), MAX(X,Y), etc.	
3	Exponentiation	**	
4 5	Negation Complement	– NOT	
6 7 8	Multiply Divide Modulo	* / MOD	
9 10	Add Subtract	+ –	
11	Comparison	<, >, <=, >=	
12 13	Equality Inequality	= <>	
14 15	Boolean AND Boolean AND	& AND	
16	Boolean Exclusive OR	XOR	
17	Boolean OR	OR	LOWEST

NOTES

1 The same restrictions apply to the operands of these operators as to the inputs of the corresponding functions defined in 2.5.1.5.

2 The result of evaluating the expression A**B shall be the same as the result of evaluating the function EXPT(A, B) as defined in table 24.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

NEMA IA*2.3 94 ■ 6470247 0506489 498 ■

3.3.2 *Statements*

The statements of the ST language are summarized in table 56. Statements shall be terminated by semicolons as specified in the syntax of B.3.

Table 56 – ST language statements

No.	Statement type/Reference	Examples
1	Assignment (3.3.2.1)	A := B ; CV := CV+1 ; C := SIN(X) ;
2	Function block invocation and FB output usage (3.3.2.2)	CMD_TMR(IN := %IX5, PT := T#300ms) ; A := CMD_TMR.Q ;
3	RETURN (3.3.2.2)	RETURN ;

4	IF (3.3.2.3)	D := B*B - 4*A*C ;
		IF D < 0.0 THEN NROOTS := 0 ;
		ELSIF D = 0.0 THEN
		  NROOTS := 1 ;
		  X1 := - B/ (2.0*A) ;
		ELSE
		  NROOTS := 2 ;
		  X1 := (-B+SQRT(D))/(2.0*A) ;
		  X2 := (-B-SQRT(D))/(2.0*A) ;
		END_IF ;

5	CASE (3.3.2.3)	TW := BCD_TO_INT(THUMBWHEEL) ;
		TW_ERROR := 0 ;
		CASE TW OF
		  1,5 : DISPLAY := OVEN_TEMP ;
		  2 : DISPLAY := MOTOR_SPEED ;
		  3 : DISPLAY := GROSS_TARE ;
		  4,6..10 : DISPLAY := STATUS (TW-4) ;
		ELSE DISPLAY := 0 ;
		  TW_ERROR := 1 ;
		END_CASE ;
		QW100 := INT_TO_BCD(DISPLAY) ;

6	FOR (3.3.2.4)	J := 101 ;
		FOR I := 1 TO 100 BY 2 DO
		  IF WORDS[I] = 'KEY' THEN
		  J := I ;
		  EXIT ;
		  END_IF ;
		END_FOR ;

7	WHILE (3.3.2.4)	J := 1 ; WHILE J <= 100 & WORDS[J] <> 'KEY' DO J := J+2 ; END_WHILE ;
8	REPEAT (3.3.2.4)	J := -1 ; REPEAT J := J+2 ; UNTIL J = 101 OR WORDS[J] = 'KEY' END_REPEAT ;
9	EXIT (3.3.2.4)	EXIT ;
10	Empty Statement	;

NOTE - If the EXIT statement (9) is supported, then it shall be supported for all of the iteration statements (FOR, WHILE, REPEAT) which are supported in the implementation.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

3.3.2.1 *Assignment statements*

The assignment statement replaces the current value of a single or multi-element variable by the result of evaluating an expression. An assignment statement shall consist of a variable reference on the left-hand side, followed by the *assignment operator* ":=", followed by the expression to be evaluated. For instance, the statement

A := B ;

would be used to replace the single data value of variable A by the current value of variable B if both were of type INT. However, if both A and B were of type ANALOG_CHANNEL_CONFIGURATION as described in table 12, then the values of all the elements of the structured variable A would be replaced by the current values of the corresponding elements of variable B.

As illustrated in figure 6, the assignment statement shall also be used to assign the value to be returned by a function, by placing the function name to the left of an assignment operator in the body of the function declaration. The value returned by the function shall be the result of the most recent evaluation of such an assignment. It is an error to return from the evaluation of a function with the "ENO" output non-zero unless at least one such assignment has been made.

3.3.2.2 *Function and function block control statements*

Function and function block control statements consist of the mechanisms for invoking function blocks and for returning control to the invoking entity before the physical end of a function or function block.

Function evaluation shall be invoked as part of expression evaluation, as specified in 3.3.1.

Function blocks shall be invoked by a statement consisting of the name of the function block followed by a parenthesized list of named input parameter value assignments, as illustrated in table 56. The order in which input parameters are listed in a function block invocation shall not be significant. It is not required that all input parameters be assigned values in every invocation of a function block. If a particular parameter is not assigned a value in a function block invocation, the previously assigned value (or the initial value, if no previous assignment has been made) shall apply.

The RETURN statement shall provide early exit from a function or function block (e.g., as the result of the evaluation of an IF statement).

3.3.2.3 *Selection statements*

Selection statements include the IF and CASE statements. A selection statement selects one (or a group) of its component statements for execution, based on a specified condition. Examples of selection statements are given in table 56.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

NEMA IA*2.3 94 ■ 6470247 0506491 046 ■

The IF statement specifies that a group of statements is to be executed only if the associated Boolean expression evaluates to the value 1 (true). If the condition is false, then either no statement is to be executed, or the statement group following the ELSE keyword (or the ELSIF keyword if its associated Boolean condition is true) is to be executed.

The CASE statement consists of an expression which shall evaluate to a variable of type INT (the "selector"), and a list of statement groups, each group being labelled by one or more integers or ranges of integer values. It specifies that the first group of statements, one of whose ranges contains the computed value of the selector, shall be executed. If the value of the selector does not occur in a range of any case, the statement sequence following the keyword ELSE (if it occurs in the CASE statement) shall be executed. Otherwise, none of the statement sequences shall be executed.

3.3.2.4 *Iteration statements*

Iteration statements specify that the group of associated statements shall be executed repeatedly. The FOR statement is used if the number of iterations can be determined in advance; otherwise, the WHILE or REPEAT constructs are used.

The EXIT statement shall be used to terminate iterations before the termination condition is satisfied.

When the EXIT statement is located within nested iterative constructs, exit shall be from the innermost loop in which the EXIT is located, that is, control shall pass to the next statement after the first loop terminator (END_FOR, END_WHILE, or END_REPEAT) following the EXIT statement. For instance, after executing the statements shown in figure 22, the value of the variable SUM shall be 15 if the value of the Boolean variable FLAG is 0, and 6 if FLAG=1.

```
SUM := 0 ;
FOR I := 1 TO 3 DO
  FOR J := 1 TO 2 DO
    IF FLAG THEN EXIT ; END_IF
    SUM := SUM + J ;
  END_FOR ;
  SUM := SUM + I ;
END_FOR ;
```

Figure 22 – EXIT statement example

The FOR statement indicates that a statement sequence shall be repeatedly executed, up to the END_FOR keyword, while a progression of values is assigned to the FOR loop control variable. The control variable, initial value, and final value shall be expressions of the same integer type (SINT, INT, or DINT) and shall not be altered by any of the repeated statements. The FOR statement increments the control variable up or down from an initial value to a final value in increments determined by the value of an expression; this value defaults to 1. The test for the termination condition is made at the beginning of each iteration, so that the statement sequence is not executed if the initial value exceeds the final value. The value of the control variable after completion of the FOR loop is implementation-dependent.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

An example of the usage of the FOR statement is given in feature 6 of table 56. In this example, the FOR loop is used to determine the index J of the first occurrence (if any) of the string 'KEY' in the odd-numbered elements of an array of strings WORDS with a subscript range of (1..100). If no occurrence is found, J will have the value 101.

The WHILE statement causes the sequence of statements up to the END_WHILE keyword to be executed repeatedly until the associated Boolean expression is false. If the expression is initially false, then the group of statements is not executed at all. For instance, the FOR...END_FOR example given in table 56 can be rewritten using the WHILE...END_WHILE construction shown in table 56.

The REPEAT statement causes the sequence of statements up to the UNTIL keyword to be executed repeatedly (and at least once) until the associated Boolean condition is true. For instance, the WHILE...END_WHILE example given in table 56 can be rewritten using the REPEAT...END_REPEAT construction shown in table 56.

The WHILE and REPEAT statements shall not be used to achieve interprocess synchronization, for example as a "wait loop" with an externally determined termination condition. The SFC elements defined in 2.6 shall be used for this purpose.

It shall be an *error* in the sense of 1.5.1 if a WHILE or REPEAT statement is used in an algorithm for which satisfaction of the loop termination condition or execution of an EXIT statement cannot be guaranteed.

4 Graphic languages

The graphic languages defined in this standard are LD (Ladder Diagram) and FBD (Function Block Diagram). The sequential function chart (SFC) elements defined in 2.6 can be used in conjunction with either of these languages.

4.1 *Common elements*

The elements defined in this clause apply to both the graphic languages in this Standard, that is, LD (Ladder Diagram) and FBD (Function Block Diagram), and to the graphic representation of sequential function chart (SFC) elements.

4.1.1 *Representation of lines and blocks*

The graphic language elements defined in this clause are drawn with line elements using characters from the ISO/IEC 646 character set, or using graphic or semigraphic elements, as shown in table 57.

Lines can be extended by the use of *connectors* as shown in table 57. No storage of data or association with data elements shall be associated with the use of connectors; hence, to avoid ambiguity, it shall be an *error* if the identifier used as a connector label is the same as the name of another named element within the same program organization unit.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

4.1.2 *Direction of flow in networks*

A *network* is defined as a maximal set of interconnected graphic elements, excluding the left and right rails in the case of networks in the LD language defined in 4.2. Provision shall be made to associate with each network or group of networks in a graphic language a *network label* delimited on the right by a colon (:). This label shall have the form of an identifier or an unsigned decimal integer as defined in clause 2 of this part. The *scope* of a network and its label shall be *local* to the program organization unit in which the network is located. Examples of networks and network labels are shown in annex F.

Graphic languages are used to represent the flow of a conceptual quantity through one or more networks representing a control plan, that is:

– "Power flow", analogous to the flow of electric power in an electromechanical relay system, typically used in relay ladder diagrams;

– "Signal flow", analogous to the flow of signals between elements of a signal processing system, typically used in function block diagrams;

– "Activity flow", analogous to the flow of control between elements of an organization, or between the steps of an electromechanical sequencer, typically used in sequential function charts.

The appropriate conceptual quantity shall flow along lines between elements of a network according to the following rules:

1) Power flow in the LD language shall be from left to right.





2) Signal flow in the FBD language shall be from the output (right-hand) side of a function block to the input (left-hand) side of the function or function block(s) so connected.

3) Activity flow between the SFC elements defined in 2.6 shall be from the bottom of a step through the appropriate transition to the top of the corresponding successor step(s).

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

NEMA IA*2.3 94 ■ 6470247 0506494 855 ■

Table 57 – Representation of lines and block

No.	Feature	Example
1 2	Horizontal lines: ISO/IEC 646 "minus" character Graphic or semigraphic	
3 4	Vertical lines: ISO/IEC 646 "vertical line" character Graphic or semigraphic	
5 6	Horizontal/vertical connection: ISO/IEC 646 "plus" character Graphic or semigraphic	
7 8	Line crossings without connection: ISO/IEC 646 characters Graphic or semigraphic	
9 10	Connected and non-connected corners: ISO/IEC 646 characters Graphic or semigraphic	
11 12	Blocks with connecting lines: ISO/IEC 646 characters Graphic or semigraphic	
13 14	Connectors using ISO/IEC 646 characters: Connector Continuation of a connected line Graphic or semigraphic connectors	

4.1.3 *Evaluation of networks*

The order in which networks and their elements are evaluated is not necessarily the same as the order in which they are labelled or displayed. Similarly, it is not necessary that all networks be evaluated before the evaluation of a given network can be repeated. However, when the body of a program organization unit consists of one or more networks, the results of network evaluation within said body shall be functionally equivalent to the observance of the following rules:

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

1) No element of a network shall be evaluated until the states of all of its inputs have been evaluated.

2) The evaluation of a network element shall not be complete until the states of all of its outputs have been evaluated.

3) The evaluation of a network is not complete until the outputs of all of its elements have been evaluated, even if the network contains one of the execution control elements defined in 4.1.4.

(4) The order in which networks are evaluated shall conform to the provisions of 4.2.6 for the LD language and 4.3.3 for the FBD language.

A *feedback path* is said to exist in a network when the output of a function or function block is used as the input to a function or function block which precedes it in the network; the associated variable is called *a feedback variable*. For instance, the Boolean variable RUN is the feedback variable in the example shown in figure 23. A feedback variable can also be an output element of a function block data structure as defined in 2.5.2.

Feedback paths can be utilized in the graphic languages defined in 4.2 and 4.3, subject to the following rules:

1) Explicit loops such as the one shown in 23a shall only appear in the FBD language defined in 4.3.

2) It shall be possible for the user to define the order of execution of the elements in an explicit loop, for instance by selection of feedback variables to form an implicit loop as shown in figure 23b.

3) Feedback variables shall be initialized by one of the mechanisms defined in clause 2. The initial value shall be used during the first evaluation of the network.

4) Once the element with a feedback variable as output has been evaluated, the new value of the feedback variable shall be used until the next evaluation of the element.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale




Figure 23 – Feedback path example
a) Explicit loop
b) Implicit loop
c) LD language equivalent

4.1.4 *Execution control elements*

Transfer of program control in the LD and FBD languages shall be represented by the graphical elements shown in table 58.






Jumps shall be shown by a Boolean signal line terminated in a double arrowhead. The signal line for a jump condition shall originate at a Boolean variable, at a Boolean output of a function or function block, or on the power flow line of a ladder diagram. A transfer of program control to the designated network label shall occur when the Boolean value of the signal line is 1 (TRUE); thus, the unconditional jump is a special case of the conditional jump.

The target of a jump shall be a network label within the program organization unit within which the jump occurs. If the jump occurs within an ACTION...END_ACTION construct, the target of the jump shall be within the same construct.

Conditional returns from functions and function blocks shall be implemented using a RETURN construction as shown in table 58. Program execution shall be transferred back to the invoking entity when the Boolean input is 1 (TRUE), and shall continue in the normal fashion when the Boolean input is 0 (FALSE). Unconditional returns shall be provided by the physical end of the function or function block, or by a RETURN element connected to the left rail in the LD language, as shown in table 58.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 58 – Graphic execution control elements

No.	Symbol/Example	Explanation
1		Unconditional Jump: FBD Language
2		LD language
3		Conditional Jump (FBD Language) Example: Jump Condition Jump Target
4		Conditional Jump (LD Language) Example: Jump Condition Jump Target
5		Conditional Return: LD Language
6		FBD Language
7		Unconditional Return from FUNCTION from FUNCTION_BLOCK
8		Alternative representation in LD language

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

4.2 *Language LD (Ladder Diagram)*

This subclause defines the LD language for ladder diagram programming of programmable controllers.

A LD program enables the programmable controller to test and modify data by means of standardized graphic symbols. These symbols are laid out in networks in a manner similar to a "rung" of a relay ladder logic diagram. LD networks are bounded on the left and right by *power rails.*

4.2.1 *Power rails*

As shown in table 59, LD network shall be delimited on the left by a vertical line known as the *left power rail,* and on the right by a vertical line known as the *right power rail.* The right power rail may be explicit or implied.

Table 59 – Power rails

No.	Symbol	Description
1		Left power rail (with attached horizontal link)
2		Right power rail (with attached horizontal link)

4.2.2 *Link elements and states*

As shown in table 60, link elements may be horizontal or vertical. The state of the link element shall be denoted "ON" or "OFF", corresponding to the literal Boolean values 1 or 0, respectively. The term *link state* shall be synonymous with the term *power flow.*

The state of the left rail shall be considered ON at all times. No state is defined for the right rail.

A horizontal link element shall be indicated by a horizontal line. A horizontal link element transmits the state of the element on its immediate left to the element on its immediate right.


The vertical link element shall consist of a vertical line intersecting with one or more horizontal link elements on each side. The state of the vertical link shall represent the inclusive OR of the ON states of the horizontal links on its left side, that is, the state of the vertical link shall be:

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

- OFF if the states of all the attached horizontal links to its left are OFF;
- ON if the state of one or more of the attached horizontal links to its left is ON.

The state of the vertical link shall be copied to all of the attached horizontal links on its right. The state of the vertical link shall not be copied to any of the attached horizontal links on its left.

Table 60 – Link elements

No.	Symbol	Description
1	----------	Horizontal link
2		Vertical link (with attached horizontal links)

4.2.3 *Contacts*

A *contact* is an element which imparts a state to the horizontal link on its right side which is equal to the Boolean AND of the state of the horizontal link at its left side with an appropriate function of an associated Boolean input, output, or memory variable. A contact does not modify the value of the associated Boolean variable. Standard contact symbols are given in table 61.

4.2.4 *Coils*

A *coil* copies the state of the link on its left to the link on its right without modification, and stores an appropriate function of the state or transition of the left link into the associated Boolean variable. Standard coil symbols are given in table 62.

4.2.5 *Functions and function blocks*

The representation of functions and function blocks in the LD language shall be as defined in clause 2 of this part, with the following exceptions:

1) Actual parameter connections may optionally be shown by writing the appropriate data or variable outside the block adjacent to the formal parameter name on the inside.

2) At least one Boolean input and one Boolean output shall be shown on each block to allow for power flow through the block.

4.2.6 *Order of network evaluation*

Within a program organization unit written in LD, networks shall be evaluated in top-to-bottom order as they appear in the ladder diagram, except as this order is modified by the execution control elements defined in 4.1.4.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

Table 61 – Contacts

Static contacts		
No.	**Symbol**	**Description**
1 2	*** --| |-- or *** --! !--	*Normally open contact* The state of the left link is copied to the right link if the state of the associated Boolean variable (indicated by "***") is ON. Otherwise, the state of the right link is OFF.
3 4	*** --|/|-- or *** --!/!--	*Normally closed contact* The state of the left link is copied to the right link if the state of the associated Boolean variable is OFF. Otherwise, the state of the right link is OFF.
Transition-sensing contacts		
5 6	*** --|P|-- or *** --!P!--	*Positive transition-sensing contact* The state of the right link is ON from one evaluation of this element to the next when a transition of the associated variable from OFF to ON is sensed at the same time that the state of the left link is ON. The state of the right link shall be OFF at all other times.
7 8	*** --|N|-- or *** --!N!--	*Negative transition-sensing contact* The state of the right link is ON from one evaluation of this element to the next when a transition of the associated variable from ON to OFF is sensed at the same time that the state of the left link is ON. The state of the right link shall be OFF at all other times.
NOTE - As specified in 2.1.1, the exclamation mark "!" shall be used when a national character set does not support the vertical bar "|".		

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table 62 – Coils

No.	Symbol	Description
		Momentary coils
1	*** --( )--	***Coil*** The state of the left link is copied to the associated Boolean variable and to the right link.
2	*** --(/)--	***Negated coil*** The state of the left link is copied to the right link. The inverse of the state of the left link is copied to the associated Boolean variable, that is, if the state of the left link is OFF, then the state of the associated variable is ON, and vice versa.
		Latched coils
3	*** --(S)--	***SET (latch) coil*** The associated Boolean variable is set to the ON state when the left link is in the ON state, and remains set until reset by a RESET coil.
4	*** --(R)--	***RESET (unlatch) coil*** The associated Boolean variable is reset to the OFF state when the left link is in the ON state, and remains reset until set by a SET coil.
		Retentive coils (see note)
5	*** ----(M)----	Retentive (Memory) coil
6	*** ----(SM)----	SET retentive (Memory) coil
7	*** ----(RM)----	RESET retentive (Memory) coil
		Transition-sensing coils
8	*** --(P)--	***Positive transition-sensing coil*** The state of the associated Boolean variable is ON from one evaluation of this element to the next when a transition of the left link from OFF to ON is sensed. The state of the left link is always copied to the right link.
9	*** --(N)--	***Negative transition-sensing coil*** The state of the associated Boolean variable is ON from one evaluation of this element to the next when a transition of the left link from ON to OFF is sensed. The state of the left link is always copied to the right link.

NOTE - The action of coils 5, 6, and 7 is identical to that of coils 1, 3, and 4, respectively, except that the associated Boolean variable is automatically declared to be in retentive memory without the explicit use of the VAR RETAIN declaration defined in 2.4.2.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

4.3 *Language FBD (Function Block Diagram)*

4.3.1 *General*

This subclause defines FBD, a graphic language for the programming of programmable controllers which is consistent, as far as possible, with IEC 617-12. Where conflicts exist between this standard and IEC 617, the provisions of this standard shall apply for the programming of programmable controllers in the FBD language.

The provisions of clauses 2 and 4.1 shall apply to the construction and interpretation of programmable controller programs in the FBD language.

Examples of the use of the FBD language are given in annex F.

4.3.2 *Combination of elements*

Elements of the FBD language shall be interconnected by signal flow lines following the conventions of 4.1.2.

Outputs of function blocks shall not be connected together. In particular, the "wired-OR" construct of the LD language is not allowed in the FBD language; an explicit Boolean "OR" block is required instead, as shown in figure 24.




Figure 24 – Boolean OR examples
a) "Wired-OR" in LD language
b) Function in FBD language

4.3.3 *Order of network evaluation*

Within a program organization unit written in the FBD language, the order of network evaluation shall follow the rule that the evaluation of a network shall be complete before starting the evaluation of another network which uses one or more of the outputs of the preceding evaluated network.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

NEMA IA*2.3 94 ■ 6470247 0506503 698 ■

Annex A
(normative)

Specification method for textual languages

Programming languages are specified in terms of a *syntax*, which specifies the allowable combinations of symbols which can be used to define a program; and a set of *semantics*, which specify the relationship between programmed operations and the symbol combinations defined by the syntax.

A.1 Syntax

A syntax is defined by a set of *terminal symbols* to be utilized for program specification; a set of *non-terminal symbols* defined in terms of the terminal symbols; and a set of *production rules* specifying those definitions.

A.1.1 *Terminal symbols*

The terminal symbols for textual programmable controller programs shall consist of combinations of the characters in the ISO/IEC 646 character set. For interchange of programs between systems, these characters shall be represented by the seven-bit character codes defined in ISO 646.

For the purposes of this part, terminal textual symbols consist of the appropriate character string enclosed in paired single or double quotes. For example, a terminal symbol represented by the character string ABC can be represented by either

"ABC"

or

'ABC'

This allows the representation of strings containing either single or double quotes; for instance, a terminal symbol consisting of the double quote itself would be represented by '"'.

A special terminal symbol utilized in this syntax is the end-of-line delimiter, which is represented by the unquoted character string EOL. This symbol shall normally consist of the FE5 (CR = carriage return) character defined by ISO/IEC 646. Language implementors shall specify any deviation from this usage; in any case, no characters other than those in ISO/IEC 646 are allowed.

A second special terminal symbol utilized in this syntax is the "null string", that is, a string containing no characters. This is represented by the terminal symbol NIL.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

A.1.2 *Non-terminal symbols*

Non-terminal textual symbols shall be represented by strings of lower-case letters, numbers, and the underline character (_), beginning with a lower-case letter. For instance, the strings

nonterm1

and

non_term_2

are valid non-terminal symbols, while the strings

3nonterm

and

_nonterm4

are not.

A.1.3 *Production rules*

The production rules for textual programmable controller programming languages shall form an *extended grammar* in which each rule has the form

non_terminal_symbol ::= extended_structure

This rule can be read as:

"A non_terminal_symbol can consist of an extended_structure."

Extended structures can be constructed according to the following rules:

1) The null string, NIL, is an extended structure.

2) A terminal symbol is an extended structure.

3) A non-terminal symbol is an extended structure.

4) If S is an extended structure, then the following expressions are also extended structures:

(S), meaning S itself.

{S}, *closure*, meaning zero or more concatenations of S.

[S], *option*, meaning zero or one occurrence of S.

5) If S1 and S2 are extended structures, then the following expressions are extended structures:

S1| S2, *alternation*, meaning a choice of S1 or S2.

S1 S2, *concatenation*, meaning S1 followed by S2.

6) Concatenation *precedes* alternation, that is, S1 | S2 S3 is equivalent to S1 | (S2 S3), and S1 S2 | S3 is equivalent to (S1 S2) | S3.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

A.2 Semantics

Programmable controller textual programming language semantics are defined in this part by appropriate natural language text, accompanying the production rules, which references the descriptions provided in the appropriate clauses. Standard options available to the user and manufacturer are specified in these semantics.

In some cases it is more convenient to embed semantic information in an extended structure. In such cases, this information is delimited by paired angle brackets, for example, <semantic information>.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Annex B
(normative)

Formal specifications of language elements

B.0 Programming model

The contents of this annex are normative in the sense that a compiler which is capable of recognizing all the syntax in this annex shall be capable of recognizing the syntax of any textual language implementation complying with this standard.

PRODUCTION RULES:

library_element_name ::= data_type_name | *function_name*
| function_block_type_name | program_type_name
| resource_type_name | configuration_name

library_element_declaration ::= data_type_declaration
| function_declaration | function_block_declaration
| program_declaration | configuration_declaration

SEMANTICS: These productions reflect the basic programming model defined in 1.4.3, where *declarations* are the basic mechanism for the production of named *library elements.* The syntax and semantics of the non-terminal symbols given above are defined in the sub-clauses listed below.

Non-terminal symbol	Syntax	Semantic
data_type_name data_type_declaration	B.1.3	2.3
function_name function_declaration	B.1.5.1	2.5.1
function_block_type_name function_block_declaration	B.1.5.2	2.5.2
program_type_name program_declaration	B.1.5.3	2.5.3
resource_type_name configuration_name configuration_declaration	B.1.7	2.7

B.1 Common elements

B.1.1 *Letters, digits and identifiers*

PRODUCTION RULES:

letter ::= 'A'|'B'|<...>|'Z'|'a'|'b'|<...>|'z'

digit ::= '0'|'1'|'2'|'3'|'4'|'5'|'6'|'7'|'8'|'9'

octal_digit ::= '0'|'1'|'2'|'3'|'4'|'5'|'6'|'7'

hex_digit ::= digit|'A'|'B'|'C'|'D'|'E'|'F'|'a'|'b'|'c'|'d'|'e'|'f'

identifier ::= (letter|('_'(letter|digit))) {['_'](letter|digit)}

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

SEMANTICS:

The ellipsis <...> here indicates the ISO/IEC 646 sequence of 26 letters.

Characters from national character sets can be used; however, international portability of the printed representation of programs cannot be guaranteed in this case.

The case of letters shall be significant in terminal symbols, but not in other syntactic elements.

B.1.2 *Constants*

PRODUCTION RULE:

constant ::= numeric_literal | character_string | time_literal

SEMANTICS:

The external representations of data described in 2.2 are designated as "constants" in this annex.

B.1.2.1 *Numeric literals*

PRODUCTION RULES:

numeric_literal ::= integer_literal | real_literal

integer_literal ::= signed_integer | binary_integer | octal_integer | hex_integer

signed_integer ::= ['+' |'-'] integer

integer ::= digit {['_'] digit}

binary_integer ::= '2#' bit {['_'] bit}

bit ::= '1' | '0'

octal_integer ::= '8#' octal_digit {['_'] octal_digit}

hex_integer ::= '16#' hex_digit {['_'] hex_digit}

real_literal ::= signed_integer '.' integer [exponent]

exponent ::= ('E' | 'e') ['+'|'-'] integer

SEMANTICS: See 2.2.1.

B.1.2.2 *Character strings*

PRODUCTION RULES:

character_string ::= " ' " {character_representation} " ' "

character_representation ::= <any printable character except '$'> |'$' hex_digit hex_digit |'$$' |"$'"|'$L'|'$N'|'$P'|'$R'|'$T'|'$l'|'$n'|'$p'|'$r'|'$t'

SEMANTICS: See 2.2.2.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

B.1.2.3 *Time literals*

PRODUCTION RULE:

time_literal ::= duration | time_of_day | date | date_and_time

SEMANTICS: See 2.2.3.

B.1.2.3.1 *Duration*

PRODUCTION RULES:

duration ::= ('T'|'t'|'TIME'|'time') '#' ['-'] interval

interval ::= days | hours | minutes | seconds | milliseconds

days ::= fixed_point ('d'|'D') | integer ('d'|'D') ['_'] hours

fixed_point ::= integer ['.' integer]

hours ::= fixed_point ('h'|'H') | integer ('h'|'H') ['_'] minutes

minutes ::= fixed_point ('m'|'M') | integer ('m'|'M') ['_'] seconds

seconds ::= fixed_point ('s'|'S') | integer ('s'|'S') ['_'] milliseconds

milliseconds ::= fixed_point ('ms'|'MS')

SEMANTICS: See 2.2.3.1.

NOTE - The semantics of 2.2.3.1 impose additional constraints on the allowable values of hours, minutes, seconds, and milliseconds.

B.1.2.3.2 *Time of day and date*

PRODUCTION RULES:

time_of_day ::= ('TIME_OF_DAY'|'time_of_day'|'TOD'|'tod') '#' daytime

daytime ::= day_hour ':' day_minute ':' day_second

day_hour ::= integer

day_minute ::= integer

day_second ::= fixed_point

date ::= ('DATE'|'date'|'D'|'d') '#' date_literal

date_literal ::= year '-' month '-' day

year ::= integer

month ::= integer

day ::= integer

date_and_time ::= ('DATE_AND_TIME'|'date_and_time'|'DT'|'dt') '#' date_literal '-' daytime

SEMANTICS: See 2.2.3.2.

NOTE - The semantics of 2.2.3.2 impose additional constraints on the allowable values of day_hour, day_minute, day_second, year, month, and day.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

B.1.3 *Data types*

PRODUCTION RULES:

data_type_name ::= non_generic_type_name | generic_type_name

non_generic_type_name ::= elementary_type_name | derived_type_name

SEMANTICS: See 2.3.

B.1.3.1 *Elementary data types*

PRODUCTION RULES:

elementary_type_name ::= numeric_type_name | date_type_name
| bit_string_type_name |'STRING'|'TIME'

numeric_type_name ::= integer_type_name | real_type_name

integer_type_name ::= signed_integer_type_name | unsigned_integer_type_name

signed_integer_type_name ::= 'SINT'|'INT'|'DINT'|'LINT'

unsigned_integer_type_name ::= 'USINT'|'UINT'|'UDINT'|'ULINT'

real_type_name ::= 'REAL'|'LREAL'

date_type_name ::= 'DATE'|'TIME_OF_DAY'|'TOD'|'DATE_AND_TIME'|'DT'

bit_string_type_name ::= 'BOOL'|'BYTE'|'WORD'|'DWORD'|'LWORD'

SEMANTICS: See 2.3.1.

B.1.3.2 *Generic data types*

PRODUCTION RULE:

generic_type_name ::= 'ANY'|'ANY_NUM'|'ANY_REAL'|'ANY_INT'|'ANY_BIT'
|'ANY_DATE'

SEMANTICS: See 2.3.2.

B.1.3.3 *Derived data types*

PRODUCTION RULES:

derived_type_name ::= single_element_type_name | array_type_name
| structure_type_name

single_element_type_name ::= simple_type_name | subrange_type_name
| enumerated_type_name

simple_type_name ::= identifier

subrange_type_name ::= identifier

enumerated_type_name ::= identifier

array_type_name ::= identifier

structure_type_name ::= identifier

data_type_declaration ::= 'TYPE' type_declaration ';' {type_declaration ';'} 'END_TYPE'

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

type_declaration ::= single_element_type_declaration | array_type_declaration
| structure_type_declaration

single_element_type_declaration ::= simple_type_declaration
| subrange_type_declaration | enumerated_type_declaration

simple_type_declaration ::= simple_type_name ':' simple_spec_init

simple_spec_init ::= simple_specification [':=' constant]

simple_specification ::= elementary_type_name | simple_type_name

subrange_type_declaration ::= subrange_type_name ':' subrange_spec_init

subrange_spec_init ::= subrange_specification [':=' signed_integer]

subrange_specification ::= integer_type_name '(' subrange')' | subrange_type_name

subrange ::= signed_integer '..' signed_integer

enumerated_type_declaration ::= enumerated_type_name ':' enumerated_spec_init

enumerated_spec_init ::= enumerated_specification [':=' enumerated_value]

enumerated_specification ::= ('(' enumerated_value {',' enumerated_value} ')')
| enumerated_type_name

enumerated_value ::= identifier

array_type_declaration ::= array_type_name ':' array_spec_init

array_spec_init ::= array_specification [':=' array_initialization]

array_specification ::= array_type_name
| 'ARRAY' '[' subrange {',' subrange} ']' 'OF' non_generic_type_name

array_initialization ::= array_initial_elements {',' array_initial_elements}

array_initial_elements ::= array_initial_element | integer '(' array_initial_element ')'

array_initial_element ::= constant | enumerated_value | structure_initialization
| array_initialization

structure_type_declaration ::= structure_type_name ':' structure_specification

structure_specification ::= structure_declaration | initialized_structure

initialized_structure ::= structure_type_name [structure_initialization]

structure_declaration ::= 'STRUCT' structure_element_declaration ';'
{struture_element_declaration ';'} 'END_STRUCT'

structure_element_declaration ::= structure_element_name ':'
(simple_spec_init | subrange_spec_init | enumerated_spec_init | array_spec_init
| initialized_structure)

structure_element_name ::= identifier

structure_initialization ::= '(' structure_element_initialization
{',' structure_element_initialization} ')'

structure_element_initialization ::= structure_element_name ':='
(constant | enumerated_value | array_initialization | structure_initialization)

SEMANTICS: See 2.3.3.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

B.1.4 *Variables*

PRODUCTION RULES:

variable ::= direct_variable | symbolic_variable

symbolic_variable ::= variable_name | multi_element_variable

variable_name ::= identifier

SEMANTICS: See 2.4.1.

B.1.4.1 *Directly represented variables*

PRODUCTION RULES:

direct_variable ::= '%' location_prefix size_prefix integer {'.' integer}

location_prefix ::= 'I'|'Q'|'M'

size_prefix ::= NIL| 'X' | 'B' | 'W' | 'D' | 'L

SEMANTICS: See 2.4.1.1.

B.1.4.2 *Multi-element variables*

PRODUCTION RULES:

multi_element_variable ::= array_variable | structured_variable

array_variable ::= subscripted_variable subscript_list

subscripted_variable ::= symbolic_variable

subscript_list ::= '[' subscript {',' subscript} ']'

subscript ::= expression

structured_variable ::= record_variable '.' field_selector

record_variable ::= symbolic_variable

field_selector ::= identifier

SEMANTICS: See 2.4.1.2.

B.1.4.3 *Declaration and initialization*

PRODUCTION RULES:

input_declarations ::= 'VAR_INPUT' input_declaration ';' {input_declaration ';'}
'END_VAR'

input_declaration ::= var_init_decl | edge_declaration

edge_declaration ::= var1_list ':' 'BOOL' ['R_EDGE'|'F_EDGE']

var_init_decl ::= var1_init_decl | array_var_init_decl | structured_var_init_decl
| fb_name_decl

var1_init_decl ::= var1_list ':' (simple_spec_init | subrange_spec_init
| enumerated_spec_init)

var1_list ::= variable_name {',' variable_name}

array_var_init_decl ::= var1_list ':' array_spec_init

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

structured_var_init_decl ::= var1_list ':' initialized_structure

fb_name_decl ::= fb_name_list ':' function_block_type_name

fb_name_list ::= fb_name {',' fb_name}

fb_name ::= identifier

output_declarations ::= 'VAR_OUTPUT' ['RETAIN'] var_init_decl ';' {var_init_decl ';'} 'END_VAR'

input_output_declarations ::= 'VAR_IN_OUT' var_declaration ';' {var_declaration ';'} 'END_VAR'

var_declaration ::= var1_declaration | array_var_declaration | structured_var_declaration | fb_name_decl

var1_declaration ::= var1_list ':' (simple_specification | subrange_specification | *enumerated_specification*)

array_var_declaration ::= var1_list ':' array_specification

structured_var_declaration ::= var1_list ':' structure_type_name

var_declarations ::= 'VAR' ['CONSTANT'] var_init_decl ';' {(var_init_decl ';') } 'END_VAR'

retentive_var_declarations ::= 'VAR' 'RETAIN' var_init_decl ';' {var_init_decl ';'} 'END_VAR'

located_var_declarations ::= 'VAR' ['CONSTANT'] ['RETAIN'] located_var_decl ';' {located_var_decl ';'} 'END_VAR'

located_var_decl ::= [variable_name] location ':' located_var_spec_init

external_var_declarations ::= 'VAR_EXTERNAL' external_declaration ';' {external_declaration ';'} 'END_VAR'

external_declaration ::= global_var_name ':' (simple_specification | subrange_specification | enumerated_specification | array_specification | structure_type_name | function_block_type_name)

global_var_name ::= identifier

global_var_declarations ::= 'VAR_GLOBAL' ['CONSTANT'] ['RETAIN'] global_var_decl ';' {global_var_decl ';'} 'END_VAR'

global_var_decl ::= global_var_spec ':' located_var_spec_init

global_var_spec ::= global_var_list | [global_var_name] location

located_var_spec_init ::= simple_spec_init | subrange_spec_init | enumerated_spec_init | array_spec_init | initialized_structure

location ::= 'AT' direct_variable

global_var_list ::= global_var_name {',' global_var_name}

SEMANTICS: See 2.4.2. The non-terminal "function_block_type_name" is defined in B.1.5.2.

B.1.5 *Program organization units*

B.1.5.1 *Functions*

PRODUCTION RULES:

function_name ::= standard_function_name | derived_function_name

standard_function_name ::= <as defined in 2.5.1.5>

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

```
derived_function_name ::= identifier

function_declaration ::=
    'FUNCTION' derived_function_name ':' (elementary_type_name | derived_type_name)
      input_declarations
      ['VAR' ['CONSTANT'] function_var_decls 'END_VAR']
      function_body
    'END_FUNCTION'

function_var_decls ::= function_var_decl ';' {function_var_decl ';'}

function_var_decl ::= var1_declaration | array_var_declaration
    | structured_var_declaration

function_body ::= ladder_diagram | function_block_diagram | instruction_list
    | statement_list
```

SEMANTICS: See 2.5.1.

NOTES

1 This syntax does not reflect the fact that function block references and invocations are not allowed in function bodies.

2 Ladder diagrams and function block diagrams are graphically represented as defined in clause 4. The non-terminals *instruction_list* and *statement_list* are defined in B.2.1 and B.3.2, respectively.

B.1.5.2 *Function blocks*

PRODUCTION RULES:

```
function_block_type_name ::= standard_function_block_name | derived_function_
    block_name

standard_function_block_name ::= <as defined in 2.5.2.3>

derived_function_block_name ::= identifier

function_block_declaration ::=
    'FUNCTION_BLOCK' derived_function_block_name
      {fb_io_var_declarations}
      {other_var_declarations}
      function_block_body
    'END_FUNCTION_BLOCK'

fb_io_var_declarations ::= input_declarations | output_declarations
      | input_output_declarations

other_var_declarations ::= external_var_declarations | var_declarations
      | retentive_var_declarations

function_block_body ::= sequential_function_chart | ladder_diagram
    | function_block_diagram | instruction_list | statement_list
```

SEMANTICS: See 2.5.2.

NOTES

1 Ladder diagrams and function block diagrams are graphically represented as defined in clause 4.

2 The non-terminals *sequential_function_chart*, *instruction_list*, and *statement_list* are defined in B.1.6, B.2, and B.3.2, respectively.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

B.1.5.3 *Programs*

PRODUCTION RULES:

program_type_name ::= identifier

program_declaration ::=
'PROGRAM' program_type_name
{fb_io_var_declarations}
{other_var_declarations | located_var_declarations | global_var_declarations}
[program_access_decls]
function_block_body
'END_PROGRAM'

program_access_decls ::=
'VAR_ACCESS' program_access_decl ';'
{program_access_decl ';' }
'END_VAR'

program_access_decl ::= access_name ':' symbolic_variable ':'
non_generic_type_name direction

SEMANTICS: See 2.5.3.

B.1.6 *Sequential function chart elements*

PRODUCTION RULES:

sequential_function_chart ::= sfc_network {sfc_network}

sfc_network ::= initial_step {step | transition | action}

initial_step ::= 'INITIAL_STEP' step_name ':' {action_association ';'} 'END_STEP'

step ::= 'STEP' step_name ':' {action_association ';'} 'END_STEP'

step_name ::= identifier

action_association ::= action_name '(' action_qualifier {',' feedback_name} ')'

action_name ::= identifier

action_qualifier ::= 'N' | 'R' | 'S' | 'P' | timed_qualifier ',' action_time

timed_qualifier ::= 'L' | 'D' | 'SD' | 'DS' | 'SL'

action_time ::= duration | variable_name

feedback_name ::= variable_name

transition ::= 'TRANSITION' (transition_name | unnamed_trans) transition_condition
'END_TRANSITION'

unnamed_trans ::= 'FROM' steps 'TO' steps

transition_name ::= identifier

steps ::= step_name | '(' step_name ',' step_name {',' step_name} ')'

transition_condition ::= ':' instruction_list | ':=' expression ';' | ':' (fbd_network | rung)

action ::= 'ACTION' action_name ':'
function_block_body
'END_ACTION'

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

SEMANTICS: See 2.6. The use of function block diagram networks and ladder diagram rungs, denoted by the non-terminals *fbd_network* and *rung*, respectively, for the expression of transition conditions shall be as defined in 2.6.3.

NOTE - The non-terminals *instruction_list* and *expression* are defined in B.2.1 and B.3.1, respectively.

B.1.7 *Configuration elements*

PRODUCTION RULES:

configuration_name ::= identifier

resource_type_name ::= identifier

configuration_declaration ::= 'CONFIGURATION' configuration_name
[global_var_declarations]
resource_declaration
{resource_declaration}
[access_declarations]
'END_CONFIGURATION'

resource_declaration ::= 'RESOURCE' resource_name 'ON' resource_type_name
[global_var_declarations]
{task_configuration ';'}
program_configuration ';'
{program_configuration ';'}
'END_RESOURCE'

resource_name ::= identifier

access_declarations ::= 'VAR_ACCESS' access_declaration ';' {access_declaration ';'}
'END_VAR'

access_declaration ::= access_name ':' access_path ':' non_generic_type_name
[direction]

access_path ::= [resource_name '.'] direct_variable
| resource_name '.' program_io_reference | global_var_reference

global_var_reference ::= [resource_name '.'] global_var_name
['.' structure_element_name]

access_name ::= identifier

program_io_reference ::= program_input_reference | program_output_reference

program_output_reference ::= program_name '.' symbolic_variable

program_input_reference ::= program_name '.' symbolic_variable

program_name ::= identifier

direction ::= 'READ_WRITE' | 'READ_ONLY'

task_configuration ::= 'TASK' task_name task_initialization

task_name ::= identifier

task_initialization ::= '(' ['SINGLE' ':=' data_source ','] ['INTERVAL' ':=' data_source ','
'PRIORITY' ':=' integer ')'

data_source ::= constant | global_var_reference | program_output_reference
| direct_variable

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

```
program_configuration ::= 'PROGRAM' program_name ['WITH' task_name] ':'
                          program_type_name ['(' prog_conf_elements ')']
prog_conf_elements ::= prog_conf_element {',' prog_conf_element}
prog_conf_element ::= fb_task | prog_cnxn
fb_task ::= fb_name 'WITH' task_name
prog_cnxn ::= symbolic_variable ':=' prog_data_source
            | symbolic_variable '=>' data_sink
prog_data_source ::= constant | global_var_reference | direct_variable
data_sink ::= global_var_reference | direct_variable
```

SEMANTICS: See 2.7.

B.2 Language IL (Instruction List)

B.2.1 *Instructions and operands*

PRODUCTION RULES:

```
instruction_list ::= instruction {instruction}
instruction ::= [[label ':'] (il_operation | il_fb_call)] EOL
label ::= identifier
il_operation ::= il_operator [' ' il_operand_list]
il_operand_list ::= il_operand {',' il_operand}
il_operand ::= [identifier ':='] (constant | variable)
il_fb_call ::= 'CAL' ['C'['N']] fb_name ['(' il_operand_list ')']
```

SEMANTICS: See 3.2.

B.2.2 *Operators*

PRODUCTION RULES:

```
il_operator ::= ('LD' | 'ST') ['N'] | 'S' | 'R'
      | ('AND' | 'OR' | 'XOR') ['N'] ['(']
      | ('ADD' | 'SUB' | 'MUL' | 'DIV') ['(']
      | ('GT' | 'GE' | 'EQ' | 'NE' | 'LT' | 'LE') ['(']
      | ('JMP' | 'RET') ['C' ['N']]
      |'S1' | 'R1' | 'CLK' | 'CU' | 'CD' | 'PV'
      | ' IN' | 'PT' | ')'
      | function_name
```

SEMANTICS: See 3.2.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

B.3 Language ST (Structured Text)

B.3.1 *Expressions*

PRODUCTION RULES:

expression ::= xor_expression {'OR' xor_expression}

xor_expression ::= and_expression {'XOR' and_expression}

and_expression ::= comparison {('&' | 'AND') comparison}

comparison ::= add_expression {comparison_operator add_expression}

comparison_operator ::= '<' | '>' | '<=' | '>=' | '=' | '<>'

add_expression ::= term {add_operator term}

add_operator ::= '+' | '-'

term ::= power_expression {multiply_operator power_expression}

multiply_operator ::= '*' | '/' | 'MOD'

power_expression ::= unary_expression {'**' unary_expression}

unary_expression ::= [unary_operator] primary_expression

unary_operator ::= '-' | 'NOT'

primary_expression ::= constant | variable | '(' expression ')'
| function_name '(' [st_function_inputs] ')'

st_function_inputs ::= st_function_input { ',' st_function_input}

st_function_input ::= [variable_name ':='] expression

SEMANTICS: These definitions have been arranged to show a top-down derivation of expression structure. The precedence of operations is then implied by a "bottom-up" reading of the definitions of the various kinds of expressions. Further discussion of the semantics of these definitions is given in 3.3.1.

B.3.2 *Statements*

PRODUCTION RULE:

statement_list ::= statement ';' {statement ';'}

statement ::= NIL | assignment_statement | subprogram_control_statement
| selection_statement | iteration_statement

SEMANTICS: See 3.3.2.

B.3.2.1 *Assignment statements*

PRODUCTION RULE:

assignment_statement ::= variable ':=' expression

SEMANTICS: See 3.3.2.1.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

B.3.2.2 *Subprogram control statements*

PRODUCTION RULES:

subprogram_control_statement ::= fb_invocation | 'RETURN'

fb_invocation ::= fb_name '(' [fb_input_assignment {',' fb_input_assignment}] ')'

fb_input_assignment ::= variable_name ':=' expression

SEMANTICS: See 3.3.2.2.

B.3.2.3 *Selection statements*

PRODUCTION RULES:

selection_statement ::= if_statement | case_statement

if_statement ::= 'IF' expression 'THEN' statement_list
{'ELSIF' expression 'THEN' statement_list}
['ELSE' statement_list]
'END_IF'

case_statement ::= 'CASE' expression 'OF'
case_element {case_element}
['ELSE' statement_list]
'END_CASE'

case_element ::= case_list ':' statement_list

case_list ::= case_list_element {',' case_list_element}

case_list_element ::= subrange | signed_integer

SEMANTICS: See 3.3.2.3.

B.3.2.4 *Iteration statements*

PRODUCTION RULES:

iteration_statement ::= for_statement | while_statement | repeat_statement
| exit_statement

for_statement ::= 'FOR' control_variable ':=' for_list 'DO' statement_list 'END_FOR'

control_variable ::= identifier

for_list ::= expression 'TO' expression ['BY' expression]

while_statement ::= 'WHILE' expression 'DO' statement_list 'END_WHILE'

repeat_statement ::= 'REPEAT' statement_list 'UNTIL' expression 'END_REPEAT'

exit_statement ::= 'EXIT'

SEMANTICS: See 3.3.2.4.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

Annex C
(normative)

Delimiters and keywords

The usages of delimiters and keywords in IEC 1131-3 is summarized in tables C.1 and C.2. National standards organizations can publish tables of translations for the textual portions of the delimiters listed in table C.1 and the keywords listed in table C.2.

Table C.1 – Delimiters

Delimiters	Clause	Usage
Space	2.1.4	As specified in 2.1.4.
(* *)	2.1.5	Begin comment End comment
+	2.2.1 3.3.1	Leading sign of decimal literal Addition operator
–	2.2.1 2.2.3.2 3.3.1 4.1.1	Leading sign of decimal literal Year-month-day separator Subtraction, negation operator Horizontal line*
#	2.2.1 2.2.3	Based number separator Time literal separator
.	2.2.1 2.4.1.1 2.4.1.2 2.5.2.1	Integer/fraction separator Hierarchical address separator Structure element separator Function block structure separator
e or E	2.2.1	Real exponent delimiter
'	2.2.2	Start and end of character string
$	2.2.2	Start of special character in strings
2.2.3 – Time literal delimiters, including: t#, T#, d, D, h, H, m, M, s, S, ms, MS DATE#, date#, D#, d#, TIME_OF_DAY#, time_of_day# TOD#, tod#, DATE_AND_TIME#, date_and_time#, DT#, dt#		
:	2.2.3.2 2.3.3.1 2.4.2 2.6.2 2.7 2.7 2.7 3.2.1 4.1.2	Time of day separator Type name/specification separator Variable/type separator Step name terminator RESOURCE name/type separator PROGRAM name/type separator Access name/path/type separator Instruction label terminator Network label terminator
:=	2.3.3.1 2.7.1 3.3.2.1	Initialization operator Input connection operator Assignment operator

(continued overleaf)

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table C.1 – *(concluded)*

Delimiters	Clause	Usage
( )	2.3.3.1	Enumeration list delimiters
	2.3.3.1	Subrange delimiters
	2.4.1.2	Array subscript delimiters
	2.4.2	*String length delimiters*
	2.4.2	Multiple initialization
	3.2.2	Instruction List modifier/operator
	3.3.1	Function arguments
	3.3.1	Subexpression hierarchy
	3.3.2.2	Function block input list delimiters
,	2.3.3.1	Enumeration list separator
	2.3.3.2	Initial value separator
	2.4.1	Array subscript separator
	2.4.2	Declared variable separator
	2.5.2.1	Function block initial value separator
	2.5.2.1	Function block input list separator
	3.2.1	Operand list separator
	3.3.1	Function argument list separator
	3.3.2.3	CASE value list separator
;	2.3.3.1	Type declaration separator
	3.3	Statement separator
..	2.3.3.1	Subrange separator
	3.3.2.3	CASE range separator
%	2.4.1.1	Direct representation prefix
3.3.1 – Infix operators, including: **, NOT, *, /, MOD, +, -, <, >, <=, >=, =, <>, &, AND, XOR, OR		
=>	2.7.1	Output connection operator
| or !	4.1.1	Vertical lines (note)

NOTE - "!" is only allowed when "|" does not exist in a national character set.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

Table C.2 – Keywords

Keywords	Clause
Action qualifiers	2.6.4.4
ACTION...END_ACTION	2.6.4.1
ARRAY...OF	2.3.3.1
AT	2.4.3
CASE...OF...ELSE...END_CASE	3.3.2.3
CONFIGURATION...END_CONFIGURATION	2.7.1
CONSTANT	2.4.3
Data type names	2.3
EN, ENO	2.5.1.2
EXIT	3.3.2.4
FALSE	2.2.1
F_EDGE	2.5.2.2
FOR...TO...BY...DO...END_FOR	3.3.2.4
FUNCTION...END_FUNCTION	2.5.1.3
Function names	2.5.1
FUNCTION_BLOCK...END_FUNCTION_BLOCK	2.5.2.2
Function Block names	2.5.2
IF...THEN...ELSIF...ELSE...END_IF	3.3.2.3
INITIAL_STEP...END_STEP	2.6.2
PROGRAM...WITH...	2.7.1
PROGRAM...END_PROGRAM	2.5.3
R_EDGE	2.5.2.2
READ_ONLY, READ_WRITE	2.7.1
REPEAT...UNTIL...END_REPEAT	3.3.2.4
RESOURCE...ON...END_RESOURCE	2.7.1
RETAIN	2.4.3
RETURN	3.3.2.2
STEP...END_STEP	2.6.2
STRUCT...END_STRUCT	2.3.3.1
TASK	2.7.2
Textual operators (IL language)	3.2.2
(ST language)	3.3.1
TRANSITION...FROM...TO...END_TRANSITION	2.6.3
TRUE	2.2.1
TYPE...END_TYPE	2.3.3.1
VAR...END_VAR VAR_INPUT...END_VAR VAR_OUTPUT...END_VAR VAR_IN_OUT...END_VAR VAR_EXTERNAL...END_VAR	2.4.2
VAR_ACCESS...END_VAR	2.7.1
VAR_GLOBAL...END_VAR	2.7.1
WHILE...DO...END_WHILE	3.3.2.4
WITH	2.7.1

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

Annex D
(normative)

Implementation-dependent parameters

The implementation-dependent parameters defined in IEC 1131-3, and the primary reference clause for each, are listed in table D.1.

Table D.1 – Implementation-dependent parameters

Clause	Parameters
1.5.1	Error handling procedures
2.1.1	National characters used # or "pounds Sterling" sign $ or "currency" sign | or !
2.1.2	Maximum length of identifiers
2.1.5	Maximum comment length
2.2.3.1	Range of values of duration
2.3.1	Range of values for variables of type TIME Precision of representation of seconds in types TIME_OF_DAY and DATE_AND_TIME
2.3.3	Maximum number of array subscripts Maximum array size Maximum number of structure elements Maximum structure size Maximum number of variables per declaration
2.3.3.1	Maximum number of enumerated values
2.3.3.2	Default maximum length of STRING variables Maximum allowed length of STRING variables
2.4.1.1	Maximum number of hierarchical levels Logical or physical mapping
2.4.1.2	Maximum number of subscripts Maximum range of subscript values Maximum number of levels of structures
2.4.2	Initialization of system inputs
2.4.3	Maximum number of variables per declaration
2.5	Information to determine execution times of program organization units
2.5.1.1	Method of function representation (names or symbols)
2.5.1.3	Maximum number of function specifications
2.5.1.5	Maximum number of inputs of extensible functions
2.5.1.5.1	Effects of type conversions on accuracy
2.5.1.5.2	Accuracy of functions of one variable Implementation of arithmetic functions

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Table D.1 *(concluded)*

Clause	Parameters
2.5.2	Maximum number of function block specifications and instantiations
2.5.2.3.3	PVmin, PVmax of counters
2.5.3	Program size limitations
2.6	Timing and portability effects of execution control elements
2.6.2	Precision of step elapsed time Maximum number of steps per SFC
2.6.3	Maximum number of transitions per SFC and per step
2.6.4	Action control mechanism
2.6.4.2	Maximum number of action blocks per step
2.6.5	Graphic indication of step state *Transition clearing time* Maximum width of diverge/converge constructs
2.7.1	Contents of RESOURCE libraries
2.7.2	Maximum number of tasks Task interval resolution Pre-emptive or non-pre-emptive scheduling
3.3.1	Maximum length of expressions Partial evaluation of Boolean expressions
3.3.2	Maximum length of statements
3.3.2.3	Maximum number of CASE selections
3.3.2.4	Value of control variable upon termination of FOR loop
4.1.1	Graphic/semigraphic representation Restrictions on network topology
4.1.3	Evaluation order of feedback loops

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Annex E
(normative)

Error conditions

The error conditions defined in IEC 1131-3, and the primary reference clause for each, are listed in table E.1. These errors may be detected during preparation of the program for execution or during execution of the program. The manufacturer shall specify the disposition of these errors according to the provisions of subclause 1.5.1 of this part.

Table E.1 – Error conditions

Clause	Errors conditions
2.3.3.1	Value of a variable exceeds the specified subrange
2.4.2	Length of initialization list does not match number of array entries
2.5.1.5.1	Type conversion errors
2.5.1.5.2	Numerical result exceeds range for data type Division by zero
2.5.1.5.4	Mixed input data types to a selection function Selector (K) out of range for MUX function
2.5.1.5.5	Invalid character position specified Result exceeds maximum string length
2.5.1.5.6	Result exceeds range for data type
2.6.2	Zero or more than one initial steps in SFC network User program attempts to modify step state or time
2.6.2.5	Simultaneously true, non-prioritized transitions in a selection divergence
2.6.3	Side effects in evaluation of transition condition
2.6.4.5	Action control contention error
2.6.5	"Unsafe" or "unreachable" SFC
2.7.1	Data type conflict in VAR_ACCESS
2.7.2	Tasks require too many processor resources Execution deadline not met Other task scheduling conflicts
3.2.2	Numerical result exceeds range for data type
3.3.1	Division by zero Invalid data type for operation
3.3.2.1	Return from function without value assigned
3.3.2.4	Iteration fails to terminate
4.1.1	Same identifier used as connector label and element name
4.1.4	Uninitialized feedback variable
4.1.5	As for 2.5.1.5.2

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Annex F
(informative)

Examples

F.1 Function WEIGH

Example function WEIGH provides the functions of BCD-to-binary conversion of a gross-weight input from a scale, the binary integer subtraction of a tare weight which has been previously converted and stored in the memory of the programmable controller, and the conversion of the resulting net weight back to BCD form, e.g., for an output display. The "EN" input is used to indicate that the scale is ready to perform the weighing operation.

The "ENO" output indicates that an appropriate command exists (e.g., from an operator pushbutton), the scale is in proper condition for the weight to be read, and each function has a correct result.

A textual form of the declaration of this function is:

```
FUNCTION WEIGH : WORD (* BCD encoded *)
  VAR_INPUT (* "EN" input is used to indicate "scale ready" *)
     weigh_command : BOOL ;
     gross_weight : WORD ; (* BCD encoded *)
     tare_weight : INT ;
  END_VAR
(* Function Body *)
END_FUNCTION                (* Implicit "ENO" *)
```

The body of function WEIGH in the IL language is:


```
            LD          weigh_command
            JMPC        WEIGH_NOW
            ST          ENO             (* No weighing, 0 to "ENO" *)
            RET
WEIGH_NOW:  LD          gross_weight
            BCD_TO_INT
            SUB         tare_weight
            INT_TO_BCD                  (* Return evaluated weight *)
```

The body of function WEIGH in the ST language is:


```
IF weight_command THEN
  WEIGH  := INT_TO_BCD (BCD_TO INT (gross_weight) - tare_weight) ;
END_IF ;
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale


An equivalent graphical declaration of function WEIGH is:



The function body in the LD language is:



The function body in the FBD language is:



F.2 Function block CMD_MONITOR

Example function block CMD_MONITOR illustrates the control of an operative unit which is capable of responding to a Boolean command (the CMD output) and returning a Boolean feedback signal (the FDBK input) indicating successful completion of the commanded action. The function block provides for manual control via the MAN_CMD input, or automated control via the AUTO_CMD input, depending on the state of the AUTO_MODE input (0 or 1 respectively). Verification of the MAN_CMD input is provided via the MAN_CMD_CHK input, which must be 0 in order to enable the MAN_CMD input.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS


Not for Resale

If confirmation of command completion is not received on the FDBK input within a predetermined time specified by the T_CMD_MAX input, the command is cancelled and an alarm condition is signalled via the ALRM output. The alarm condition may be cancelled by the ACK (acknowledge) input, enabling further operation of the command cycle.

A textual form of the declaration of function block CMD_MONITOR is:

```
FUNCTION_BLOCK CMD_MONITOR
  VAR_INPUT AUTO_CMD : BOOL ;   (* Automated command *)
  AUTO_MODE : BOOL ;            (* AUTO_CMD enable *)
  MAN_CMD : BOOL ;              (* Manual command *)
  MAN_CMD_CHK : BOOL ;          (* Negated MAN_CMD to debounce *)
  T_CMD_MAX : TIME ;            (* Max time from CMD to FDBK *)
  FDBK : BOOL ;                 (* Confirmation of CMD completion by operative unit *)
  ACK : BOOL ;                  (* Acknowledge/cancel ALRM *)
END_VAR
VAR_OUTPUT CMD : BOOL ;         (* Command to operative unit *)
  ALRM : BOOL ;                 (* T_CMD_MAX expired without FDBK *)
END_VAR
VAR CMD_TMR : TON ;             (* CMD-to-FDBK timer *)
  ALRM_FF : SR ;                (* Note over-riding "S" input: *)
END_VAR                         (* Command must be cancelled before "ACK" can cancel alarm *)
(* Function Block Body *)
END_FUNCTION_BLOCK
```

An equivalent graphical declaration is:



The body of function block CMD_MONITOR in the ST language is:


```
CMD := AUTO_CMD & AUTO_MODE
       OR MAN_CMD & NOT MAN_CMD_CHK & NOT AUTO_MODE ;
CMD_TMR (IN := CMD, PT := T_CMD_MAX) ;
ALRM_FF (S1 := CMD_TMR.Q & NOT FDBK, R := ACK) ;
ALRM := ALRM_FF.Q1 ;
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale


The body of function block CMD_MONITOR in the IL language is:

```
LD          T_CMD_MAX
ST          CMD_TMR.PT          (* Store an input to the TON FB *)
LD          AUTO_CMD
AND         AUTO_MODE
OR(         MAN_CMD
ANDN        AUTO_MODE
ANDN        MAN_CMD_CHK
)
ST          CMD
IN          CMD_TMR             (* Invoke the TON FB *)
LD          CMD_TMR.Q
ANDN        FDBK
ST          ALRM_FF.S1          (* Store an input to the SR FB *)
LD          ACK
R           ALRM_FF             (* Invoke the SR FB *)
LD          ALRM_FF.Q1
ST          ALRM
```

The body of function block CMD_MONITOR in the LD language is:



The body of function block CMD_MONITOR in the FBD language is:




Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

F.3 Function block FWD_REV_MON

Example function block FWD_REV_MON illustrates the control of an operative unit capable of two-way positioning action, e.g., a motor-operated valve. Both automated and manual control modes are possible, with alarm capabilities provided for each direction of motion, as described for function block CMD_MONITOR above. In addition, contention between forward and reverse commands causes the cancellation of both commands and signalling of an alarm condition. The Boolean OR of all alarm conditions is made available as a KLAXON output for operator signaling.

A graphical declaration of this function block is:



Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

A textual form of the declaration of function block FWD_REV_MON is:

```
FUNCTION_BLOCK FWD_REV_MON
  VAR_INPUT AUTO : BOOL ;              (* Enable automated commands *)
  ACK : BOOL ;                         (* Acknowledge/cancel all alarms *)
  AUTO_FWD : BOOL ;                    (* Automated forward command *)
  MAN_FWD : BOOL ;                     (* Manual forward command *)
  MAN_FWD_CHK : BOOL ;                 (* Negated MAN_FWD for debouncing *)
  T_FWD_MAX : TIME ;                   (* Maximum time from FWD_CMD to FWD_FDBK *)
  FWD_FDBK : BOOL ;                    (* Confirmation of FWD_CMD completion *)
                                       (* by operative unit *)
  AUTO_REV : BOOL ;                    (* Automated reverse command *)
  MAN_REV : BOOL ;                     (* Manual reverse command *)
  MAN_REV_CHK : BOOL ;                 (* Negated MAN_REV for debouncing *)
  T_REV_MAX : TIME ;                   (* Maximum time from REV_CMD to REV_FDBK *)
  REV_FDBK : BOOL ;                    (* Confirmation of REV_CMD completion *)
END_VAR                                (* by operative unit *)

VAR_OUTPUT KLAXON : BOOL ;             (* Any alarm active *)
  FWD_REV_ALRM : BOOL ;                (* Forward/reverse command conflict *)
  FWD_CMD : BOOL ;                     (* "Forward" command to operative unit *)
  FWD_ALRM : BOOL ;                    (* T_FWD_MAX expired without FWD_FDBK *)
  REV_CMD : BOOL ;                     (* "Reverse" command to operative unit *)
  REV_ALRM : BOOL ;                    (* T_REV_MAX expired without REV_FDBK *)
END_VAR

VAR FWD_MON : CMD_MONITOR ;            (* "Forward" command monitor *)
  REV_MON : CMD_MONITOR ;              (* "Reverse" command monitor *)
  FWD_REV_FF : SR ;                    (* Forward/reverse contention latch *)
END_VAR

(* Function block body *)
END_FUNCTION_BLOCK
```

The body of function block FWD_REV_MON can be written in the ST language as:

```
(* Evaluate internal function blocks *)

FWD_MON          (AUTO_MODE := AUTO,
                 ACK := ACK,
                 AUTO_CMD := AUTO_FWD,
                 MAN_CMD := MAN_FWD,
                 MAN_CMD_CHK := MAN_FWD_CHK,
                 T_CMD_MAX := T_FWD_MAX,
                 FDBK := FWD_FDBK) ;
REV_MON          (AUTO MODE := AUTO,
                 ACK := ACK,
                 AUTO_CMD := AUTO_REV,
                 MAN_CMD := MAN_REV,
                 MAN_CMD_CHK := MAN_REV_CHK,
                 T_CMD_MAX := T_REV_MAX,
                 FDBK := REV_FDBK) ;
FWD_REV_FF       (S1 := FWD_MON.CMD & REV_MON.CMD, R := ACK) ;

(* Transfer data to outputs *)

FWD_REV_ ALRM := FWD_REV_FF.Q1 ;
FWD_CMD := FWD_MON.CMD & NOT FWD_REV_ALRM ;
FWD_ ALRM := FWD_MON.ALRM ;
REV_CMD := REV_MON.CMD & NOT FWD_REV_ALRM ;
REV_ALRM := REV_MON.ALRM ;
KLAXON := FWD_ALRM OR REV_ALRM OR FWD_REV_ALRM ;
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS


Not for Resale

The body of function block FWD_REV_MON in the IL language is:

```
LD      AUTO                    (* Load common inputs *)
ST      FWD_MON.AUTO_MODE
ST      REV_MON.AUTO_MODE
LD      ACK
ST      FWD_MON.ACK
ST      REV_MON.ACK
ST      FWD_REV_FF.R
LD      AUTO_FWD                (* Load inputs to FWD_MON *)
ST      FWD_MON.AUTO_CMD
LD      MAN_FWD
ST      FWD_MON.MAN_CMD
LD      MAN_FWD_CHK
ST      FWD_MON.MAN_CMD_CHK
LD      T_FWD_MAX
ST      FWD_MON.T_CMD_MAX
LD      FWD_FDBK
ST      FWD_MON.FDBK
CAL     FWD_MON                 (* Activate FWD_MON *)
LD      AUTO_REV                (* Load inputs to REV_MON *)
ST      REV_MON.AUTO_CMD
LD      MAN_REV
ST      REV_MON.MAN_CMD
LD      MAN_REV_CHK
ST      REV_MON.MAN_CMD_CHK
LD      T_REV_MAX
ST      REV_MON.T_CMD_MAX
LD      REV_FDBK
ST      REV_MON.FDBK
CAL     REV_MON                 (* Activate REV_MON *)
LD      FWD_MON.CMD             (* Check for contention *)
AND     REV_MON.CMD
S1      FWD_REV_FF              (* Latch contention condition *)
LD      FWD_REV_FF.Q
ST      FWD_REV_ALRM            (* Contention alarm *)
LD      FWD_MON.CMD             (* "Forward" command and alarm *)
ANDN    FWD_REV_ALRM
ST      FWD_CMD
LD      FWD_MON.ALRM
ST      FWD_ALRM
LD      REV_MON.CMD             (* "Reverse" command and alarm *)
ANDN    FWD_REV_ALRM
ST      REV_CMD
LD      REV_MON.ALRM
ST      REV_ALRM
OR      FWD_ALRM                (* OR all alarms *)
OR      FWD_REV_ALRM
ST      KLAXON
```


Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

The body of function block FWD_REV_MON in the FBD language is:



Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

The body of function block FWD_REV_MON in the LD language is:



Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

F.4 Function block STACK_INT

This function block provides a stack of up to 128 integers. The usual stack operations of PUSH and POP are provided by edge-triggered Boolean inputs. An overriding reset (R1) input is provided; the maximum stack depth (N) is determined at the time of resetting. In addition to the top-of-stack data (OUT), Boolean outputs are provided indicating stack empty and stack overflow states.

A textual form of the declaration of this function block is:

```
FUNCTION_BLOCK STACK_INT
  VAR_INPUT PUSH, POP : BOOL R_EDGE ;        (* Basic stack operations *)
            R1 : BOOL ;                      (* Over-riding reset *)
            IN : INT ;                       (* Input to be pushed *)
            N : INT ;                        (* Maximum depth after reset *)
  END_VAR
  VAR_OUTPUT EMPTY : BOOL := 1 ;             (* Stack empty *)
            OFLO : BOOL := 0 ;               (* Stack overflow *)
            OUT : INT := 0 ;                 (* Top of stack data *)
  END_VAR
  VAR STK : ARRAY[0..127] OF INT ;           (* Internal stack *)
            NI : INT := 128  ;               (* Storage for N upon reset *)
            PTR : INT := -1 ;                (* Stack pointer *)
  END_VAR

  (* Function block body *)

  END_FUNCTION_BLOCK
```

A graphical declaration of function block STACK_INT is:

```
                    +------------+
                    | STACK_INT  |
              BOOL--->PUSH  EMPTY|---BOOL
              BOOL--->POP     OFLO|---BOOL
              BOOL---|R1       OUT|---INT
              INT----|IN          |
              INT----|N           |
                    +------------+

(* Internal variable declarations *)

VAR STK : ARRAY[0..127] OF INT ;              (* Internal stack *)
    NI : INT := 128 ;                         (* Storage for N upon reset *)
    PTR : INT := -1 ;                         (* Stack pointer *)
END_VAR
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS


Not for Resale

The function block body in the ST language is:

```
IF R1 THEN
  OFLO := 0 ; EMPTY := 1 ; PTR := -1 ;
  NI := LIMIT (MN := 1,IN := N,MX := 128) ; OUT := 0 ;
ELSIF POP & NOT EMPTY THEN
  OFLO := 0 ; PTR := PTR-1 ; EMPTY := PTR < 0 ;
  IF EMPTY THEN OUT := 0 ;
  ELSE OUT := STK[PTR] ;
  END_IF ;
ELSIF PUSH & NOT OFLO THEN
  EMPTY := 0 ; PTR := PTR+1 ; OFLO := (PTR = NI) ;
  IF NOT OFLO THEN OUT := IN ; STK[PTR] := IN ;
  ELSE OUT := 0 ;
  END_IF ;
END_IF ;
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

The function block body in the LD language is:



Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale


The body of function block STACK_INT in the IL language is:

```
            LD      R1                          (* Dispatch on operations *)
            JMPC    RESET
            LD      POP
            ANDN    EMPTY                       (* Don't pop empty stack *)
            JMPC    POP_STK
            LD      PUSH
            ANDN    OFLO                        (* Don't push overflowed stack *)
            JMPC    PUSH_STK
            RET                                 (* Return if no operations active *)
RESET:      LD      0                           (* Stack reset operations *)
            ST      OFLO
            LD      1
            ST      EMPTY
            LD      -1
            ST      PTR
            CAL     LIMIT(MN := 1,IN := N,MX := 128)
            ST      NI
            JMP     ZRO_OUT
POP STK:    LD      0
            ST      OFLO                        (* Popped stack is not overflowing *)
            LD      PTR
            SUB     1
            ST      PTR
            LT      0                           (* Empty when PTR < 0 *)
            ST      EMPTY
            JMPC    ZRO_OUT
            LD      STK[PTR]
            JMP     SET_OUT
PUSH_STK:   LD      0
            ST      EMPTY                       (* Pushed stack is not empty *)
            LD      PTR
            ADD     1
            ST      PTR
            EQ      NI                          (* Overflow when PTR = NI *)
            ST      OFLO
            JMPC    ZRO_OUT
            LD      IN
            ST      STK[PTR]                    (* Push IN onto STK *)
            JMP     SET_OUT
ZRO_OUT:    LD      0                           (* OUT=0 for EMPTY or OFLO *)
SET_OUT:    ST      OUT
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

The body of function block STACK_INT in the FBD language is:



Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

F.5 Function block MIX_2_BRIX

Function block MIX_2_BRIX is to control the mixing of two bricks of solid material, brought one at a time on a belt, with weighed quantities of two liquid components, A and B, as shown in figure F.1. A "Start" (ST) command, which may be manual or automatic, initiates a measurement and mixing cycle beginning with simultaneous weighing and brick transport as follows:

- liquid A is weighed up to mark "a" of the weighing unit, then liquid B is weighed up to mark "b", followed by filling of the mixer from weighing unit C;
- two bricks are transported by belt into the mixer.

The cycle ends with the mixer rotating and finally tipping after a predetermined time "t1". Rotation of the mixer continues while it is emptying.

The scale reading "WC" is given as four BCD digits, and will be converted to type INT for internal operations. It is assumed that the tare (empty weight) "z" has been previously determined.





Figure F.1 – Function block MIX_2_BRIX – Physical model

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

The textual form of the declaration of this function block is:


```
FUNCTION_BLOCK MIX_2_BRIX
  VAR_INPUT
    ST : BOOL ;                    (* "Start" command *)
    d : BOOL ;                     (* Transit detector *)
    S0 : BOOL ;                    (* "Mixer up" limit switch *)
    S1 : BOOL ;                    (* "Mixer down" limit switch *)
    WC : WORD ;                    (* Current scale reading in BCD *)
    z : INT ;                      (* Tare (empty) weight *)
    WA : INT ;                     (* Desired weight of A *)
    WB : INT ;                     (* Desired weight of B *)
    t1 : TIME ;                    (* Mixing time *)
  END_VAR
  VAR_OUTPUT
    DONE ,
    VA ,                           (* Valve "A" : 0 - close, 1 - open *)
    VB ,                           (* Valve "B" : 0 - close, 1 - open *)
    VC ,                           (* Valve "C" : 0 - close, 1 - open *)
    MT ,                           (* Feed belt motor *)
    MR ,                           (* Mixer rotation motor *)
    MP0 ,                          (* Tipping motor "up" command *)
    MP1 : BOOL;                    (* Tipping motor "down" command *)
  END_VAR
  (* Function block body *)
END_FUNCTION_BLOCK
```

A graphical declaration is:



Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

The body of function block MIX_2_BRIX using graphical SFC elements with transition conditions in the ST language is:



Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

The body function block MIX_2_BRIX in a textual SFC representation using ST language elements is:

```
INITIAL_STEP START : DONE(N) ; END_STEP
TRANSITION FROM START TO (WEIGH_A, BRICK1)
    := ST & S0 & BCD_TO_INT(WC) <= z ;
END_TRANSITION

STEP WEIGH_A : VA(N) ; END_STEP
TRANSITION FROM WEIGH_A TO WEIGH_B := BCD_TO_INT(WC) >= WA+z ;
END_TRANSITION

STEP WEIGH_B : VB(N) ; END_STEP
TRANSITION FROM WEIGH_B TO FILL := BCD_TO_INT(WC) >= WA+WB+z ;
END_TRANSITION

STEP FILL : VC(N) ; END_STEP
STEP BRICK1 : MT(S) ; END_STEP
TRANSITION FROM BRICK1 TO DROP_1 := d ; END_TRANSITION
STEP DROP_1 : END_STEP
TRANSITION FROM DROP_1 TO BRICK2 := NOT d ; END_TRANSITION
STEP BRICK2 : END_STEP
TRANSITION FROM BRICK2 TO DROP_2 := d ; END_TRANSITION
STEP DROP_2 : MT(R) ; END_STEP
TRANSITION FROM (FILL,DROP_2) TO MIX
    := BCD_TO_INT(WC) <= z & NOT d ;
END_TRANSITION

STEP MIX : MR(S) ; END_STEP
TRANSITION FROM MIX TO TIP := MIX.T >= t1 ; END_TRANSITION
STEP TIP: MP1(N) ; END_STEP
TRANSITION FROM TIP TO RAISE := S1 ; END_TRANSITION
STEP RAISE : MR(R) ; MP0(N) ; END_STEP
TRANSITION FROM RAISE TO START := S0 ; END_TRANSITION
```

F.6 Analog signal processing

The purpose of this portion of this annex is to illustrate the application of the programming languages defined in this standard to accomplish the basic measurement and control functions of process-computer aided automation. The blocks shown below are not restricted to analog signals; they may be used to process any variables of the appropriate types. Similarly, other functions and function blocks defined in this standard (e.g., mathematical functions) can be used for the processing of variables which may appear as analog signals at the programmable controller's I/O terminals.


These function blocks can be typed with respect to the input and output variables shown below as REAL (e.g., XIN, XOUT) by appending the appropriate data type name, e.g., LAG1_LREAL. The default data type for these variables is REAL.

These examples are given for illustrative purposes only. Manufacturers may have varying implementations of analog signal processing elements. The inclusion of these examples is not intended to preclude the standardization of such elements by the appropriate standards bodies.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

F.6.1 *Function block LAG1*


This function block implements a first-order lag filter.




```
FUNCTION_BLOCK LAG1
  VAR_INPUT
    RUN : BOOL ;                          (* 1 = Run, 0 = reset *)
    XIN : REAL ;                          (* Input variable *)
    TAU : TIME ;                          (* Filter time constant *)
    CYCLE : TIME ;                        (* Sampling time interval *)
  END_VAR
  VAR_OUTPUT XOUT : REAL ; END_VAR        (* Filtered output *)
  VAR K : REAL ;                          (* Smoothing constant, 0.0<=K<1.0 *)
  END_VAR
  IF RUN THEN XOUT := XOUT + K *  (XIN  - XOUT) ;
  ELSE XOUT := XIN ;
  K := TIME_TO_REAL (CYCLE) / TIME_TO_REAL (CYCLE + TAU) ;
  END_IF ;
END_FUNCTION_BLOCK
```

F.6.2 *Function block DELAY*

This function block implements an N-sample delay.





```
FUNCTION_BLOCK DELAY                      (* N-sample Delay *)
  VAR_INPUT
    RUN : BOOL ;                          (* 1 = run, 0 = reset *)
    XIN : REAL ;
    N : INT                               (* 0 <= N < 128 or manufacturer *)
  END_VAR                                 (* specified maximum value *)
  VAR_OUTPUT XOUT : REAL ; END_VAR        (* Delayed output *)
  VAR X : ARRAY [0..127]                  (* N-Element queue *)
  OF REAL ;                               (* with FIFO discipline *)
  I, IXIN, IXOUT : INT := 0 ;
  END_VAR
  IF RUN THEN IXIN := MOD(IXIN + 1, 128)  ; X[IXIN] := XIN ;
              IXOUT := MOD(IXOUT + 1, 128) ; XOUT := X[IXOUT] ;
  ELSE XOUT := XIN ; IXIN := N ; IXOUT := 0 ;
       FOR I := 0 TO N DO X[I] := XIN ; END_FOR ;
  END_IF ;
END_FUNCTION_BLOCK
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

F.6.3 *Function block AVERAGE*

This function block implements a running average over N samples.





```
FUNCTION_BLOCK AVERAGE
  VAR_INPUT
    EN : BOOL ;                          (* 1 = run, 0 = reset *)
    XIN : REAL ;                         (* Input variable *)
    N : INT ;                            (* 0 <= N < 128 or manufacturer *)
  END_VAR                                (* specified maximum value *)

  VAR_OUTPUT XOUT : REAL ; END_VAR       (* Averaged output *)
  VAR SUM : REAL := 0.0 ;                (* Running sum *)
    FIFO : DELAY ;                       (* N-Element FIFO *)
  END_VAR

  SUM := SUM - FIFO.XOUT ;
  FIFO (RUN := RUN , XIN := XIN , N := N) ;
  SUM := SUM + FIFO.XOUT ;
  IF RUN THEN XOUT := SUM/N ;
  ELSE SUM := N*XIN ; XOUT := XIN ;
  END_IF ;
END_FUNCTION_BLOCK
```

F.6.4 *Function block INTEGRAL*

This function block implements integration over time.




```
FUNCTION_BLOCK INTEGRAL
  VAR_INPUT
    RUN : BOOL ;                         (* 1 = integrate, 0 = hold *)
    R1 : BOOL ;                          (* Overriding reset *)
    XIN : REAL ;                         (* Input variable *)
    X0  : REAL ;                         (* Initial value *)
    CYCLE : TIME ;                       (* Sampling period *)
  END_VAR

  VAR_OUTPUT
    Q : BOOL ;                           (* NOT R1 *)
    XOUT : REAL ;                        (* Integrated output *)
  END_VAR

  Q := NOT R1 ;
  IF R1 THEN XOUT := X0 ;
  ELSIF RUN THEN XOUT := XOUT + XIN * TIME_TO_REAL(CYCLE)
  END_IF ;
END_FUNCTION_BLOCK
```


Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

NEMA IA*2.3 94 6470247 0506545 047

F.6.5 *Function block DERIVATIVE*


This function block implements differentiation with respect to time.




```
FUNCTION_BLOCK DERIVATIVE
  VAR_INPUT
    RUN : BOOL ;                          (* 0 = reset *)
    XIN : REAL ;                          (* Input to be differentiated *)
    CYCLE : TIME ;                        (* Sampling period *)
  END_VAR
  VAR_OUTPUT
    XOUT : REAL ;                         (* Differentiated output *)
  END_VAR
  VAR X1, X2, X3 : REAL ; END_VAR
  IF RUN THEN
    XOUT := (3.0 * (XIN - X3) + X1 - X2)
    / (10.0 * TIME_TO_REAL(CYCLE)) ;
    X3 := X2 ; X2 := X1 ; X1 := XIN ;
  ELSE XOUT := 0.0; X1 := XIN ; X2 := XIN ; X3 := XIN ;
  END _IF ;
END_FUNCTION_BLOCK
```

F.6.6 *Function block HYSTERESIS*

This function block implements Boolean hysteresis on the difference of REAL inputs.





```
FUNCTION_BLOCK HYSTERESIS
    (* Boolean hysteresis on difference *)
    (* of REAL inputs, XIN1 - XIN2 *)
  VAR_INPUT XIN1, XIN2, EPS : REAL ; END_VAR
  VAR_OUTPUT Q : BOOL := 0 ; END_VAR
  IF Q THEN IF XIN1 < (XIN2 - EPS) THEN Q := 0 ; END_IF ;
  ELSIF XIN1 > (XIN2 + EPS) THEN Q := 1 ;
  END_IF ;
END_FUNCTION_BLOCK
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

F.6.7 *Function block LIMITS_ALARM*

This function block implements a high/low limit alarm with hysteresis on both outputs.



F.6.8 *Structure ANALOG_LIMITS*

This data type implements the declarations of parameters for analog signal monitoring.


```
TYPE ANALOG_LIMITS :
    STRUCT
      ES : REAL ;                    (* High end of signal range *)
      EM : REAL ;                    (* High end of measurement range *)
      HA : REAL ;                    (* High alarm threshold *)
      HW : REAL ;                    (* High warning threshold *)
      NV : REAL ;                    (* Nominal value *)
      EPS : REAL ;                   (* Hysteresis *)
      LW : REAL ;                    (* Low warning threshold *)
      LA : REAL ;                    (* Low alarm threshold *)
      LM : REAL ;                    (* Low end of measurement range *)
      LS : REAL ;                    (* Low end of signal range *)
    END_STRUCT
END_TYPE
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

F.6.9 *Function block ANALOG_MONITOR*


This function block implements analog signal monitoring.



Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

F.6.10 *Function block PID*

This function block implements Proportional + Integral + Derivative control action. The functionality is derived by functional composition of previously declared function blocks.





```
FUNCTION_BLOCK PID
  VAR_INPUT
    AUTO : BOOL ;                        (* 0 - manual , 1 - automatic *)
    PV : REAL ;                          (* Process variable *)
    SP : REAL ;                          (* Set point *)
    X0 : REAL ;                          (* Manual output adjustment - *)
                                         (* Typically from transfer station *)
    KP : REAL ;                          (* Proportionality constant *)
    TR : REAL ;                          (* Reset time *)
    TD : REAL ;                          (* Derivative time constant *)
    CYCLE : TIME ;                       (* Sampling period *)
  END_VAR
  VAR_OUTPUT XOUT : REAL ; END_VAR
  VAR ERROR : REAL ;                     (* PV - SP *)
    ITERM : INTEGRAL ;                   (* FB for integral term *)
    DTERM : DERIVATIVE ;                 (* FB for derivative term *)
  END_VAR
  ERROR := PV - SP ;
  (*** Adjust ITERM so that XOUT := X0 when AUTO = 0 ***)
  ITERM (RUN := AUTO, R1 := NOT AUTO, XIN := ERROR,
        X0 := TR * (X0 - ERROR), CYCLE := CYCLE) ;
  DTERM (RUN := AUTO, XIN := ERROR, CYCLE := CYCLE) ;
  XOUT := KP * (ERROR + ITERM.XOUT/TR + DTERM.XOUT*TD) ;
END_FUNCTION_BLOCK
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

F.6.11 *Function block DIFFEQ*

This function block implements a general difference equation.




```
FUNCTION_BLOCK DIFFEQ
  VAR_INPUT
    RUN : BOOL ;                              (* 1 = run, 0 = reset *)
    XIN : REAL ;
    A : ARRAY[1..20] OF REAL ;                (* Input coefficients *)
    M : INT ;                                 (* Length of input history *)
    B : ARRAY[0..19] OF REAL ;                (* Output coefficients *)
    N : INT ;                                 (* Length of output history *)
  END_VAR


  VAR_OUTPUT XOUT : REAL := 0.0 ; END_VAR
  VAR                    (* Note: Manufacturer may specify other array sizes *)
    XI : ARRAY [0..128] OF REAL ;             (* Input history *)
    XO : ARRAY [0..128] OF REAL ;             (* Output history *)
    I : INT ;
  END_VAR

  XO[0] := XOUT ; XI[0] := XIN ;
  XOUT := B[0] * XIN ;
  IF RUN THEN
    FOR I := M TO 1 -1 DO
        XOUT := XOUT + A[I] * XO[I] ; XO[I] := XO[I-1] ;
    END_FOR ;
    FOR I := N TO 1 -1 DO
        XOUT := XOUT + B[I] * XI[I] ; XI[I] := XI[I-1] ;
    END_FOR ;
  ELSE
    FOR I := 1 TO M DO XO[I] := 0.0 ; END_FOR ;
    FOR I := 1 TO N DO XI[I] := 0.0 ; END_FOR ;
  END_IF ;
END_FUNCTION_BLOCK
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

F.6.12 *Function block RAMP*

This function block implements a time-based ramp.




```
FUNCTION_BLOCK RAMP
  VAR_INPUT
    RUN : BOOL ;                          (* 0 - track X0, 1 - ramp to/track X1 *)
    X0,X1 : REAL ;
    TR : TIME ;                           (* Ramp duration *)
    CYCLE : TIME ;                        (* Sampling period *)
  END_VAR

  VAR_OUTPUT
    BUSY : BOOL ;                         (* BUSY = 1 during ramping period *)
    XOUT : REAL := 0.0 ;
  END_VAR

  VAR XI : REAL ;                         (* Initial value *)
    T : TIME := T#0s ;                    (* Elapsed time of ramp *)
  END_VAR


  BUSY := RUN ;
  IF RUN THEN
    IF T >= TR THEN BUSY := 0 ; XOUT := X1 ;
    ELSE XOUT := XI + (X1-XI) * TIME_TO_REAL(T) / TIME_TO_REAL(TR) ;
        T := T + CYCLE ;
    END_IF ;
  ELSE XOUT := X0 ; XI := X0 ; T := t#0s ;
  END_IF ;
END_FUNCTION_BLOCK
```

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

F.6.13 *Function block TRANSFER*

This function block implements a manual transfer station with bumpless transfer.




```
FUNCTION_BLOCK TRANSFER
  VAR_INPUT
    AUTO : BOOL ;                          (* 1 - track X0, 0 - ramp or hold *)
    XIN : REAL ;                           (* Typically from PID function block *)
    FAST_RATE, SLOW_RATE : REAL ;          (* Up/down ramp slopes *)
    FAST_UP, SLOW_UP,                      (* Typically pushbuttons *)
    FAST_DOWN, SLOW_DOWN : BOOL ;
    CYCLE : TIME ;                         (* Sampling period *)
  END_VAR

  VAR_OUTPUT XOUT : REAL ; END_VAR
  VAR XFER_RAMP : INTEGRAL ;
    RAMP_RATE : REAL ;
  END_VAR

  RAMP_RATE := 0.0 ;
  IF NOT AUTO THEN
    IF FAST_UP THEN RAMP_RATE := FAST_RATE ; END_IF  ;
    IF SLOW_UP THEN RAMP_RATE := RAMP_RATE + SLOW_RATE ; END_IF ;
    IF FAST_DOWN THEN RAMP_RATE := RAMP_RATE - FAST_RATE ; END_IF ;
    IF SLOW_DOWN THEN RAMP_RATE := RAMP_RATE - SLOW_RATE ; END_IF ;
  END_IF ;
  XFER_RAMP (RUN := 1, CYCLE := CYCLE, R1 := AUTO,
             XIN := RAMP_RATE, X0 := XIN) ;
  XOUT := XFER_RAMP.XOUT ;
END_FUNCTION_BLOCK
```

F.7 Program GRAVEL

A control system is to be used to measure an operator-specified amount of gravel from a silo into an intermediate bin, and to convey the gravel after measurement from the bin into a truck.

The quantity of gravel to be transferred is specified via a thumbwheel with a range of 0 to 99 units. The amount of gravel in the bin is indicated on a digital display.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

For safety reasons, visual and audible alarms must be raised immediately when the silo is empty. The signalling functions are to be implemented in the control program.

A graphic representation of the control problem is shown in figure F.2, while the variable declarations for the control program are given in figure F.3.

As shown in figure F.4, the operation of the system consists of a number of major states, beginning with filling of the bin upon command from the FILL push button. After the bin is filled, the truck loading sequence begins upon command by the LOAD pushbutton when a truck is present on the ramp. Loading consists of a "run-in" period for starting the conveyor, followed by dumping of the bin contents on to the conveyor. After the bin has emptied, the conveyor "runs out" for a predetermined time to assure that all gravel has been loaded to the truck. The loading sequence is stopped and re-initialized if the truck leaves the ramp or if the automatic control is stopped by the OFF push button.

Figure F.5 shows the OFF/ON sequence of automatic control states, as well as the generation of display blinking pulses and conveyor motor gating when the control is ON.

Bin level monitoring, operator interface and display functions are defined in figure F.6.

A textual version of the body of program GRAVEL is given in figure F.7, using the ST language with SFC elements.

An example configuration for program GRAVEL is given in figure F.8.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale




Figure F.2 – Gravel measurement and loading system

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

```
PROGRAM GRAVEL                          (* Gravel measurement and loading system *)
  VAR_INPUT
    OFF_PB : BOOL ;
    ON_PB : BOOL ;
    FILL_PB : BOOL ;
    SIREN_ACK : BOOL ;
    LOAD_PB : BOOL ;                    (* Load truck from bin *)
    JOG_PB : BOOL ;
    LAMP_TEST : BOOL ;
    TRUCK_ON_RAMP : BOOL ;              (* Optical sensor *)
    SILO_EMPTY_LS : BOOL ;
    BIN_EMPTY_LS : BOOL ;
    SETPOINT : BYTE ;                   (* 2-digit BCD *)
  END_VAR

  VAR_OUTPUT
    CONTROL_LAMP : BOOL ;
    TRUCK_LAMP : BOOL ;
    SILO_EMPTY_LAMP : BOOL ;
    CONVEYOR_LAMP : BOOL ;
    CONVEYOR_MOTOR : BOOL ;
    SILO_VALVE : BOOL ;
    BIN_VALVE : BOOL ;
    SIREN : BOOL ;
    BIN_LEVEL : BYTE ;
  END_VAR

  VAR
    BLINK_TIME : TIME ;                 (* BLINK ON/OFF time *)
    PULSE_TIME : TIME ;                 (* LEVEL_CTR increment interval *)
    RUNOUT_TIME : TIME ;                (* Conveyor running time after loading *)
    RUN_IN_TIME : TIME ;                (* Conveyor running time before loading *)
    SILENT_TIME : TIME ;                (* Siren silent time after SIREN ACK *)
    OK_TO_RUN : BOOL ;                  (* 1 = Conveyor is allowed to run *)
    (* Function blocks *)
    BLINK : TON ;                       (* Blinker OFF period timer / ON output *)
    BLANK : TON ;                       (* Blinker ON period timer / blanking pulse *)
    PULSE : TON ;                       (* LEVEL CTR pulse interval timer *)
    SIREN_FF : RS ;
    SILENCE_TMR : TP ;                  (* Siren silent period timer *)
  END_VAR
  VAR RETAIN LEVEL_CTR : CTU ; END VAR
  (* Program Body *)
END_PROGRAM
```

Figure F.3 – Declarations for program GRAVEL

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale




Figure F.4 – SFC of program GRAVEL body

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale




Figure F.5 – Body of program GRAVEL
Control state sequencing and monitoring

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale




Figure F.6 – Body of action MONITOR_ACTION in FBD language

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

```
(* Major operating states *)
INITIAL_STEP START : END_STEP
TRANSITION FROM START TO FILL_BIN := FILL_PB & CONTROL.X ; END_TRANSITION
STEP FILL_BIN : SILO_VALVE(N) ; END_STEP
TRANSITION FROM FILL_BIN TO START := NOT FILL_PB OR NOT CONTROL.X ; END_TRANSITION
TRANSITION FROM FILL_BIN TO LOAD_WAIT := LEVEL_CTR.Q ;
END_TRANSITION

STEP LOAD_WAIT : END_STEP
TRANSITION FROM LOAD_WAIT TO RUN_IN := LOAD_PB & OK_TO_RUN ; END_TRANSITION
STEP RUN_IN : END_STEP
TRANSITION FROM RUN_IN TO LOAD_WAIT := NOT OK_TO_RUN ;
END_TRANSITION

TRANSITION FROM RUN_IN TO DUMP_BIN := RUN_IN.T > RUN_IN_TIME ;
END_TRANSITION

STEP DUMP_BIN : BIN_VALVE(N) ; END_STEP
TRANSITION FROM DUMP_BIN TO LOAD_WAIT := NOT OK_TO_RUN ;
END_TRANSITION

TRANSITION FROM DUMP_BIN TO RUNOUT := BIN_EMPTY_LS ;
END_TRANSITION

STEP RUNOUT : END_STEP
TRANSITION FROM RUNOUT TO LOAD_WAIT := NOT OK_TO_RUN ;
END_TRANSITION

TRANSITION FROM RUNOUT TO START := RUNOUT.T >= RUNOUT_TIME ;
END_TRANSITION
```

```
(* Control state sequencing *)
INITIAL_STEP CONTROL_OFF : END_STEP
TRANSITION FROM CONTROL_OFF TO CONTROL := ON_PB & NOT OFF_PB ; END_TRANSITION
STEP CONTROL : CONTROL_ACTION(N) ; END_STEP
ACTION CONTROL_ACTION :
   BLINK(EN := CONTROL.X & NOT BLANK.Q, PT := BLINK_TIME) ;
   BLANK(EN := BLINK.Q, PT := BLINK_TIME) ;
   OK_TO_RUN := CONTROL.X & TRUCK_ON_RAMP ;
   CONVEYOR_MOTOR := OK_TO_RUN & OR(JOG_PB, RUN_IN.X, DUMP_BIN.X, RUNOUT.X) ;
END_ACTION
TRANSITION FROM CONTROL TO CONTROL_OFF := OFF_PB ;
END_TRANSITION

(* Monitor logic *)
INITIAL_STEP MONITOR : MONITOR_ACTION(N) ; END_STEP
ACTION MONITOR_ACTION :
   CONVEYOR_LAMP := CONVEYOR_MOTOR & BLINK.Q ;
   CONTROL_LAMP := CONTROL.X OR LAMP_TEST ;
   TRUCK_LAMP := TRUCK_ON_RAMP OR LAMP_TEST ;
   SILO_EMPTY_LAMP := BLINK.Q & SILO_EMPTY_LS OR LAMP_TEST ;
   SILENCE_TMR(EN := SIREN_ACK, PT := SILENT_TIME) ;
   SIREN_FF(S := SILO_EMPTY_LS, R1 := SILENCE_TMR.Q) ;
   SIREN := SIREN_FF.Q1 ;
   PULSE(EN := FILL_BIN.X & NOT PULSE.Q, PT := PULSE_TIME) ;
   LEVEL_CTR(EN := BIN_EMPTY_LS, CU := PULSE.Q, PV := BCD_TO_INT(SETPOINT)) ;
   BIN_LEVEL := INT_TO_BCD(LEVEL_CTR.CV) ;
END_ACTION
```

Figure F.7 – Body of program GRAVEL in textual SFC representation using ST language elements

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

```
CONFIGURATION GRAVEL_CONTROL
   RESOURCE PROC1 ON PROC_TYPE_Y
     PROGRAM G : GRAVEL
       (* Inputs *)
        (OFF_PB := %I0.0,
        ON_PB := %I0.1,
        FILL_PB := %I0.2,
        SIREN_ACK := %I0.3,
        LOAD_PB := %I0.4,
        JOG_PB := %I0.5,
        LAMP_TEST := %I0.7,
        TRUCK_ON_RAMP := %I1.4,
        SILO_EMPTY_LS := %I1.5,
        BIN_EMPTY_LS := %I1.6,
        SETPOINT := %IB2,
       (* Outputs *)
        CONTROL_LAMP => %Q4.0,
        TRUCK_LAMP => %Q4.2,
        SILO_EMPTY_LAMP => %Q4.3,
        CONVEYOR_LAMP => %Q5.3,
        CONVEYOR_MOTOR => %Q5.4,
        SILO_VALVE => %Q5.5,
        BIN_VALVE => %Q5.6,
        SIREN => %Q5.7,
        BIN_LEVEL => %B6) ;
   END_RESOURCE
END_CONFIGURATION
```

Figure F.8 – Example configuration for program GRAVEL

F.8 Program AGV

As illustrated in figure F.9, a program is to be devised to control an automatic guided vehicle (AGV). The AGV is to travel between two extreme positions, left (indicated by limit switch LEFT_LS) and right (indicated by limit switch RIGHT_LS). The normal position of the AGV is on the left.

The AGV is to execute one cycle of left-to-right and return motion when the operator actuates pushbutton SINGLE_PB, and two cycles when the operator actuates pushbutton DOUBLE_PB. It is also possible to pass from a single to a double cycle by actuating push-button DOUBLE_PB during a single cycle. Finally, non-repeat locking is to be provided if either SINGLE_PB or DOUBLE_PB remains actuated.

Figure F.10 illustrates the declaration of program AGV, while figure F.11 shows a typical configuration for this program. Figure F.12 shows the AGV program body, consisting of a main control sequence and a single-cycle control sequence.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale




Figure F.9 – Physical model for program AGV

```
PROGRAM AGV
                        +----------------------+
                        |         AGV          |
                  BOOL---|SINGLE_PB    FWD_MOTOR|---BOOL
                  BOOL---|DOUBLE_PB    REV_MOTOR|---BOOL
                  BOOL---|LEFT_LS               |
                  BOOL---|RIGHT_LS              |
                        +----------------------+

VAR CYCLE : BOOL; END_VAR
END_PROGRAM
```

Figure F.10 – Graphical/textual declaration of program AGV

```
CONFIGURATION AGV_CONTROL


   RESOURCE AGV_PROC: SMALL_PC

                  AGV_1
            +----------------------+
            |         AGV          |
      %IX1---|SINGLE_PB  FWD_MOTOR|---%QX1
      %IX2---|DOUBLE_PB  REV_MOTOR|---%QX2
      %IX3---|LEFT_LS               |
      %IX4---|RIGHT_LS              |
            +----------------------+
```

Figure F.11 – A graphical configuration of program AGV

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale



(concluded overleaf)

Figure F.12 – Body of program AGV

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale




Figure F.12 – Body of program AGV *(concluded)*

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

Annex G
(informative)

Index

Primary references for delimiters and keywords are given in annex C. Page numbers in bold face type indicate where the definition of a term is to be found.

absolute time, **10**, 28

access path, **10**, 102-105
  communication, 16-19
  keyword, 40
  loading/deletion, 16
  programming, 19-21

action, **10**, 77, 83,92, 115, 117
  control, 88-92
  qualifiers, 88

action block, **10**, 83, 86-88

active association, 88-89

activity flow, 125

aggregate, **10**

argument, **10**, 44, 61, 117-120

array, **10**, 44
  access path, 104
  declaration, 33-34, 41
  initialization, 33, 42-43
  location assignment, 41
  usage, 10, 124

assignment, **10**, 45-47, 80
  FOR loop variable values, 123
  function block parameters, 62
  of input values, 122
  operator, 33, 80
  statement, 121, 122

based number, **10**, 26-27

basic code table, 24

bistable function block, **10**, 70-71

bit string, **10**
  comparison, 55
  data types, 30-32
  functions, 55-56
  initial value assignment, 42-43
  variable declaration, 40-41

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

body, **11**
function, 46, **47**, 48, 122
function block, 61-76
program organization unit, 126

Boolean
AND, in ladder diagrams, 131
data type, 31-32
default initial value, 34
edge detection, 63, 72
expression, 80, 119, 123, 124
functions, 55-56, 88
input, action control, 88-89
input, RETURN, 128
literals, 27
negation, 45, 116
operators, 116-117, 120
OR, LD, vs. FBD, 134
output, 128
signal, 128
values, power flow, 130
variable, 37, 78, 79, 83, 84, 86-88, 105, 123, 128
variable, in ladder diagrams, 131, 133

byte (data element size), 37

BYTE (data type), 30-32, 34

call, **11**
operator, 117, 118

case (of characters), 24, 25, 29

CASE statement, 121-123

character code, 24, 26, 27, 58

character set, 9, 24-25, 78, 97, 124, 132

character string, **11**
character positions in, 58
comparison 58
data type, 30-32
functions, 58-59
initialization, 42-43
literals, 27
variable declaration, 40-41

cold restart, 39, 41, 43

comment, 11, 26, 115

comparison
bit strings, 55
character strings, 58
functions, 55,59

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

compilation, 11, 23

compliance, 21-23
  action declarations, 83
  EXIT statement, 121
  PC systems, 21-23
  programs, 23-24
  sequential function chart (SFC), 101
  step/action association, 86
  syntax, 23

concatenation
  action blocks, 86, 87
  hierarchical addresses, 36-37
  time data, 60

conditional
  call, 117
  instruction, 116
  jump, 128
  return, 128

configuration, 11, 15-16
  communication, 16-19
  elements, 102-114
  initialization, 16
  programming, 19-21
  starting and stopping, 16

connector, 80, 81, 124, 126

contact, 131-132

counter, 11, 73

data type, 11
  compliance, 23
  declaration, 32-34
  elementary, 30-32
  generic, 31-32, 48-50
  initialization, 34-35
  of an expression, 118-119
  of functions, 47-48
  of input parameters, 47-48
  of internal variables, 47-48
  programming, 19-21
  usage, 35-36

date and time, 11, 74
  data types, 29-32
  default initial values, 34
  functions, 60
  literals, 15, 29-30

decimal number (decimal literal), 26-27, 125

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS

Not for Resale

NEMA IA*2.3 94 ■ 6470247 0506566 871 ■

declaration, **11, 20-21**
access paths, 103-105
actions, 83-85, 88
configurations, 102-114
data types, 32-34
function blocks, 61-69
functions, 47-48, 122
programs, 76
resources, 103-105
tasks, 105-114
variables, 39-40, 133

default value, 48
FOR increment, 123
function block inputs, 63
of data types, 33-35
of variables, 38-39, 42-43
task interval, 106

delimiter, **11**
comments, 26
LD network, 130
network label, 125
time literals, 28-30

direct representation, **11**, 36-37, 76, 102-104
in programs, 76
initial value assignment, 42-43
variable declaration, 39-41

double word, **11**, 34-36
size prefix, 36-37

duration
data type (TIME), 34-36
literals, 28-29
of action qualifiers, 88
of step activity, 93

edge detection, 63, 65
function blocks, 72

EN/ENO (enable) variables, 46-47

errors, 48, 79, 89, 93, 122, 124
documentation, 23
handling, 23-24, 47
reporting, 23

evaluation, **11**
of assignment statements, 122
of CASE expressions, 123
of expressions, 118-120
of function blocks, 106-107
of functions, 54, 120, 122
of instructions, 115-118

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

of language elements, 107
of network elements, 126-127
of networks, 61, 126-127, 131, 134
of programs, 107
of transitions, 94, 95, 96

execution
of actions, 77, 88
of EXIT statements, 124
of function blocks, 61, 72, 105-106
of functions, 44, 46-47
of instructions, 115-117
of iteration statements, 123-124
of loop elements, 127-128
of programs, 128
of selection statements, 123

execution control element, **11**, 77, 105, 126-129, 131

extensions, 23, 24, 26, 36-37
documentation, 23
processing, 23
usage, 24

falling edge, **12**, 63, 65, 72

feedback
path, 127-128
variable, 127

FOR statement, 123-124

function, **12**, 44-60
compliance, 23
control statements, 122-123
extensible, 51
in LD language, 131
overloaded, 48-50, 53, 55
programming, 19-21
return value, 122
signal flow, 125
typing, 48

function block, **12**, 15-16, 61-76
action control, 88-92
communication, 16-19, 76
compliance, 23
control statements, 122-123
in LD language, 131
instance, **12**, 105-107
operation, 73-74
programming, 19-21
retentive, 78
SFC structuring, 77
signal flow, 125
type, **12**, 61

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

function block diagram (FBD), **12**, 15, 134
  action blocks in, 87
  execution control, 128-129
  loops in, 127-128
  signal flow in, 125

generic data types, **12**, 31-32, 48-50

global variable, **12**, 102
  communication, 17-19
  declaration, 39-40, 76, 103-105
  function block instance, 61
  initial value assignment, 42-43
  initialization, 16
  loading/deletion, 16
  programming, 19-21

hierarchical addressing, **12**, 37

identifier, **21**, 25, 47, 61, 77, 80, 120, 124, 125

implementation-dependent
  feature, 23, 38, 41, 123
  parameter, 22, 33, 37, 38, 51, 73, 93
  side effects, 62

indicator
  variable, 87

initial
  state, 78
  step, 78, 79, 92

initial value, **12**
  assignment, 42-43
  default, 34-35
  feedback variable, 127
  FOR loop variable, 123
  function block variables, 63, 122

initialization, 16, 38-39
  function blocks, 62-69, 92
  programs, 76, 92
  SFC networks, 92
  steps, 78-79

input, **12**
  declaration, 39-40, 47-48, 62-69
  dynamic, 63
  extensible, 51
  initialization, 39
  instance name, 61
  location prefix, 36-37
  negated, 45
  operators (IL language), 118
  overloaded, 48-50

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

NEMA IA*2.3 94 ■ 6470247 0506569 580 ■

parameter, **12**, 44-45, 61, 122
parameter, read/write privileges, 62
program, 104
string, 52
variable, 61, 76, 104, 131

input/output
parameter, 62-69
variable, 61

instance, **12**
function block, **12**, 61, 62, 65, 105-107
name, **12**, 61, 62, 65

instantiation, **12**
action control, 89
function block, 76
program, 76

instruction, 80, 83, 115-118

integer
data types, 30-32, 123
literal, **13**, 26-27, 125

invocation, **13**
by tasks, 105
function block, 61-63, 117-118, 121-123
of actions, 77
of functions, 44-46, 117-120
of non-PC language elements, 20
recursive, 44
return from, 128

iteration, 121-124

keyword, **13**, 26
Boolean literals, 27, 80
data types, 30-32
ELSE statement, 123
FOR statement, 123
function block declaration, 63
function declaration, 47
IF statement, 123
program declaration, 76
REPEAT statement, 124
time literals, 28-30
transition, 80
variable declaration, 39-40
WHILE statement, 124

label, **13**, 115, 117
connector, 124
network, 125, 126, 128

ladder diagram, 130-133
evaluation, 126-128
execution control, 128-129
network, 80

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

NEMA IA*2.3 94 ■ 6470247 0506570 2T2 ■

language element, 9, **13**, 15-16
compliance, 22-23
programming, 19-21, 76

library, 19-21, 103

literal, **13**, 26-30, 115, 119, 130

logical location, 13, 36-37, 39-40

long real, 13, 29-32

long word, 13, 29-32

memory, 131

memory (user data storage), **13**
allocation, 40-41, 133
direct representation, 36-37
initial value assignment, 42-43
initialization, 38-39

named element, 13, 38, 122, 124

network, 88, **125**
direction of flow, 125
evaluation, 61, 126-128, 131-134
function block diagram (FBD), 80-83
label, 127
ladder diagram (LD), 80, 131
sequential function chart (SFC), 78, 91, 92

numeric literals, 26-27

off-delay, **13**, 74-75

on-delay, **13**, 74-75

operand, **13**
function as, 44
of an expression, 119-120
of an instruction, 115-117

operator, **13**
assignment, 33, 80, 122
Instruction List, 115-118
overloaded, 48-49
precedence, 119, 120
Structured Text (ST), 119-120
symbols, 54, 56-58

output, **13**
action control, 88
declaration, 62-69
function block, 121, 134
graphical representation, 45, 61
location prefix, 36-37

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

negated, 45
network, 134
parameter(s), **13**, 45, 61
parameter, read/write privileges, 62
program, 104
string, 52
typed, 49
values, 61
variable declaration, 39-40
variables, 61, 76, 104, 131

overloading, **13**, 31, 48-49
of operators, 117, 119

parameter
actual, 45, 50, 131
formal, 45-46, 50, 61, 131
formal, declaration, 47-48, 62-69, 76
input, **12**, 44, 61, 122
output, **13**, 45, 61
passing, 39, 63

parentheses, 24-26, 33, 37, 42, 80, 116-117, 120, 122

power flow, **14**, 87, 125, 128, 130, 131

power rails, 125, 128, 130

pre-emptive scheduling, 106-114

priority
of tasks, 106-114
of transitions, 93-96

program, 15-17, 76
communication, 16-19
compliance, 23-24
declaration, 39, 61, 76, 104
retentive, 78
scheduling, 106-114
semaphore use in, 70-71
SFC structuring, 77

program organization unit, **14**, 44, 61
compliance, 21-23
declaration, 39, 44
initial state, 78
jumps in, 128
networks in, 125-127, 131, 134
scheduling, 106-114
SFC partitioning of, 77
state, 77

programming, **14**, 15-16, 19-21, 130, 134

real literal, **14**, 26-27

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

resource, **14**, 15-17, 76
communication, 19
declaration, 103-105
global variables in, 104
initialization, 16, 38
programming, 19, 21
starting and stopping, 16, 106

retentive data, **14**
declaration, 38-41, 76, 133
in function blocks, 63
in steps, 78
initial value assignment, 42-43
initialization, 38-39
keyword, 39-40
type assignment, 40-41

return, **14**, 117, 121, 122, 128

rising edge, **14**, 63, 65, 72, 74, 105-106

rung, 83, 130

scope, **14**
global, 104
of actions, 83
of declarations, 39
of function block instances, 61
of networks, 125
of steps, 78
of transitions, 80

selection
functions, 55, 57, 60
statements, 122-123

semantics, **14**
Instruction List (IL), 115-118
Structured Text (ST), 118-124

semigraphic representation, 9, **14**, 62, 105, 124-126

sequential function chart (SFC)
activity flow, 125
compliance, 101
convergence, simultaneous, 93
divergence, selection, 94-96
divergence, simultaneous, 93
elements, 15, 70-71, 77-92, 115, 123-124
elements, compatibility of, 101
errors, 93, 99-100
evolution, 92-100
programming, 19-20

signal flow, 116, 134

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

single data element, **14**, 35-37

step, **14**, 77-79
  action association, 86
  activation, 93
  active, 77-79, 88, 92-93
  deactivation, 78, 85, 93
  duration, 93
  elapsed time, 78, 79
  flag, 78-79
  inactive, 77, 79
  initial, 78, 79, 92
  initialization, 78
  retentive, 78
  state, 77, 78, 92-96, 98

structured data type, **14**, 61
  declaration, 32-34
  initialization, 33-35
  usage, 35-36

structured variable, **38**, 44
  access path, 104
  assignment, 122
  declaration, 41
  initialization, 42-43
  step elements, 77-78

subscripting, **14**, 37-38
  array initialization, 42

symbolic representation, **14**, 36, 40

synchronization
  interprocess, 124
  of function blocks, 105-114

syntax, 15
  documentation, 23
  step/transition, 93

task, **14**, 15-16, 105-114
  declaration, 103-105
  programming, 19-21

TIME data type, 30-32, 78, 79, 88
  default initial value, 34
  function blocks, 74-75
  functions, 60

time literal, **15**, 28-30

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

NEMA IA*2.3 94 ■ 6470247 0506574 948 ■

time of day
data types, 30-32
default initial value, 34
functions, 60
keywords, 29-30
literals, 28-30

timer, 13, 74-75

transition, 15, 77, 79-82
clearing, 92-93, 98
clearing time, 93
condition, 77, 80-82, 83, 93, 94, 95
enabled, 93,
evaluation, 94-96
priority, 94-96
symbol, 93

type conversion
functions, 50--52

underline character, 25, 27, 49

unsigned integer, 15, 125
data types, 31

variable, 36-43
declaration, 47-48, 62-69
usage, 35-36

WAIT function, 83, 124

warm restart, 38

wired OR, 15, 134

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

Annex H
(informative)

Software compliance testing

This topic is under consideration for future standardization.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS Not for Resale

NEMA STANDARDIZATION BACKGROUND

The purpose of NEMA standards, their classification, and status are set forth in certain clauses of the NEMA *Standardization Policies and Procedures* manual and are referenced below:

Purpose of Standards

National Electrical Manufacturers Association Standards are adopted in the public interest and are designed to eliminate misunderstandings between the manufacturer and the purchaser and to assist the purchaser in selecting and obtaining the proper product for their particular needs. Existence of a National Electrical Manufacturers Association Standard does not in any respect preclude any member or nonmember from manufacturing or selling products not conforming to the standard.

Definition of a Standard

A standard of the National Electrical Manufacturers Association defines a product, process, or procedure with reference to one or more of the following: nomenclature, composition, dimensions, tolerances, safety, operating characteristics, performance, rating, testing, and the service for which they are designed.

(Standardization Policies and Procedures, p. 1)

Dimensions

Where dimensions are given for interchangeability purposes, alternate dimensions satisfying the other provisions of the Standards Publication may be capable of otherwise equivalent performance.

(Standardization Policies and Procedures, p. 6)

Categories of Standards

National Electrical Manufacturers Association Standards are of three classes, which have received the affirmative vote of at least two-thirds of the Subdivision votes cast in the affirmative or negative:

1. NEMA Standard, which relates to a product, process, or procedure commercially standardized and subject to repetitive manufacture.
2. Suggested Standard for Future Design, which may not have been regularly applied to a commercial product, but which suggests a sound engineering approach to future development.
3. Adoptive Standard, which is adopted in whole or in part from the standards of another organization, either domestic, regional, or international.

(Standardization Policies and Procedures, pp. 5)

Authorized Engineering Information

Authorized Engineering Information consists of explanatory data and other engineering information of an informative character not falling within the classification of NEMA Standard or Suggested Standard for Future Design, which standard has received the affirmative vote of at least two-thirds of the Subdivision votes cast in the affirmative or negative.

(Standardization Policies and Procedures, pp. 5)

Identification of Status

Standards in NEMA Standards Publications are identified as "NEMA Standard," "Suggested Standard for Future Design," or "Adoptive Standard." These indicate the status of the standard. A statement incorporating the auxiliary verb "shall" indicates that compliance with a requirement is mandatory for compliance with the standard. These classes of standards are identified in the foreword or throughout the text.

The material identified as "Authorized Engineering Information" is designated similarly. Statements incorporating other auxiliary verbs such as "should," "may," etc. refer to the authorized engineering information and not to procedures required for compliance with the standard.

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale

INDUSTRIAL AUTOMATION SECTION OF THE NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION MEMBER COMPANIES

ABB Robotics, Inc.
Industrial Automation
New Berlin, WI 53151-2840

AEG Automation Systems Corporation
Drive Control Systems Division
Canonsburg, PA 15317-0441

AEG Schnider Automation, Inc
No. Andover, MA 01845

Allen-Bradley Company
Automation Group
Milwaukee, WI 53204-2086

Amp Incorporated
Harrisburg, PA 17111-3608

AstroSystems, Inc.
Lake Success, NY 11042

AT&T
Engineering Division
Berkeley Heights, NJ 07922

Baldor Electric Company
Fort Smith, AR 72902

BDM International, Inc.
Gaithersburg, MD 20878

Best Power Technologies, Inc.
Framingham, MA 01701

Robert Bosch Corporation
Collinsville, CT 06022-1260

CEGELEC Automation, Inc.
Macon, GA 31206

Danaher Controls
Gurnee, IL 60031

Eaton Corporation
Electrical Components Division
Arden, NC 28704

EBT, Inc.
Columbians, AL 35051

Echlon
Palo Alto, CA 94304

Furnas Electric Company
Batavia, IL 60510

GE Fanuc Automation
Charlottesville, VA 22906

Gettys/AEG
Racine, WI 53404

R & D Engineer
Giddings & Lewis, Inc
Fond du Lac, WI 54936-1658

Hobart Lasers & Advanced Systems
Troy, OH 45373

Honeywell, Inc.
Industrial Automation & Control
Phoenix, AZ 85023

Klockner-Moeller Corporation
Franklin, MA 02038

Kollmorgen Industrial Drives
Motion Technologies Group
Radford, VA 24141

The Lincoln Electric Company
Cleveland, OH 44117-1199

Measurex Corporation
Cupertino, CA 95014-5991

Micro Mo Electronics, Inc.
Advanced Research and Planning
St Petersburg, FL 33701

NAMCO Controls Corporation
A Sub of Acme-Cleveland Corp.
Mentor, OH 44060

Omron Electronics, Inc.
Factory Automation Division
Schaumburg, IL 60173

Peerless-Winsmith, Inc.
Warren, OH 44485

Phoenix Contact, Inc.
Interbus Systems Group
Harrisburg, PA 17111-0100

Pittman, A Division of
Penn Engineering & Mfg Corporation
Harleysville, PA 19438

Reliance Electric Company
Research Center
Cleveland, OH 44117

Rexroth Corporation
Indramat Division
Wood Dale, IL 60191

Siemens Industrial Automation, Inc.
Johnson City, TN 37601

Square D Company
Palatine, IL 60067-7399

The Superior Electric Company
Bristol, CT 06010

Texas Instruments, Inc.
Motor Controls Department
Attleboro, MA 02703

Toshiba International Corporation
Houston, TX 77041

Weidmuller, Inc.
Richmond, VA 23236

Westinghouse Electric Corporation
Electrical Components Division
Arden, NC 28704

Westinghouse Electric Corporation
Electrical Components Division
Arden, NC 28704

Zenith Controls, Inc.
Chicago, IL 60609

Copyright National Electrical Manufacturers Association
Provided by IHS under license with NEMA
No reproduction or networking permitted without license from IHS
Not for Resale