
ISO/IEC 29341-8-13

Edition 1.0 2008-11

INTERNATIONAL STANDARD

Information technology – UPnP Device Architecture – Part 8-13: Internet Gateway Device Control Protocol – Radius Client Service



ISO/IEC 29341-8-13:2008(E)

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS

Not for Resale



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2008 ISO/IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about ISO/IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembé
CH-1211 Geneva 20
Switzerland
Email: inmail@iec.ch
Web: www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

- Catalogue of IEC publications: www.iec.ch/searchpub

The IEC on-line Catalogue enables you to search by a variety of criteria (reference number, text, technical committee,…). It also gives information on projects, withdrawn and replaced publications.

- IEC Just Published: www.iec.ch/online_news/justpub

Stay up to date on all new IEC publications. Just Published details twice a month all new publications released. Available on-line and also by email.

- Electropedia: www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 20 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary online.

- Customer Service Centre: www.iec.ch/webstore/custserv

If you wish to give us your feedback on this publication or need further assistance, please visit the Customer Service Centre FAQ or contact us:

Email: csc@iec.ch
Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS
Not for Resale

ISO/IEC 29341-8-13

Edition 1.0 2008-11

INTERNATIONAL STANDARD

Information technology – UPnP Device Architecture – Part 8-13: Internet Gateway Device Control Protocol – Radius Client Service

INTERNATIONAL ELECTROTECHNICAL COMMISSION

PRICE CODE E

ICS 35.200

ISBN 2-8318-1010-0

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS

Not for Resale

CONTENTS

FOREWORD 3
ORIGINAL UPNP DOCUMENTS (informative) 5
1. Overview and Scope 7
2. Service Modeling Definitions 7
2.1. ServiceType 7
2.2. State Variables 7
2.2.1. NumberOfAuthServerEntries 7
2.2.2. AuthServerIPAddress 8
2.2.3. AuthServerPortNumber 8
2.2.4. AuthServerSharedSecret 8
2.3. Eventing and Moderation 8
2.3.1. Event Model 8
2.4. Actions 8
2.4.1. GetGenericAuthServerEntry 9
2.4.2. GetSpecificAuthServerEntry 9
2.4.3. AddAuthServerEntry 10
2.4.4. DeleteAuthServerEntry 11
2.4.5. FactoryDefaultReset 11
2.4.6. ResetAuthentication 11
2.4.7. Non-Standard Actions Implemented by a UPnP Device Vendor 12
2.4.8. Common Error Codes 12
2.5. Theory of Operation 12
2.5.1. Operation of the RADIUS Client 12
3. XML Service Description 13
4. Test 15

LIST OF TABLES

Table 1: State Variables 7
Table 2: Event Moderation 8
Table 3: Actions 8
Table 4: Arguments for GetGenericAuthServerEntry 9
Table 5: Arguments for GetSpecificAuthServerEntry 9
Table 6: Arguments for AddAuthServerEntry 10
Table 7: Arguments for DeleteAuthServerEntry 11
Table 8: Common Error Codes 12

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

INFORMATION TECHNOLOGY – UPNP DEVICE ARCHITECTURE –

Part 8-13: Internet Gateway Device Control Protocol – Radius Client Service

FOREWORD

1) ISO (International Organization for Standardization) and IEC (International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards. Their preparation is entrusted to technical committees; any ISO and IEC member body interested in the subject dealt with may participate in this preparatory work. International governmental and non-governmental organizations liaising with ISO and IEC also participate in this preparation.

2) In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1. Draft International Standards adopted by the joint technical committee are circulated to national bodies for voting. Publication as an International Standard requires approval by at least 75 % of the national bodies casting a vote.

3) The formal decisions or agreements of IEC and ISO on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC and ISO member bodies.

4) IEC, ISO and ISO/IEC publications have the form of recommendations for international use and are accepted by IEC and ISO member bodies in that sense. While all reasonable efforts are made to ensure that the technical content of IEC, ISO and ISO/IEC publications is accurate, IEC or ISO cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.

5) In order to promote international uniformity, IEC and ISO member bodies undertake to apply IEC, ISO and ISO/IEC publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any ISO/IEC publication and the corresponding national or regional publication should be clearly indicated in the latter.

6) ISO and IEC provide no marking procedure to indicate their approval and cannot be rendered responsible for any equipment declared to be in conformity with an ISO/IEC publication.

7) All users should ensure that they have the latest edition of this publication.

8) No liability shall attach to IEC or ISO or its directors, employees, servants or agents including individual experts and members of their technical committees and IEC or ISO member bodies for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication of, use of, or reliance upon, this ISO/IEC publication or any other IEC, ISO or ISO/IEC publications.

9) Attention is drawn to the normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.

IEC and ISO draw attention to the fact that it is claimed that compliance with this document may involve the use of patents as indicated below.

ISO and IEC take no position concerning the evidence, validity and scope of the putative patent rights. The holders of the putative patent rights have assured IEC and ISO that they are willing to negotiate free licences or licences under reasonable and non-discriminatory terms and conditions with applicants throughout the world. In this respect, the statements of the holders of the putative patent rights are registered with IEC and ISO.

Intel Corporation has informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

Intel Corporation
Standards Licensing Department
5200 NE Elam Young Parkway
MS: JFS-98
USA – Hillsboro, Oregon 97124

Microsoft Corporation has informed IEC and ISO that it has patent applications or granted patents as listed below:

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

6101499 / US; 6687755 / US; 6910068 / US; 7130895 / US; 6725281 / US; 7089307 / US; 7069312 / US; 10/783 524 /US

Information may be obtained from:

Microsoft Corporation
One Microsoft Way
USA – Redmond WA 98052

Philips International B.V. has informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

Philips International B.V. – IP&S
High Tech campus, building 44 3A21
NL – 5656 Eindhoven

NXP B.V. (NL) has informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

NXP B.V. (NL)
High Tech campus 60
NL – 5656 AG Eindhoven

Matsushita Electric Industrial Co. Ltd. has informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

Matsushita Electric Industrial Co. Ltd.
1-3-7 Shiromi, Chuoh-ku
JP – Osaka 540-6139

Hewlett Packard Company has informed IEC and ISO that it has patent applications or granted patents as listed below:

5 956 487 / US; 6 170 007 / US; 6 139 177 / US; 6 529 936 / US; 6 470 339 / US; 6 571 388 / US; 6 205 466 / US

Information may be obtained from:

Hewlett Packard Company
1501 Page Mill Road
USA – Palo Alto, CA 94304

Samsung Electronics Co. Ltd. has informed IEC and ISO that it has patent applications or granted patents.

Information may be obtained from:

Digital Media Business, Samsung Electronics Co. Ltd.
416 Maetan-3 Dong, Yeongtang-Gu,
KR – Suwon City 443-742

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights other than those identified above. IEC and ISO shall not be held responsible for identifying any or all such patent rights.

ISO/IEC 29341-8-13 was prepared by UPnP Implementers Corporation and adopted, under the PAS procedure, by joint technical committee ISO/IEC JTC 1, *Information technology*, in parallel with its approval by national bodies of ISO and IEC.

The list of all currently available parts of the ISO/IEC 29341 series, under the general title *Universal plug and play (UPnP) architecture*, can be found on the IEC web site.

This International Standard has been approved by vote of the member bodies, and the voting results may be obtained from the address given on the second title page.

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

ORIGINAL UPNP DOCUMENTS
(informative)

Reference may be made in this document to original UPnP documents. These references are retained in order to maintain consistency between the specifications as published by ISO/IEC and by UPnP Implementers Corporation. The following table indicates the original UPnP document titles and the corresponding part of ISO/IEC 29341:

UPnP Document Title	**ISO/IEC 29341 Part**
UPnP Device Architecture 1.0	ISO/IEC 29341-1
UPnP Basic:1 Device	ISO/IEC 29341-2
UPnP AV Architecture:1	ISO/IEC 29341-3-1
UPnP MediaRenderer:1 Device	ISO/IEC 29341-3-2
UPnP MediaServer:1 Device	ISO/IEC 29341-3-3
UPnP AVTransport:1 Service	ISO/IEC 29341-3-10
UPnP ConnectionManager:1 Service	ISO/IEC 29341-3-11
UPnP ContentDirectory:1 Service	ISO/IEC 29341-3-12
UPnP RenderingControl:1 Service	ISO/IEC 29341-3-13
UPnP MediaRenderer:2 Device	ISO/IEC 29341-4-2
UPnP MediaServer:2 Device	ISO/IEC 29341-4-3
UPnP AV Datastructure Template:1	ISO/IEC 29341-4-4
UPnP AVTransport:2 Service	ISO/IEC 29341-4-10
UPnP ConnectionManager:2 Service	ISO/IEC 29341-4-11
UPnP ContentDirectory:2 Service	ISO/IEC 29341-4-12
UPnP RenderingControl:2 Service	ISO/IEC 29341-4-13
UPnP ScheduledRecording:1	ISO/IEC 29341-4-14
UPnP DigitalSecurityCamera:1 Device	ISO/IEC 29341-5-1
UPnP DigitalSecurityCameraMotionImage:1 Service	ISO/IEC 29341-5-10
UPnP DigitalSecurityCameraSettings:1 Service	ISO/IEC 29341-5-11
UPnP DigitalSecurityCameraStillImage:1 Service	ISO/IEC 29341-5-12
UPnP HVAC_System:1 Device	ISO/IEC 29341-6-1
UPnP HVAC_ZoneThermostat:1 Device	ISO/IEC 29341-6-2
UPnP ControlValve:1 Service	ISO/IEC 29341-6-10
UPnP HVAC_FanOperatingMode:1 Service	ISO/IEC 29341-6-11
UPnP FanSpeed:1 Service	ISO/IEC 29341-6-12
UPnP HouseStatus:1 Service	ISO/IEC 29341-6-13
UPnP HVAC_SetpointSchedule:1 Service	ISO/IEC 29341-6-14
UPnP TemperatureSensor:1 Service	ISO/IEC 29341-6-15
UPnP TemperatureSetpoint:1 Service	ISO/IEC 29341-6-16
UPnP HVAC_UserOperatingMode:1 Service	ISO/IEC 29341-6-17
UPnP BinaryLight:1 Device	ISO/IEC 29341-7-1
UPnP DimmableLight:1 Device	ISO/IEC 29341-7-2
UPnP Dimming:1 Service	ISO/IEC 29341-7-10
UPnP SwitchPower:1 Service	ISO/IEC 29341-7-11
UPnP InternetGatewayDevice:1 Device	ISO/IEC 29341-8-1
UPnP LANDevice:1 Device	ISO/IEC 29341-8-2
UPnP WANDevice:1 Device	ISO/IEC 29341-8-3
UPnP WANConnectionDevice:1 Device	ISO/IEC 29341-8-4
UPnP WLANAccessPointDevice:1 Device	ISO/IEC 29341-8-5
UPnP LANHostConfigManagement:1 Service	ISO/IEC 29341-8-10
UPnP Layer3Forwarding:1 Service	ISO/IEC 29341-8-11
UPnP LinkAuthentication:1 Service	ISO/IEC 29341-8-12
UPnP RadiusClient:1 Service	ISO/IEC 29341-8-13
UPnP WANCableLinkConfig:1 Service	ISO/IEC 29341-8-14
UPnP WANCommonInterfaceConfig:1 Service	ISO/IEC 29341-8-15
UPnP WANDSLLinkConfig:1 Service	ISO/IEC 29341-8-16
UPnP WANEthernetLinkConfig:1 Service	ISO/IEC 29341-8-17
UPnP WANIPConnection:1 Service	ISO/IEC 29341-8-18
UPnP WANPOTSLinkConfig:1 Service	ISO/IEC 29341-8-19
UPnP WANPPPConnection:1 Service	ISO/IEC 29341-8-20
UPnP WLANConfiguration:1 Service	ISO/IEC 29341-8-21
UPnP Printer:1 Device	ISO/IEC 29341-9-1
UPnP Scanner:1.0 Device	ISO/IEC 29341-9-2
UPnP ExternalActivity:1 Service	ISO/IEC 29341-9-10
UPnP Feeder:1.0 Service	ISO/IEC 29341-9-11
UPnP PrintBasic:1 Service	ISO/IEC 29341-9-12
UPnP Scan:1 Service	ISO/IEC 29341-9-13
UPnP QoS Architecture:1.0	ISO/IEC 29341-10-1
UPnP QosDevice:1 Service	ISO/IEC 29341-10-10
UPnP QosManager:1 Service	ISO/IEC 29341-10-11
UPnP QosPolicyHolder:1 Service	ISO/IEC 29341-10-12
UPnP QoS Architecture:2	ISO/IEC 29341-11-1
UPnP QOS v2 Schema Files	ISO/IEC 29341-11-2

--`,,```,,,,````-`-`,,`,,`,`,,`---

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

UPnP Document Title	ISO/IEC 29341 Part
UPnP QosDevice:2 Service	ISO/IEC 29341-11-10
UPnP QosManager:2 Service	ISO/IEC 29341-11-11
UPnP QosPolicyHolder:2 Service	ISO/IEC 29341-11-12
UPnP RemoteUIClientDevice:1 Device	ISO/IEC 29341-12-1
UPnP RemoteUIServerDevice:1 Device	ISO/IEC 29341-12-2
UPnP RemoteUIClient:1 Service	ISO/IEC 29341-12-10
UPnP RemoteUIServer:1 Service	ISO/IEC 29341-12-11
UPnP DeviceSecurity:1 Service	ISO/IEC 29341-13-10
UPnP SecurityConsole:1 Service	ISO/IEC 29341-13-11

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

1. Overview and Scope

This service definition is compliant with the UPnP Device Architecture version 1.0.

This service enables the **control and configuration of radius component of IEEE 802.11 Wireless Access Points for the unmanaged network space, namely residential and small office LANs**.

Its intent is to simplify the setup experience, secure wireless networks and provide the framework for diagnosing and monitoring problems on wireless networks.

- This service-type enables remote setup and configuration of the **RADIUS related parameters of a wireless access point**

2. Service Modeling Definitions

2.1. ServiceType

The service is OPTIONAL as specified in
urn:schemas-upnp-org:device:*WLANAccessPointDevice:1*

The following service type identifies a service that is compliant with this template:
urn:schemas-upnp-org:service:*RadiusClient:1*

This service does not support the QueryStateVariable action.

2.2. State Variables

Table 1 shows all the state variables of RadiusClient service.

Table 1: State Variables

Variable Name	Req. or Opt.[1]	Data Type	Allowed Value	Default Value[2]	Eng. Units
NumberOfAuthServerEntries	R	ui2	>=0	0	N/A
AuthServerIPAddress	R	String	IP Address, <= 32 char	Empty String	N/A
AuthServerPortNumber	R	ui2	Between 1 and 65535 inclusive	0	N/A
AuthServerSharedSecret	R	String	Shared Secret, <= 128 char	Empty String	N/A
Non-standard state variables implemented by an UPnP device vendor go here.	*X*	*TBD*	*TBD*	*TBD*	*TBD*

[1] R = Required, O = Optional, X = Non-standard.

[2] Values listed in this column are required. To specify standard optional values or to delegate assignment of values to the vendor, you must reference a specific instance from the appropriate table below.

2.2.1. NumberOfAuthServerEntries

This variable indicates the number of Authentication Server entries (number of elements in the array) configured for this access point. The access point will attempt authentication with the authentication servers listed in the array in order. This variable is read/write and is evented.

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

2.2.2. AuthServerIPAddress

This variable is an IPv4 or IPv6 address of the Authentication Server, such as a RADIUS Server, for 802.1x-based Authentication.

2.2.3. AuthServerPortNumber

This variable is the port number (such as 1645 or 1812 for RADIUS) of the Authentication Server, such as a RADIUS Server, for EAP-based Authentication. This variable is read/write.

2.2.4. AuthServerSharedSecret

This variable is a string that represents the password in plain text for the access point to authenticate into the Authentication Server, such as a Radius Server, for EAP-based Authentication. This variable is read/write.

2.3. Eventing and Moderation

Table 2: Event Moderation

Variable Name	Evented	Moderated Event	Max Event Rate[1]	Logical Combination	Min Delta per Event[2]
NumberOfAuthServerEntries	Yes	No	N/A	N/A	N/A
Non-standard state variables implemented by an UPnP device vendor go here.	*TBD*	*TBD*	*TBD*	*TBD*	*TBD*

[1] Determined by N, where Rate = (Event)/(N secs).
[2] (N) * (allowedValueRange Step).

2.3.1. Event Model

Only one state variable of the *RadiusClient* service is evented:

NumberOfAuthServerEntries: This state variable event helps keep the client's authentication server list synchronized with the authentication server list maintained at the AP device.

None of the events are moderated.

2.4. Actions

Table 3 lists the required and optional actions for the UPnP AP device. This is followed by detailed information about these actions, including short descriptions of the actions, the effects of the actions on state variables, and error codes defined by the actions.

Securing UPnP actions in this service is optional but strongly recommended, using UPnP security protocols as defined by UPnP Security working group. If the AP implements security for UPnP actions, Table 3 indicates the actions that MUST be secure. The others may be implemented as secure or open. Secure actions MUST be protected for both confidentiality and integrity.

Access permissions will be inherited from the containing device (e.g., *WLANAccessPointDevice*).

Table 3: Actions

Name	Secure or Open*	Req. or Opt.
GetGenericAuthServerEntry	S	R
GetSpecificAuthServerEntry	S	R

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

Name	Secure or Open*	Req. or Opt.
AddAuthServerEntry	S	R
DeleteAuthServerEntry	S	R
FactoryDefaultReset	S	R
ResetAuthentication	S	R

[1] R = Required, O = Optional, X = Non-standard.

* This column is relevant if DeviceSecurity service is present in the container device

2.4.1. GetGenericAuthServerEntry

This action retrieves Authentication Server Entries one entry at a time. Control points can call this action with an incrementing array index until no more entries are found on the gateway. If NumberOfAuthServerEntries is updated during a call, the process may have to start over. Entries in the array are contiguous. As entries are deleted, the array is compacted, and the evented variable NumberOfAuthServerEntries is decremented. Authentication Server Entries are logically stored as an array on the AP and retrieved using an array index ranging from 0 to NumberOfAuthServerEntries – 1.

2.4.1.1. Arguments

Table 4: Arguments for GetGenericAuthServerEntry

Argument	Direction	relatedStateVariable
NewAuthServerIndex	IN	NumberOfAuthServerEntries
NewAuthServerIPAddress	OUT	AuthServerIPAddress
NewAuthServerPortNumber	OUT	AuthServerPortNumber
NewAuthServerSharedSecret	OUT	AuthServerSharedSecret

2.4.1.2. Dependency on State (if any)

2.4.1.3. Effect on State (if any)

2.4.1.4. Errors

errorCode	errorDescription	Description
402	Invalid Args	See UPnP Device Architecture section on Control
713	InvalidIndex	The specified array index is out of bounds

2.4.2. GetSpecificAuthServerEntry

This action retrieves the Authentication Server Entry for a specified {address, port} combination.

2.4.2.1. Arguments

Table 5: Arguments for GetSpecificAuthServerEntry

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

Argument	Direction	relatedStateVariable
NewAuthServerIPAddress	IN	AuthServerIPAddress
NewAuthServerPortNumber	IN	AuthServerPortNumber
NewAuthServerSharedSecret	OUT	AuthServerSharedSecret

2.4.2.2. Dependency on State (if any)

2.4.2.3. Effect on State (if any)

2.4.2.4. Errors

errorCode	errorDescription	Description
402	Invalid Args	See UPnP Device Architecture section on Control
714	NoSuchEntryInArray	The specified values of AuthServerIPAddress and AuthServerPortNumber combination does not exist in the array

2.4.3. AddAuthServerEntry

This action creates a new authentication server entry in the Authentication server list.

2.4.3.1. Arguments

Table 6: Arguments for AddAuthServerEntry

Argument	Direction	relatedStateVariable
NewAuthServerIP	IN	AuthServerIPAddress
NewAuthServerPortNumber	IN	AuthServerPortNumber
NewAuthServerSharedSecret	IN	AuthServerSharedSecret

2.4.3.2. Dependency on State (if any)

2.4.3.3. Effect on State (if any)

2.4.3.4. Errors

errorCode	errorDescription	Description
402	Invalid Args	See UPnP Device Architecture section on Control
701	AlreadyHaveAuthenticationServerEntry	The specified server entry is already present in the authentication server entry this happen when ip,port are same, but different shared secret

--`,,```,,,,````-`-`,,`,,`,`,,`---

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

2.4.4. DeleteAuthServerEntry

This action deletes the existing authentication server entry from the authentication server list. The authentication server entry is identified using authentication server IP address and port number.

2.4.4.1. Arguments

Table 7: Arguments for DeleteAuthServerEntry

Argument	Direction	relatedStateVariable
NewAuthServerIPAddress	IN	AuthServerIPAddress
NewAuthServerPortNumber	IN	AuthServerPortNumber

2.4.4.2. Dependency on State (if any)

2.4.4.3. Effect on State (if any)

2.4.4.4. Errors

errorCode	errorDescription	Description
402	Invalid Args	See UPnP Device Architecture section on Control
714	NoSuchEntryInArray	The specified values of AuthServerIPAddress and AuthServerPortNumber combination does not exist in the array

2.4.5. FactoryDefaultReset

This action resets all the state variables of the *RadiusClient* service to their factory default settings. It will remove all the radius server entries. This action also resets all the wireless sessions that were authenticated using radius server.

This action must be invoked internally if the control point calls FactoryDefaultReset action of the *DeviceSecurity* (or *WLANConfiguration* service if this service resides in the AP device), whereas vice versa is not true i.e., resetting this service will not invoke the DeviceSecurity reset (or *WLANConfiguration* reset).

2.4.5.1. Arguments

None

2.4.5.2. Dependency on State (if any)

2.4.5.3. Effect on State (if any)

2.4.5.4. Errors

errorCode	errorDescription	Description
402	Invalid Args	See UPnP Device Architecture section on Control

2.4.6. ResetAuthentication

This action resets all wireless stations that were authenticated via the RADIUS server.

--`,,```,,,,````-`-`,,`,,`,`,,`---

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

This action must be invoked internally if the control point calls ResetAuthentication action of the *WLANConfiguration* service if RadiusClient service resides in the AP device, whereas vice versa is not true.

2.4.6.1. Arguments

None

2.4.6.2. Dependency on State (if any)

2.4.6.3. Effect on State (if any)

2.4.6.4. Errors

errorCode	errorDescription	Description
402	Invalid Args	See UPnP Device Architecture section on Control

2.4.7. Non-Standard Actions Implemented by a UPnP Device Vendor

To facilitate certification, non-standard actions implemented by UPnP device vendors should be included in this service template. The UPnP Device Architecture lists naming requirements for non-standard actions (see the section on Description).

2.4.8. Common Error Codes

The following table lists error codes common to actions for this service type. If an action results in multiple errors, the most specific error should be returned.

Table 8: Common Error Codes

ErrorCode	errorDescription	Description
401	Invalid Action	See UPnP Device Architecture section on Control
402	Invalid Args	See UPnP Device Architecture section on Control
404	Invalid Var	See UPnP Device Architecture section on Control
501	Action Failed	See UPnP Device Architecture section on Control
600-699	TBD	Common action errors. Defined by UPnP Forum Technical Committee
701-799		Common action errors defined by the UPnP Forum working committees
800-899	*TBD*	*(Specified by UPnP device vendor)*

2.5. Theory of Operation

2.5.1. Operation of the RADIUS Client

An AP enabled with UPnP technology may maintain the list of remote authentication (RADIUS) servers for EAP authentication. This list can be updated by the control points. The AP device may also have the capability to run the authentication server locally. The AP device will pick an authentication server from the authentication server list in the order they have been added to the list.

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

3. XML Service Description

```
<?xml version="1.0"?>
<scpd xmlns="urn:schemas-upnp-org:service-1-0">
    <specVersion>
        <major>1</major>
        <minor>0</minor>
    </specVersion>
    <actionList>
        <action>
            <name>GetGenericAuthServerEntry</name>
            <argumentList>
                <argument>
                    <name>NewAuthServerIndex</name>
                    <direction>in</direction>
  <relatedStateVariable>NumberOfAuthServerEntries</relatedStateVariable>
                </argument>
                <argument>
                    <name>NewAuthServerIPAddress</name>
                    <direction>out</direction>
  <relatedStateVariable>AuthServerIPAddress</relatedStateVariable>
                </argument>
                <argument>
                    <name>NewAuthServerPortNumber</name>
                    <direction>out</direction>
  <relatedStateVariable>AuthServerPortNumber</relatedStateVariable>
                </argument>
                <argument>
                    <name>NewAuthServerSharedSecret</name>
                    <direction>out</direction>
  <relatedStateVariable>AuthServerSharedSecret</relatedStateVariable>
                </argument>
            </argumentList>
        </action>
        <action>
            <name>GetSpecificAuthServerEntry</name>
            <argumentList>
                <argument>
                    <name>NewAuthServerIPAddress</name>
                    <direction>in</direction>
  <relatedStateVariable>AuthServerIPAddress</relatedStateVariable>
                </argument>
                <argument>
                    <name>NewAuthServerPortNumber</name>
                    <direction>in</direction>
  <relatedStateVariable>AuthServerPortNumber</relatedStateVariable>
                </argument>
                <argument>
                    <name>NewAuthServerSharedSecret</name>
                    <direction>out</direction>
  <relatedStateVariable>AuthServerSharedSecret</relatedStateVariable>
                </argument>
            </argumentList>
        </action>
        <action>
            <name>AddAuthServerEntry</name>
            <argumentList>
                <argument>
                    <name>NewAuthServerIPAddress</name>
                    <direction>in</direction>
  <relatedStateVariable>AuthServerIPAddress</relatedStateVariable>
                </argument>
                <argument>
                    <name>NewAuthServerPortNumber</name>
                    <direction>in</direction>
  <relatedStateVariable>AuthServerPortNumber</relatedStateVariable>
                </argument>
                <argument>
                    <name>NewAuthServerSharedSecret</name>
                    <direction>in</direction>
  <relatedStateVariable>AuthServerSharedSecret</relatedStateVariable>
                </argument>
            </argumentList>
        </action>
        <action>
            <name>DeleteAuthServerEntry</name>
            <argumentList>
                <argument>
                    <name>NewAuthServerIPAddress</name>
                    <direction>in</direction>
  <relatedStateVariable>AuthServerIPAddress</relatedStateVariable>
```

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

```
                </argument>
                <argument>
                    <name>NewAuthServerPortNumber</name>
                    <direction>in</direction>
  <relatedStateVariable>AuthServerPortNumber</relatedStateVariable>
                </argument>
            </argumentList>
        </action>
        <action>
            <name>FactoryDefaultReset</name>
        </action>
        <action>
            <name>ResetAuthentication</name>
        </action>
    </actionList>
    <serviceStateTable>
        <stateVariable sendEvents="yes">
            <name>NumberOfAuthServerEntries</name>
            <dataType>ui2</dataType>
        </stateVariable>
        <stateVariable sendEvents="no">
            <name>AuthServerIPAddress</name>
            <dataType>string</dataType>
        </stateVariable>
        <stateVariable sendEvents="no">
            <name>AuthServerPortNumber</name>
            <dataType>ui2</dataType>
        </stateVariable>
        <stateVariable sendEvents="no">
            <name>AuthServerSharedSecret</name>
            <dataType>string</dataType>
        </stateVariable>
    </serviceStateTable>
</scpd>
```

--`,,```,,,,````-`-`,,`,,`,`,,`---

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

4. Test

No semantic tests have been defined for this service..

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS Not for Resale

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS
Not for Resale

--`,,```,,,,````-`-`,,`,,`,`,,`---

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS

Not for Resale

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

3, rue de Varembé
PO Box 131
CH-1211 Geneva 20
Switzerland

Tel: + 41 22 919 02 11
Fax: + 41 22 919 03 00
info@iec.ch
www.iec.ch

Copyright International Organization for Standardization
Provided by IHS under license with ISO
No reproduction or networking permitted without license from IHS

Not for Resale